

LM124/LM224/LM324/LM2902

Low Power Quad Operational Amplifiers

General Description

The LM124 series consists of four independent, high gain, internally frequency compensated operational amplifiers which were designed specifically to operate from a single power supply over a wide range of voltages. Operation from split power supplies is also possible and the low power supply current drain is independent of the magnitude of the power supply voltage.

Application areas include transducer amplifiers, DC gain blocks and all the conventional op amp circuits which now can be more easily implemented in single power supply systems. For example, the LM124 series can be directly operated off of the standard +5V power supply voltage which is used in digital systems and will easily provide the required interface electronics without requiring the additional $\pm 15V$ power supplies.

Unique Characteristics

- In the linear mode the input common-mode voltage range includes ground and the output voltage can also swing to ground, even though operated from only a single power supply voltage
- The unity gain cross frequency is temperature compensated
- The input bias current is also temperature compensated


Advantages

- Eliminates need for dual supplies
- Four internally compensated op amps in a single package
- Allows directly sensing near GND and V_{OUT} also goes to GND
- Compatible with all forms of logic
- Power drain suitable for battery operation

Features

- Internally frequency compensated for unity gain
- Large DC voltage gain 100 dB
- Wide bandwidth (unity gain) 1 MHz (temperature compensated)
- Wide power supply range:
 - Single supply 3V to 32V
 - or dual supplies $\pm 1.5V$ to $\pm 16V$
- Very low supply current drain (700 μA)—essentially independent of supply voltage
- Low input biasing current 45 nA (temperature compensated)
- Low input offset voltage 2 mV and offset current 5 nA
- Input common-mode voltage range includes ground
- Differential input voltage range equal to the power supply voltage
- Large output voltage swing 0V to $V^+ - 1.5V$

Connection Diagram




Top View


Order Number LM124J, LM124AJ, LM124J/883**,
LM124AJ/883*, LM224J, LM224AJ, LM324J, LM324M,
LM324AM, LM2902M, LM324N, LM324AN or LM2902N
See NS Package Number J14A, M14A or N14A

*LM124A available per JM38510/11006

**LM124 available per JM38510/11005



Order Number LM124AE/883 or LM124E/883
See NS Package Number E20A



Order Number LM124AW/883 or LM124W/883
See NS Package Number W14B

Absolute Maximum Ratings

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications. (Note 9)

		LM124/LM224/LM324		LM2902		LM124/LM224/LM324		LM124A/LM224A/LM324A		LM2902		LM124/LM224/LM324		LM124A/LM224A/LM324A		LM2902	
Supply Voltage, V^+		32V		26V		26V		26V		26V		Storage Temperature Range		-65°C to +150°C		-65°C to +150°C	
Differential Input Voltage		32V		26V		26V		26V		26V		Lead Temperature (Soldering, 10 seconds)		260°C		260°C	
Input Voltage		-0.3V to +32V		-0.3V to +26V		-0.3V to +26V		-0.3V to +26V		-0.3V to +26V		Soldering Information		260°C		260°C	
Input Current		50 mA		50 mA		50 mA		50 mA		50 mA		Dual-In-Line Package		260°C		260°C	
Power Dissipation (Note 3)		1130 mW		1130 mW		1130 mW		1130 mW		1130 mW		Soldering (10 seconds)		215°C		215°C	
Molded DIP		1260 mW		1260 mW		1260 mW		1260 mW		1260 mW		Small Outline Package		220°C		220°C	
Cavity DIP		800 mW		800 mW		800 mW		800 mW		800 mW		Vapor Phase (60 seconds)		215°C		215°C	
Small Outline Package		Continuous		Continuous		Continuous		Continuous		Continuous		Infrared (15 seconds)		220°C		220°C	
Output Short-Circuit to GND		0°C to +70°C		0°C to +70°C		0°C to +70°C		0°C to +70°C		0°C to +70°C		See AN-450 "Surface Mounting Methods and Their Effect on Product Reliability" for other methods of soldering surface mount devices.		250V		250V	
(One Amplifier) (Note 2)		-25°C to +85°C		-25°C to +85°C		-25°C to +85°C		-25°C to +85°C		-25°C to +85°C		ESD Tolerance (Note 10)		250V		250V	
Operating Temperature Range		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A	
LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A		LM324/LM324A	
LM224/LM224A		LM224/LM224A		LM224/LM224A		LM224/LM224A		LM224/LM224A		LM224/LM224A		LM224/LM224A		LM224/LM224A		LM224/LM224A	
LM124/LM124A		LM124/LM124A		LM124/LM124A		LM124/LM124A		LM124/LM124A		LM124/LM124A		LM124/LM124A		LM124/LM124A		LM124/LM124A	

Electrical Characteristics $V^+ = +5.0V$, (Note 4), unless otherwise stated

Parameter	Conditions	LM124A		LM224A		LM324A		LM124/LM224		LM324		LM2902		Units	
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	Min	Max
Input Offset Voltage	(Note 5) $T_A = 25^\circ C$	1	2		1	3		2	5	7	2	7	7	mV	
Input Bias Current (Note 6)	$I_{IN(+)} \text{ or } I_{IN(-)}; V_{CM} = 0V, T_A = 25^\circ C$	20	50		40	80		45	150	250	45	250	250	nA	
Input Offset Current	$I_{IN(+)} - I_{IN(-)}; V_{CM} = 0V, T_A = 25^\circ C$	2	10		2	15		3	30	50	5	50	50	nA	
Input Common-Mode Voltage Range (Note 7)	$V^+ = 30V, (LM2902, V^+ = 26V), T_A = 25^\circ C$	0	$V^+ - 1.5$	0	$V^+ - 1.5$	0	$V^+ - 1.5$	0	$V^+ - 1.5$	0	$V^+ - 1.5$	0	$V^+ - 1.5$	V	
Supply Current	Over Full Temperature Range $R_L = \infty$ On All Op Amps $V^+ = 30V (LM2902, V^+ = 26V)$ $V^+ = 5V$	1.5	3		1.5	3		1.5	3	1.5	3	1.5	3	mA	
		0.7	1.2		0.7	1.2		0.7	1.2	0.7	1.2	0.7	1.2		
Large Signal Voltage Gain	$V^+ = 15V, R_L \geq 2k\Omega, (V_O = 1V \text{ to } 11V), T_A = 25^\circ C$	50	100		50	100		50	100	25	100	25	100	V/mV	
Common-Mode Rejection Ratio	DC, $V_{CM} = 0V$ to $V^+ - 1.5V, T_A = 25^\circ C$	70	85		70	85		70	85	65	85	50	70	dB	
Power Supply Rejection Ratio	$V^+ = 5V$ to $30V (LM2902, V^+ = 5V \text{ to } 26V), T_A = 25^\circ C$	65	100		65	100		65	100	65	100	50	100	dB	

Electrical Characteristics $V^+ = +5.0V$ (Note 4) unless otherwise stated (Continued)

Parameter	Conditions	LM124A		LM224A		LM324A		LM124/LM224		LM324		LM2902		Units
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	
Amplifier-to-Amplifier Coupling (Note 8)	$f = 1 \text{ kHz}$ to 20 kHz , $T_A = 25^\circ\text{C}$ (Input Referred)		-120			-120			-120			-120		dB
Output Current	Source		20	40		20	40		20	40		20	40	
		$V_{IN}^+ = 1V, V_{IN}^- = 0V, V^+ = 15V, V_O = 2V, T_A = 25^\circ\text{C}$												
	Sink		10	20		10	20		10	20		10	20	
		$V_{IN}^- = 1V, V_{IN}^+ = 0V, V^+ = 15V, V_O = 2V, T_A = 25^\circ\text{C}$												
Short Circuit to Ground			12	50		12	50		12	50		12	50	
		$V_{IN}^- = 1V, V_{IN}^+ = 0V, V^+ = 15V, V_O = 200 \text{ mV}, T_A = 25^\circ\text{C}$												
			40	60		40	60		40	60		40	60	
		(Note 2) $V^+ = 15V, T_A = 25^\circ\text{C}$												
Input Offset Voltage	(Note 5)		4			4			5			9		mV
Input Offset Voltage Drift	$R_S = 0\Omega$		7	20		7	20		7	30		7		$\mu\text{V}/^\circ\text{C}$
Input Offset Current	$I_{IN}(+) - I_{IN}(-), V_{CM} = 0V$		30			30			75			150	45	nA
Input Offset Current Drift	$R_S = 0\Omega$		10	200		10	200		10	300		10		$\text{pA}/^\circ\text{C}$
Input Bias Current	$I_{IN}(+) \text{ or } I_{IN}(-)$		40	100		40	100		40	200		40	500	nA
Input Common-Mode Voltage Range (Note 7)	$V^+ = +30V$ (LM2902, $V^+ = 26V$)	0	$V^+ - 2$	0	$V^+ - 2$	0	$V^+ - 2$	0	$V^+ - 2$	0	$V^+ - 2$	0	$V^+ - 2$	V
Large Signal Voltage Gain	$V^+ = +15V$ (V_O Swing = $1V$ to $11V$) $R_L \geq 2 \text{ k}\Omega$	25		25		15		25		15		15		V/mV
Output Voltage Swing	V_{OH}		26			26			26			22		V
		$R_L = 2 \text{ k}\Omega$												
	V_{OL}		27	28		27	28		27	28		23	24	
		$R_L = 10 \text{ k}\Omega$												
		$V^+ = 5V, R_L = 10 \text{ k}\Omega$												
		5	20		5	20		5	20		5	20		mV

Electrical Characteristics $V^+ = +5.0V$ (Note 4) unless otherwise stated (Continued)

Parameter		Conditions	LM124A		LM224A		LM324A		LM124/LM224		LM324		LM2902		Units
			Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	
Output Current	Source	$V_O = 2V$ $V_{IN}^+ = +1V$, $V_{IN}^- = 0V$, $V^+ = 15V$	10	20		10	20		10	20		10	20		mA
	Sink	$V_{IN}^+ = +1V$, $V_{IN}^- = 0V$, $V^+ = 15V$	10	15		5	8		5	8		5	8		

Note 1: For operating at high temperatures, the LM324/LM324A/LM2902 must be derated based on a $+125^\circ C$ maximum junction temperature and a thermal resistance of $88^\circ C/W$ which applies for the device soldered in a printed circuit board, operating in a still air ambient. The LM224/LM224A and LM124/LM124A can be derated based on a $+150^\circ C$ maximum junction temperature. The dissipation is the total of all four amplifiers—use external resistors, where possible, to allow the amplifier to saturate of to reduce the power which is dissipated in the integrated circuit.

Note 2: Short circuits from the output to V^+ can cause excessive heating and eventual destruction. When considering short circuits can exceed the power dissipation ratings and cause eventual destruction.

Note 3: This input current will only exist when the voltage at any of the input leads is driven negative. It is due to the collector-base junction of the input PNP transistors becoming forward biased and thereby acting as input diode clamps. In addition to this diode action, there is also lateral NPN parasitic transistor action on the IC chip. This transistor action can cause the output voltages of the op amps to go to the V^+ voltage level (or to ground for a large overdrive) for the time duration that an input is driven negative. This is not destructive and normal output states will re-establish when the input voltage, which was negative, again returns to a value greater than $-0.3V$ (at $25^\circ C$).

Note 4: These specifications are limited to $-55^\circ C \leq T_A \leq +125^\circ C$ for the LM124/LM124A. With the LM224/LM224A, all temperature specifications are limited to $-25^\circ C \leq T_A \leq +85^\circ C$, the LM324/LM324A temperature specifications are limited to $0^\circ C \leq T_A \leq +70^\circ C$, and the LM2902 specifications are limited to $-40^\circ C \leq T_A \leq +85^\circ C$.

Note 5: $V_O = 1.4V$, $R_S = 0\Omega$ with V^+ from $5V$ to $30V$; and over the full input common-mode range ($0V$ to $V^+ - 1.5V$) for LM2902, V^+ from $5V$ to $26V$.


Note 6: The direction of the input current is out of the IC due to the PNP input stage. This current is essentially constant, independent of the state of the output so no loading change exists on the input lines.

Note 7: The input common-mode voltage of either input signal voltage should not be allowed to go negative by more than $0.3V$ (at $25^\circ C$). The upper end of the common-mode voltage range is $V^+ - 1.5V$ (at $25^\circ C$), but either or both inputs can go to $+32V$ without damage ($+1.26V$ for LM2902), independent of the magnitude of V^+ .













Note 8: Refer to RETS124AX for LM124A military specifications and refer to RETS124X for LM124 military specifications.

Note 10: Human body model, $1.5\text{ k}\Omega$ in series with 100 pF .

Schematic Diagram (Each Amplifier)





Typical Performance Characteristics



TL/H/9299-3

Typical Performance Characteristics (LM2902 only)



TL/H/9299-4

Application Hints

The LM124 series are op amps which operate with only a single power supply voltage, have true-differential inputs, and remain in the linear mode with an input common-mode voltage of 0 V_{DC}. These amplifiers operate over a wide range of power supply voltage with little change in performance characteristics. At 25°C amplifier operation is possible down to a minimum supply voltage of 2.3 V_{DC}.

The pinouts of the package have been designed to simplify PC board layouts. Inverting inputs are adjacent to outputs for all of the amplifiers and the outputs have also been placed at the corners of the package (pins 1, 7, 8, and 14).

Precautions should be taken to insure that the power supply for the integrated circuit never becomes reversed in polarity or that the unit is not inadvertently installed backwards in a test socket as an unlimited current surge through the resulting forward diode within the IC could cause fusing of the internal conductors and result in a destroyed unit.

Large differential input voltages can be easily accommodated and, as input differential voltage protection diodes are not needed, no large input currents result from large differential input voltages. The differential input voltage may be larger than V⁺ without damaging the device. Protection should be provided to prevent the input voltages from going negative more than -0.3 V_{DC} (at 25°C). An input clamp diode with a resistor to the IC input terminal can be used.

To reduce the power supply drain, the amplifiers have a class A output stage for small signal levels which converts to class B in a large signal mode. This allows the amplifiers to both source and sink large output currents. Therefore both NPN and PNP external current boost transistors can be used to extend the power capability of the basic amplifiers. The output voltage needs to raise approximately 1 diode drop above ground to bias the on-chip vertical PNP transistor for output current sinking applications.

For ac applications, where the load is capacitively coupled to the output of the amplifier, a resistor should be used, from the output of the amplifier to ground to increase the class A bias current and prevent crossover distortion.

Where the load is directly coupled, as in dc applications, there is no crossover distortion.

Capacitive loads which are applied directly to the output of the amplifier reduce the loop stability margin. Values of 50 pF can be accommodated using the worst-case non-inverting unity gain connection. Large closed loop gains or resistive isolation should be used if larger load capacitance must be driven by the amplifier.



The bias network of the LM124 establishes a drain current which is independent of the magnitude of the power supply voltage over the range of from 3 V_{DC} to 30 V_{DC}.

Output short circuits either to ground or to the positive power supply should be of short time duration. Units can be destroyed, not as a result of the short circuit current causing metal fusing, but rather due to the large increase in IC chip dissipation which will cause eventual failure due to excessive junction temperatures. Putting direct short-circuits on more than one amplifier at a time will increase the total IC power dissipation to destructive levels, if not properly protected with external dissipation limiting resistors in series with the output leads of the amplifiers. The larger value of output source current which is available at 25°C provides a larger output current capability at elevated temperatures (see typical performance characteristics) than a standard IC op amp.

The circuits presented in the section on typical applications emphasize operation on only a single power supply voltage. If complementary power supplies are available, all of the standard op amp circuits can be used. In general, introducing a pseudo-ground (a bias voltage reference of V⁺/2) will allow operation above and below this value in single power supply systems. Many application circuits are shown which take advantage of the wide input common-mode voltage range which includes ground. In most cases, input biasing is not required and input voltages which range to ground can easily be accommodated.


Typical Single-Supply Applications ($V^+ = 5.0 V_{DC}$)

Non-Inverting DC Gain ($0V$ Input = $0V$ Output)



TL/H/9299-5


DC Summing Amplifier ($V_{IN'S} \geq 0 V_{DC}$ and $V_O \geq V_{DC}$)



TL/H/9299-6


Where: $V_O = V_1 + V_2 - V_3 - V_4$
 $(V_1 + V_2) \geq (V_3 + V_4)$ to keep $V_O > 0 V_{DC}$

Power Amplifier




TL/H/9299-7

LED Driver



TL/H/9299-8


"BI-QUAD" RC Active Bandpass Filter



TL/H/9299-9


Typical Single-Supply Applications ($V^+ = 5.0 V_{DC}$) (Continued)

Fixed Current Sources




TL/H/9299-10

Lamp Driver




TL/H/9299-11

Current Monitor




TL/H/9299-12

Driving TTL




TL/H/9299-13

Voltage Follower



TL/H/9299-14


Pulse Generator



TL/H/9299-15


Typical Single-Supply Applications ($V^+ = 5.0 V_{DC}$) (Continued)

Squarewave Oscillator




TL/H/9299-16

Pulse Generator




TL/H/9299-17

High Compliance Current Sink




TL/H/9299-18

Low Drift Peak Detector




TL/H/9299-19

Comparator with Hysteresis



TL/H/9299-20


Ground Referencing a Differential Input Signal



TL/H/9299-21

Typical Single-Supply Applications ($V^+ = 5.0 V_{DC}$) (Continued)


Voltage Controlled Oscillator Circuit



TL/H/9299-22


*Wide control voltage range: $0 V_{DC} \leq V_C \leq 2 (V^+ - 1.5 V_{DC})$

Photo Voltaic-Cell Amplifier



TL/H/9299-23

AC Coupled Inverting Amplifier




$$A_v = \frac{R_i}{R_1} \text{ (As shown, } A_v = 10 \text{)}$$

TL/H/9299-24


Typical Single-Supply Applications ($V^+ = 5.0 V_{DC}$) (Continued)

AC Coupled Non-Inverting Amplifier




TL/H/9299-25

DC Coupled Low-Pass RC Active Filter



TL/H/9299-26


High Input Z, DC Differential Amplifier



TL/H/9299-27

Typical Single-Supply Applications ($V^+ = 5.0 V_{DC}$) (Continued)

High Input Z Adjustable-Gain DC Instrumentation Amplifier




If $R1 = R5$ & $R3 = R4 = R6 = R7$ (CMRR depends on match)

TL/H/9299-28

$$V_O = 1 + \frac{2R1}{R2} (V_2 - V_1)$$


As shown $V_O = 101 (V_2 - V_1)$

Using Symmetrical Amplifiers to Reduce Input Current (General Concept)



TL/H/9299-29

Bridge Current Amplifier




For $\delta \ll 1$ and $R_f \gg R$

$$V_O \approx V_{REF} \left(\frac{\delta}{2} \right) \frac{R_f}{R}$$

TL/H/9299-30

Typical Single-Supply Applications ($V^+ = 5.0\text{ V}_{\text{DC}}$) (Continued)

Bandpass Active Filter



TL/H/9299-31