



LM4935 Evaluation Package Instructions v1.3

National Semiconductor Audio

Table of Contents

Evaluation Package Contents.....	3
Software Installation Instructions.....	3
LM4935 Control Software.....	3
Hardware Installation Instructions.....	3
Powering up the LM4935 Demoboard.....	4
S/PDIF Receiver Operation.....	6
Interfacing with the LM4935 Digital Audio I/O.....	7
DC Volume Control.....	8
Headphone Output Configuration.....	9
High-Efficiency Loudspeaker Evaluation.....	10
3.5mm and 2.5mm Audio Jacks.....	11

Evaluation Package Contents:

LM4935 Demoboard
USB Interface Card
USB Cable
LM4935 Control Software

Software Installation Instructions (Windows 2000/NT/XP):

- 1) Unzip the LM4935 Setup 1_2.zip file to a specified folder.
- 2) Run setup.exe from the specified folder.
- 3) The LM4935 Control Software installation will begin.
- 4) Please refer to the readme.txt for further information.

LM4935 Control Software:

- 1) The LM4935 Control Software will operate only if the LM4935 Demoboard setup has been properly powered up and connected to the PC's USB port.
- 2) If there is no proper connection made, the LM4935 Control Software will not operate correctly.
- 3) If the LM4935 Demoboard setup is correct and the LM4935 control software loads normally, and then either the USB or power is disconnected, the LM4935 Control Software will indicate that there is a USB I/O error and will freeze up. Once the proper connection (USB or Power) has been re-established then the LM4935 Control Software will operate normally.
- 4) For more detail please refer to the LM4935 Control Software readme.txt file.

Hardware Installation Instructions:

- 1) Plug the USB Interface Card to the bottom side of the LM4935 Demoboard. The connection between the USB Interface Card and the LM4935 Demoboard is keyed in a way such that there is only one possible physical orientation between the two boards.
- 2) Attach one end of the USB cable to a free USB port on your PC and the other end to the USB Interface Card.
- 3) Run the LM4935.exe file. The LM4935 Control Software will run only if a proper USB connection exists from the PC to the demoboard and also if there is power supplied to the demoboard (see next section).

Powering up the LM4935 Demoboard:

- 1) The LM4935 Demoboard can be powered up through the USB Interface Card or through an external power supply.
- 2) Switch Y1 sets USB Power operation (USB POW) or External Power supply operation (EXT POW).




Fig. 1 Powering up the LM4935 Demoboard

- 3) When setting switch Y1 for USB Power operation, please make sure that all external power supply lines are disconnected from the banana connectors of the LM4935 Demoboard. When configured for USB Power operation, the LM4935 Demoboard does not require any external power supplies, as the LM4935 Demoboard draws its required power from the USB port.
- 4) During USB Power operation, DVDD and BBVDD is set to 3.3V. AVDD is set according to the position of the J1 jumper on the USB Interface Card. Placing the J1 jumper at the “5V” position will set AVDD to 5V. Placing the J1 jumper at the “ADJ” position sets AVDD to be either 3.8V or 3V depending on the LM4935 Control Software setting (default setting is 3.8V).
- 5) Jumper S11 shorts the digital power supply pin of the onboard CS8416 S/PDIF receiver to system DVDD of the LM4935 Demoboard. If there is an S/PDIF digital audio source available, then S11 must be closed to provide power to the S/PDIF receiver. S11 should be left open whenever the CS8416 is not needed, as this will isolate the LM4935 from the CS8416.

S11




Fig. 2 Powering up the S/PDIF Receiver

- 6) During External Power supply operation, the use of external power supplies is expected. There are dedicated banana jack inputs for BBVDD, DVDD, AVDD, AGND, and DGND located on the top of the demoboard to accommodate external power supply inputs. It is recommended to keep $AVDD \geq DVDD$. Please refer to the LM4935 datasheet for operating ranges.
- 7) On the LM4935 demoboard, the A_VDD and LS_VDD pins are tied to system AVDD. The PLL_VDD and D_VDD pins are tied to system DVDD.

S/PDIF Receiver Operation:

- 1) The CS8416 S/PDIF Receiver will only operate if DVDD or the voltage applied to the CS8416's digital power supply pin (via bottom pin of S11) is set between 3V to 3.6V.
- 2) After device power up, to ensure that the CS8416 has initialized correctly, it is recommended to RESET the CS8416. To RESET the CS8416, press and release the S13 button. RESET is also recommended after toggling between the MASTER/SLAVE operation of the S/PDIF receiver. A CS8416 RESET can help in instances whenever there is no audio output while using the S/PDIF audio input.
- 3) Set the position of switch S18 to toggle between the MASTER/SLAVE operation of the CS8416 S/PDIF receiver. To run the CS8416 as MASTER, set S18 to the "S/PDIF Receiver MASTER" position. To run the CS8416 as SLAVE, set S18 to the "S/PDIF Receiver SLAVE" position. MASTER/SLAVE operation of the LM4935 is set through the Interface Tab of the LM4935 Control Software. If the CS8416 is set to MASTER, then the LM4935 should be programmed to SLAVE, and vice versa.
- 4) The S/PDIF receiver can accept S/PDIF audio data through either an optical cable or digital coaxial cable. If using an optical cable, set the position of switch S12 to "OPTICAL". If using a digital coaxial cable (75 Ohm), set the position of S12 to "Coax".




Fig. 3 S/PDIF Receiver Operation

Interfacing with the LM4935's Digital Audio I/O:

- 1) The LM4935 can accept digital audio data from either the CS8416 S/PDIF receiver or from an external digital audio data source (such as the Audio Precision PSIA-2722).
- 2) Setting switch Y2 to the "int I2S" position connects the outputs of the CS8416 to the digital audio I/O of the LM4935. In the "intI2S" position, MCLK is generated from the output of the CS8416 and routed to the MCLK input of the LM4935.
- 3) Setting switch Y2 to the "ext I2S" position connects the JP1 (7x2) connector to the LM4935's digital audio interface. JP1 is a universal connector that can accept digital audio data and clocks from an external source such as the PSIA-2722. In the "extI2S" position, MCLK is expected from an external source (via pin1 of JP1) and is routed to the MCLK input of the LM4935.
- 4) Please refer to the silkscreen of the LM4935 Demoboard's JP1 connector for the correct pinout. When using the "extI2S" switch setting, the CS8416 is not needed and therefore should be disconnected from the system power supply by opening S11





Fig. 4 Interfacing with the LM4935's Digital Audio I/O

DC Volume Control:

- 1) Using the LM4935 Control Software, the user can select between implementing I2C/SPI volume control or DC Volume control. When using the DC Volume control, jumper S17 should be shorted. S17 connects the potentiometer to the VSAR1 input (JP14) of the LM4935. This allows the potentiometer to control the DC Volume of the LM4935.
- 2) Whenever an external voltage source is required to drive the VSAR1 input (JP14), it is recommended to open S17, to isolate the potentiometer from the system.



Headphone Output Configuration:

- 1) The LM4935 Demoboard supports two different headphone output configurations: Output-Capacitorless (OCL) and Single-ended Capacitively Coupled (SE).
- 2) Switch Y3 is used to switch between OCL and SE headphone output modes. When Y3 is placed in the “Headphone OCL” position, the headphone outputs are wired for OCL operation. When Y3 is placed in the “Headphone NON-OCL” position, the headphone outputs are wired for SE operation.
- 3) The LM4935 Control Software programs the LM4935 to be either in OCL mode or SE mode. It is important to match the software setting to the position of switch Y3 on the LM4935 Demoboard for correct operation.





Fig. 6 Headphone Output Configuration

High-Efficiency Loudspeaker Evaluation:

- 1) The LM4935 contains a filterless switching amplifier output designed to drive a mobile phone's handsfree loudspeaker.
- 2) Connector JP3 is used to directly access the switching amplifier's loudspeaker outputs. Connect any speaker load directly to JP3.
- 3) The LM4935 contains an LC measurement filter to filter out the switching artifacts of the switching amplifier outputs. This allows the user to analyze the loudspeaker's audio output signal without using any special external filters. The filtered loudspeaker audio output can be accessed through banana jacks JP24 or through header JP4.



3.5mm and 2.5mm Audio Jacks:

- 1) The LM4935 Demoboard can accommodate both 3.5mm and 2.5mm audio plugs with 3 or 4 wire type headphones/headsets.




Fig. 8 3.5mm and 2.5mm Audio Jacks

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2012, Texas Instruments Incorporated