

CHEMTRONICS®

Technical Data Sheet

TDS # CW9400

CircuitWorks® Lead-Free Flux Remover Pen

PRODUCT DESCRIPTION

CircuitWorks® Lead-Free Flux Remover Pen is designed specifically to remove flux used in Lead-Free applications. The Lead-Free Flux Remover Pen quickly cleans type R, RMA, and RA rosin flux residues as well as No Clean Fluxes containing both organic and synthetic no clean fluxes.

- Removes rosin and no clean flux residues
- Can be used after soldering with lead-free or Tin/Lead solders
- Penetrates hard to reach areas
- Pen dispenser provides controlled and exact application of cleaning solvent
- Removes ionic and non-ionic residues
- Excellent material compatibility
- Fast drying
- RoHS compliant

TYPICAL APPLICATIONS

CircuitWorks® Lead-Free Flux Remover Pen removes flux residues on:

- Printed Circuit Boards
- Chip Carriers
- Heat Sinks
- Surface Mount Device Pads
- Switches
- Sockets

TYPICAL PRODUCT DATA AND PHYSICAL PROPERTIES

Lead-Free Flux Remover Pen - CW9400	
Flash Point (TCC)	102 °F (39 °C)
Vapor Density (air=1)	> 1
Surface Tension	17.7 dyne/cm
Appearance	Clear Liquid
Odor	Mild
Shelflife	5 years

CircuitWorks® Lead-Free Flux Remover Pen is generally compatible with most materials used in the electronics industry. As with any cleaning agent, material compatibility should be determined on a non-critical area prior to use.

Hold pen vertically and briefly depress tip to start liquid flow. Rub pen tip over residues on surface to be cleaned. Wipe area clean with a ControlWipe™ dry wipe to remove loosened residues.

CW9400 9 gm (0.32 oz)

MANUFACTURED BY:
ITW CHEMTRONICS
8125 COBB CENTER DRIVE
KENNESAW, GA 30152
1-770-424-4888

Chemtronics® and CircuitWorks® are registered trademarks of ITW Chemtronics. All rights reserved. ControlWipe™ is a trademark of ITW Chemtronics. All rights reserved.

DISTRIBUTED BY: