

BLDC Motor Control Kit including ATA6833/ATA6834 and ATmega32M1

Getting Started

1. Kit Contents

- 1 BLDC Motor Application Board: ATA6833/ATA6834-DK1
- 1 Display Controller Board: ATA6833/ATA6834-DK2
- 1 Brushless DC Motor Ref: FL42BLS01-001 (3 Phases, 8 Poles, 12 VDC)
- 1 Getting Started Note
- 1 CD-ROM Atmel Products Technical Library

2. Prepare Connections

1. Connect the Motor Application Board X5 to the Display Controller Board X5.
2. Connect the motor as indicated in [Table 2-1](#), motor phases (3 thick wires on pin 1 to 3) and Hall sensors (5 thin wires on pin 4 to 8).
3. Connect the Power Supply 12V to X1.

Table 2-1. BLDC Application Board Wires

Pin Number	Signal Names on PCB Bottom	Function	Motor Wire	Remark	Direction
1	Ph_A	Motor Phase A	Yellow	Thick wire	Output
2	Ph_B	Motor Phase B	Red	Thick wire	Output
3	Ph_C	Motor Phase C	Black	Thick wire	Output
4	5V	Power 5V	Red	Thin wire	Output
5	HALL_A	Hall A	Blue	Thin wire	Input
6	HALL_B	Hall B	Green	Thin wire	Input
7	HALL_C	Hall C	White	Thin wire	Input
8	GND	Power GND	Black	Thin wire	Output



**ATA6833/
ATA6834-DK**

Application Note



3. Operating Menu

3.1 Start-up

To start the system, wake up either with negative edge at input pin LIN on the motor board or positive edge on EN2 by pressing EN2 button on the motor board. The Start-up Screen is displayed (see [Figure 3-1](#)).

Figure 3-1. Start-up Screen



The first line shows the software version. The second line shows the wake-up source, either LIN or EN2. The third line shows the status of the temperature comparator. The fourth line shows the operating voltage, either 5.0V or 3.3V. In the system version 1.0, only 5V operating voltage is supported.

3.2 Intro Screen

After 3 seconds, the Intro Screen is displayed (see [Figure 3-2](#)).

Figure 3-2. Intro Screen



3.3 Operation Screen


Touch the screen with a touch pen or finger to display the Operation Screen.

The Operation screen is divided in three parts: the top and bottom lines each contain 4 function buttons, the middle part shows the speed and duty cycle values.

Press the start button in the lower right corner to start the motor.

Decay means, during duty off cycle, the decay current flows through the counterpart switch to the by PWM affected switch. The decay mode is only available in High or Low-side commutation mode but not in the simultaneous High and Low-side commutation mode.

Figure 3-3. Operating Screen





Headquarters

Atmel Corporation
2325 Orchard Parkway
San Jose, CA 95131
USA
Tel: 1(408) 441-0311
Fax: 1(408) 487-2600

International

Atmel Asia
Unit 1-5 & 16, 19/F
BEA Tower, Millennium City 5
418 Kwun Tong Road
Kwun Tong, Kowloon
Hong Kong
Tel: (852) 2245-6100
Fax: (852) 2722-1369

Atmel Europe
Le Krebs
8, Rue Jean-Pierre Timbaud
BP 309
78054
Saint-Quentin-en-Yvelines Cedex
France
Tel: (33) 1-30-60-70-00
Fax: (33) 1-30-60-71-11

Atmel Japan
9F, Tonetsu Shinkawa Bldg.
1-24-8 Shinkawa
Chuo-ku, Tokyo 104-0033
Japan
Tel: (81) 3-3523-3551
Fax: (81) 3-3523-7581

Product Contact

Web Site
www.atmel.com

Technical Support
auto_control@atmel.com

Sales Contact
www.atmel.com/contacts

Literature Requests
www.atmel.com/literature

Disclaimer: The information in this document is provided in connection with Atmel products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Atmel products. **EXCEPT AS SET FORTH IN ATMEL'S TERMS AND CONDITIONS OF SALE LOCATED ON ATMEL'S WEB SITE, ATMEL ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL ATMEL BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION, OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF ATMEL HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.** Atmel makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Atmel does not make any commitment to update the information contained herein. Unless specifically provided otherwise, Atmel products are not suitable for, and shall not be used in, automotive applications. Atmel's products are not intended, authorized, or warranted for use as components in applications intended to support or sustain life.

© 2008 Atmel Corporation. All rights reserved. Atmel®, Atmel logo and combinations thereof, and others are registered trademarks or trademarks of Atmel Corporation or its subsidiaries. Other terms and product names may be trademarks of others.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Atmel:](#)

[ATA6834-DK](#)