

# Switch-mode NPN Bipolar Power Transistor

For Switching Power Supply Applications

## MJE13007

The MJE13007 is designed for high-voltage, high-speed power switching inductive circuits where fall time is critical. It is particularly suited for 115 and 220 V switch-mode applications such as Switching Regulators, Inverters, Motor Controls, Solenoid/Relay drivers and Deflection circuits.

### Features

- SOA and Switching Applications Information
- Standard TO-220
- These Devices are Pb-Free and are RoHS Compliant\*
- Complementary to the MJE5850 through MJE5852 Series

### MAXIMUM RATINGS

| Rating                                                                                 | Symbol         | Value      | Unit                     |
|----------------------------------------------------------------------------------------|----------------|------------|--------------------------|
| Collector-Emitter Sustaining Voltage                                                   | $V_{CEO}$      | 400        | Vdc                      |
| Collector-Base Breakdown Voltage                                                       | $V_{CES}$      | 700        | Vdc                      |
| Emitter-Base Voltage                                                                   | $V_{EBO}$      | 9.0        | Vdc                      |
| Collector Current – Continuous                                                         | $I_C$          | 8.0        | Adc                      |
| Collector Current – Peak (Note 1)                                                      | $I_{CM}$       | 16         | Adc                      |
| Base Current – Continuous                                                              | $I_B$          | 4.0        | Adc                      |
| Base Current – Peak (Note 1)                                                           | $I_{BM}$       | 8.0        | Adc                      |
| Emitter Current – Continuous                                                           | $I_E$          | 12         | Adc                      |
| Emitter Current – Peak (Note 1)                                                        | $I_{EM}$       | 24         | Adc                      |
| Total Device Dissipation @ $T_C = 25^\circ\text{C}$<br>Derate above $25^\circ\text{C}$ | $P_D$          | 80<br>0.64 | W<br>W/ $^\circ\text{C}$ |
| Operating and Storage Temperature                                                      | $T_J, T_{stg}$ | -65 to 150 | $^\circ\text{C}$         |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Pulse Test: Pulse Width = 5 ms, Duty Cycle  $\leq 10\%$ .



### THERMAL CHARACTERISTICS

| Characteristics                                                                 | Symbol          | Max  | Unit               |
|---------------------------------------------------------------------------------|-----------------|------|--------------------|
| Thermal Resistance, Junction-to-Case                                            | $R_{\theta JC}$ | 1.56 | $^\circ\text{C/W}$ |
| Thermal Resistance, Junction-to-Ambient                                         | $R_{\theta JA}$ | 62.5 | $^\circ\text{C/W}$ |
| Maximum Lead Temperature for Soldering<br>Purposes 1/8" from Case for 5 Seconds | $T_L$           | 260  | $^\circ\text{C}$   |

\*Measurement made with thermocouple contacting the bottom insulated mounting surface of the package (in a location beneath the die), the device mounted on a heatsink with thermal grease applied at a mounting torque of 6 to 8lbs.

\*For additional information on our Pb-Free strategy and soldering details, please download the onsemi Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

POWER TRANSISTOR  
8.0 AMPERES  
400 VOLTS – 80 WATTS



TO-220-3  
CASE 221A  
STYLE 1

### MARKING DIAGRAM



A = Assembly Location  
Y = Year  
WW = Work Week  
G = Pb-Free Package

### ORDERING INFORMATION

| Device    | Package             | Shipping        |
|-----------|---------------------|-----------------|
| MJE13007G | TO-220<br>(Pb-Free) | 50 Units / Rail |

# MJE13007

## ELECTRICAL CHARACTERISTICS (T<sub>C</sub> = 25 °C unless otherwise noted)

| Characteristic | Symbol | Min | Typ | Max | Unit |
|----------------|--------|-----|-----|-----|------|
|----------------|--------|-----|-----|-----|------|

### OFF CHARACTERISTICS (Note 2)

|                                                                                                                   |                       |        |        |            |      |
|-------------------------------------------------------------------------------------------------------------------|-----------------------|--------|--------|------------|------|
| Collector-Emitter Sustaining Voltage<br>(I <sub>C</sub> = 10 mA, I <sub>B</sub> = 0)                              | V <sub>CEO(sus)</sub> | 400    | –      | –          | Vdc  |
| Collector Cutoff Current<br>(V <sub>CES</sub> = 700 Vdc)<br>(V <sub>CES</sub> = 700 Vdc, T <sub>C</sub> = 125 °C) | I <sub>CES</sub>      | –<br>– | –<br>– | 0.1<br>1.0 | mAdc |
| Emitter Cutoff Current<br>(V <sub>EB</sub> = 9.0 Vdc, I <sub>C</sub> = 0)                                         | I <sub>EBO</sub>      | –      | –      | 100        | μAdc |

### SECOND BREAKDOWN

|                                                             |                  |              |  |  |  |
|-------------------------------------------------------------|------------------|--------------|--|--|--|
| Second Breakdown Collector Current with Base Forward Biased | I <sub>S/b</sub> | See Figure 6 |  |  |  |
| Clamped Inductive SOA with Base Reverse Biased              | –                | See Figure 7 |  |  |  |

### ON CHARACTERISTICS (Note 2)

|                                                                                                                                                                                                                                                                                               |                      |                  |                  |                          |     |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------|------------------|------------------|--------------------------|-----|
| DC Current Gain<br>(I <sub>C</sub> = 2.0 Adc, V <sub>CE</sub> = 5.0 Vdc)<br>(I <sub>C</sub> = 5.0 Adc, V <sub>CE</sub> = 5.0 Vdc)                                                                                                                                                             | h <sub>FE</sub>      | 8.0<br>5.0       | –<br>–           | 40<br>30                 | –   |
| Collector-Emitter Saturation Voltage<br>(I <sub>C</sub> = 2.0 Adc, I <sub>B</sub> = 0.4 Adc)<br>(I <sub>C</sub> = 5.0 Adc, I <sub>B</sub> = 1.0 Adc)<br>(I <sub>C</sub> = 8.0 Adc, I <sub>B</sub> = 2.0 Adc)<br>(I <sub>C</sub> = 5.0 Adc, I <sub>B</sub> = 1.0 Adc, T <sub>C</sub> = 100 °C) | V <sub>CE(sat)</sub> | –<br>–<br>–<br>– | –<br>–<br>–<br>– | 1.0<br>2.0<br>3.0<br>3.0 | Vdc |
| Base-Emitter Saturation Voltage<br>(I <sub>C</sub> = 2.0 Adc, I <sub>B</sub> = 0.4 Adc)<br>(I <sub>C</sub> = 5.0 Adc, I <sub>B</sub> = 1.0 Adc)<br>(I <sub>C</sub> = 5.0 Adc, I <sub>B</sub> = 1.0 Adc, T <sub>C</sub> = 100 °C)                                                              | V <sub>BE(sat)</sub> | –<br>–<br>–      | –<br>–<br>–      | 1.2<br>1.6<br>1.5        | Vdc |

### DYNAMIC CHARACTERISTICS

|                                                                                                        |                 |     |    |   |     |
|--------------------------------------------------------------------------------------------------------|-----------------|-----|----|---|-----|
| Current-Gain – Bandwidth Product<br>(I <sub>C</sub> = 500 mAdc, V <sub>CE</sub> = 10 Vdc, f = 1.0 MHz) | f <sub>T</sub>  | 4.0 | 14 | – | MHz |
| Output Capacitance<br>(V <sub>CB</sub> = 10 Vdc, I <sub>E</sub> = 0, f = 0.1 MHz)                      | C <sub>ob</sub> | –   | 80 | – | pF  |

### SWITCHING CHARACTERISTICS

| Resistive Load (Table 1)          |                                                                                                                                                 |                                                   |                 |        |              |              |    |
|-----------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------|-----------------|--------|--------------|--------------|----|
| Delay Time                        | (V <sub>CC</sub> = 125 Vdc, I <sub>C</sub> = 5.0 A,<br>I <sub>B1</sub> = I <sub>B2</sub> = 1.0 A, t <sub>p</sub> = 25 μs,<br>Duty Cycle ≤ 1.0%) |                                                   | t <sub>d</sub>  | –      | 0.025        | 0.1          | μs |
| Rise Time                         |                                                                                                                                                 |                                                   | t <sub>r</sub>  | –      | 0.5          | 1.5          |    |
| Storage Time                      |                                                                                                                                                 |                                                   | t <sub>s</sub>  | –      | 1.8          | 3.0          |    |
| Fall Time                         |                                                                                                                                                 |                                                   | t <sub>f</sub>  | –      | 0.23         | 0.7          |    |
| Inductive Load, Clamped (Table 1) |                                                                                                                                                 |                                                   |                 |        |              |              |    |
| Voltage Storage Time              | V <sub>CC</sub> = 15 Vdc, I <sub>C</sub> = 5.0 A<br>V <sub>clamp</sub> = 300 Vdc                                                                | T <sub>C</sub> = 25 °C<br>T <sub>C</sub> = 100 °C | t <sub>sv</sub> | –<br>– | 1.2<br>1.6   | 2.0<br>3.0   | μs |
| Crossover Time                    | I <sub>B(on)</sub> = 1.0 A, I <sub>B(off)</sub> = 2.5 A<br>L <sub>C</sub> = 200 μH                                                              | T <sub>C</sub> = 25 °C<br>T <sub>C</sub> = 100 °C | t <sub>c</sub>  | –<br>– | 0.15<br>0.21 | 0.30<br>0.50 | μs |
| Fall Time                         |                                                                                                                                                 | T <sub>C</sub> = 25 °C<br>T <sub>C</sub> = 100 °C | t <sub>fi</sub> | –<br>– | 0.04<br>0.10 | 0.12<br>0.20 | μs |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

2. Pulse Test: Pulse Width ≤ 300 μs, Duty Cycle ≤ 2.0%.

TYPICAL CHARACTERISTICS




Figure 1. Base-Emitter Saturation Voltage




Figure 2. Collector-Emitter Saturation Voltage




Figure 3. Collector Saturation Region




Figure 4. DC Current Gain




Figure 5. Capacitance




Figure 6. Maximum Forward Bias Safe Operating Area




Figure 7. Maximum Reverse Bias Switching Safe Operating Area




Figure 8. Forward Bias Power Derating

There are two limitations on the power handling ability of a transistor: average junction temperature and second breakdown. Safe operating area curves indicate  $I_C - V_{CE}$  limits of the transistor that must be observed for reliable operation; i.e., the transistor must not be subjected to greater dissipation than the curves indicate.

The data of Figure 6 is based on  $T_C = 25^\circ\text{C}$ ;  $T_{J(pk)}$  is variable depending on power level. Second breakdown pulse limits are valid for duty cycles to 10% but must be derated when  $T_C \geq 25^\circ\text{C}$ . Second breakdown limitations do not derate the same as thermal limitations. Allowable current at the voltages shown on Figure 6 may be found at any case temperature by using the appropriate curve on Figure 8.

At high case temperatures, thermal limitations will reduce the power that can be handled to values less than the limitations imposed by second breakdown.

Use of reverse biased safe operating area data (Figure 7) is discussed in the applications information section.




Figure 9. Typical Thermal Response for MJE13007

## SPECIFICATION INFORMATION FOR SWITCHMODE APPLICATIONS

## INTRODUCTION

The primary considerations when selecting a power transistor for SWITCHMODE applications are voltage and current ratings, switching speed, and energy handling capability. In this section, these specifications will be discussed and related to the circuit examples illustrated in Table 2. (Note 1)

## VOLTAGE REQUIREMENTS

Both blocking voltage and sustaining voltage are important in SWITCHMODE applications.

Circuits B and C in Table 2 illustrate applications that require high blocking voltage capability. In both circuits the switching transistor is subjected to voltages substantially higher than  $V_{CC}$  after the device is completely off (see load line diagrams at  $I_C = I_{leakage} \approx 0$  in Table 2). The blocking capability at this point depends on the base to emitter conditions and the device junction temperature. Since the highest device capability occurs when the base to emitter junction is reverse biased ( $V_{CEV}$ ), this is the recommended and specified use condition. Maximum  $I_{CEV}$  at rated  $V_{CEV}$  is specified at a relatively low reverse bias (1.5 Volts) both

at 25 °C and 100 °C. Increasing the reverse bias will give some improvement in device blocking capability.

The sustaining or active region voltage requirements in switching applications occur during turn-on and turn-off. If the load contains a significant capacitive component, high current and voltage can exist simultaneously during turn-on and the pulsed forward bias SOA curves (Figure 6) are the proper design limits.

For inductive loads, high voltage and current must be sustained simultaneously during turn-off, in most cases, with the base to emitter junction reverse biased. Under these conditions the collector voltage must be held to a safe level at or below a specific value of collector current. This can be accomplished by several means such as active clamping, RC snubbing, load line shaping, etc. The safe level for these devices is specified as a Reverse Bias Safe Operating Area (Figure 7) which represents voltage-current conditions that can be sustained during reverse biased turn-off. This rating is verified under clamped conditions so that the device is never subjected to an avalanche mode.

NOTE: 1. For detailed information on specific switching applications, see **onsemi** Application Note AN719, AN873, AN875, AN951.

Table 1. Test Conditions For Dynamic Performance

| TEST CIRCUITS                                                            | REVERSE BIAS SAFE OPERATING AREA AND INDUCTIVE SWITCHING                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   | RESISTIVE SWITCHING                                                                                                                                                |                     |       |                                                                          |                                                                                             |                                                                                             |                                                                                                    |
|--------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------|-------|--------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------|
| CIRCUIT VALUES                                                           | <table border="1" data-bbox="446 661 933 850"> <thead> <tr> <th><math>V_{(BR)CEO(sus)}</math></th><th>Inductive Switching</th><th>RBSOA</th></tr> </thead> <tbody> <tr> <td>L = 10 mH<br/><math>R_{B2} = 8</math><br/><math>V_{CC} = 20</math> Volts<br/><math>I_{C(pk)} = 100</math> mA</td><td>L = 200 mH<br/><math>R_{B2} = 0</math><br/><math>V_{CC} = 15</math> Volts<br/><math>R_{B1}</math> selected for desired <math>I_{B1}</math></td><td>L = 500 mH<br/><math>R_{B2} = 0</math><br/><math>V_{CC} = 15</math> Volts<br/><math>R_{B1}</math> selected for desired <math>I_{B1}</math></td></tr> </tbody> </table> | $V_{(BR)CEO(sus)}$                                                                                                                                                 | Inductive Switching | RBSOA | L = 10 mH<br>$R_{B2} = 8$<br>$V_{CC} = 20$ Volts<br>$I_{C(pk)} = 100$ mA | L = 200 mH<br>$R_{B2} = 0$<br>$V_{CC} = 15$ Volts<br>$R_{B1}$ selected for desired $I_{B1}$ | L = 500 mH<br>$R_{B2} = 0$<br>$V_{CC} = 15$ Volts<br>$R_{B1}$ selected for desired $I_{B1}$ | <p><math>V_{CC} = 125</math> V<br/><math>R_C = 25</math><br/><math>D = 1N5820</math> OR EQUIV.</p> |
| $V_{(BR)CEO(sus)}$                                                       | Inductive Switching                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | RBSOA                                                                                                                                                              |                     |       |                                                                          |                                                                                             |                                                                                             |                                                                                                    |
| L = 10 mH<br>$R_{B2} = 8$<br>$V_{CC} = 20$ Volts<br>$I_{C(pk)} = 100$ mA | L = 200 mH<br>$R_{B2} = 0$<br>$V_{CC} = 15$ Volts<br>$R_{B1}$ selected for desired $I_{B1}$                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | L = 500 mH<br>$R_{B2} = 0$<br>$V_{CC} = 15$ Volts<br>$R_{B1}$ selected for desired $I_{B1}$                                                                        |                     |       |                                                                          |                                                                                             |                                                                                             |                                                                                                    |
| TEST WAVEFORMS                                                           | <div data-bbox="243 892 649 1176"> <p><math>t_1</math> ADJUSTED TO OBTAIN <math>I_C</math><br/> <math>t_1 \approx \frac{L_{coil}(I_{CM})}{V_{CC}}</math><br/> <math>t_2 \approx \frac{L_{coil}(I_{CM})}{V_{clamp}}</math></p> <p>TEST EQUIPMENT<br/>SCOPE — TEKTRONIX 475 OR EQUIVALENT</p> </div> <div data-bbox="876 882 1169 1186"> <p><b>TYPICAL WAVEFORMS</b></p> </div>                                                                                                                                                                                                                                              | <p><math>t_p, t_f &lt; 10</math> ns<br/>DUTY CYCLE = 1.0%<br/><math>R_B</math> AND <math>R_C</math> ADJUSTED FOR DESIRED <math>I_B</math> AND <math>I_C</math></p> |                     |       |                                                                          |                                                                                             |                                                                                             |                                                                                                    |

**VOLTAGE REQUIREMENTS (continued)**

In the four application examples (Table 2) load lines are shown in relation to the pulsed forward and reverse biased SOA curves.

In circuits A and D, inductive reactance is clamped by the diodes shown. In circuits B and C the voltage is clamped by the output rectifiers, however, the voltage induced in the primary leakage inductance is not clamped by these diodes and could be large enough to destroy the device. A snubber network or an additional clamp may be required to keep the turn-off load line within the Reverse Bias SOA curve.

Load lines that fall within the pulsed forward biased SOA curve during turn-on and within the reverse bias SOA curve during turn-off are considered safe, with the following assumptions:

1. The device thermal limitations are not exceeded.
2. The turn-on time does not exceed 10  $\mu$ s (see standard pulsed forward SOA curves in Figure 6).
3. The base drive conditions are within the specified limits shown on the Reverse Bias SOA curve (Figure 7).

**CURRENT REQUIREMENTS**

An efficient switching transistor must operate at the required current level with good fall time, high energy handling capability and low saturation voltage. On this data sheet, these parameters have been specified at 5.0 amperes which represents typical design conditions for these devices. The current drive requirements are usually dictated by the  $V_{CE(sat)}$  specification because the maximum saturation voltage is specified at a forced gain condition which must be duplicated or exceeded in the application to control the saturation voltage.

**SWITCHING REQUIREMENTS**

In many switching applications, a major portion of the transistor power dissipation occurs during the fall time ( $t_{fi}$ ). For this reason considerable effort is usually devoted to reducing the fall time. The recommended way to accomplish this is to reverse bias the base-emitter junction during turn-off. The reverse biased switching characteristics for inductive loads are shown in Figures 12 and 13 and resistive loads in Figures 10 and 11. Usually the inductive load components will be the dominant factor in SWITCHMODE applications and the inductive switching data will more closely represent the device performance in actual application. The inductive switching characteristics are derived from the same circuit used to specify the reverse biased SOA curves, (see Table 1) providing correlation between test procedures and actual use conditions.

**SWITCHING TIME NOTES**

In resistive switching circuits, rise, fall, and storage times have been defined and apply to both current and voltage waveforms since they are in phase. However, for inductive loads which are common to SWITCHMODE power supplies and any coil driver, current and voltage waveforms are not in phase. Therefore, separate measurements must be made on each waveform to determine the total switching time. For this reason, the following new terms have been defined.

$t_{sv}$  = Voltage Storage Time, 90%  $I_{B1}$  to 10%  $V_{clamp}$

$t_{rv}$  = Voltage Rise Time, 10–90%  $V_{clamp}$

$t_{fi}$  = Current Fall Time, 90–10%  $I_C$

$t_{ti}$  = Current Tail, 10–2%  $I_C$

$t_c$  = Crossover Time, 10%  $V_{clamp}$  to 10%  $I_C$

An enlarged portion of the turn-off waveforms is shown in Figure 12 to aid in the visual identity of these terms. For the designer, there is minimal switching loss during storage time and the predominant switching power losses occur during the crossover interval and can be obtained using the standard equation from AN222A:

$$P_{SWT} = 1/2 V_{CC} I_C (t_c) f$$

Typical inductive switching times are shown in Figure 13. In general,  $t_{rv} + t_{fi} \approx t_c$ . However, at lower test currents this relationship may not be valid.

As is common with most switching transistors, resistive switching is specified at 25 °C and has become a benchmark for designers. However, for designers of high frequency converter circuits, the user oriented specifications which make this a “SWITCHMODE” transistor are the inductive switching speeds ( $t_c$  and  $t_{sv}$ ) which are guaranteed at 100 °C.

SWITCHING PERFORMANCE




Figure 10. Turn-On Time (Resistive Load)




Figure 11. Turn-Off Time (Resistive Load)




Figure 12. Inductive Switching Measurements

















Figure 13. Typical Inductive Switching Times

Table 2. Applications Examples of Switching Circuits

| CIRCUIT                                                                                                                                        | LOAD LINE DIAGRAMS                                                                                                                                                                                 | TIME DIAGRAMS                                                                                                     |
|------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------|
| <p><b>A</b></p> <p><b>SERIES SWITCHING REGULATOR</b></p>      | <p><b>LOAD LINE DIAGRAMS</b></p>  <p>Notes:<br/>           ① See AN569 for Pulse Power Derating Procedure.</p>   | <p><b>TIME DIAGRAMS</b></p>    |
| <p><b>B</b></p> <p><b>FLYBACK INVERTER</b></p>               | <p><b>LOAD LINE DIAGRAMS</b></p>  <p>Notes:<br/>           ① See AN569 for Pulse Power Derating Procedure.</p>  | <p><b>TIME DIAGRAMS</b></p>   |
| <p><b>C</b></p> <p><b>PUSH-PULL INVERTER/CONVERTER</b></p>  | <p><b>LOAD LINE DIAGRAMS</b></p>  <p>Notes:<br/>           ① See AN569 for Pulse Power Derating Procedure.</p> | <p><b>TIME DIAGRAMS</b></p>  |
| <p><b>D</b></p> <p><b>SOLENOID DRIVER</b></p>               | <p><b>LOAD LINE DIAGRAMS</b></p>  <p>Notes:<br/>           ① See AN569 for Pulse Power Derating Procedure.</p> | <p><b>TIME DIAGRAMS</b></p>  |




TO-220-3 10.10x15.12x4.45, 2.54P

CASE 221A

ISSUE AL

DATE 05 FEB 2025



| MILLIMETERS |          |       |       |
|-------------|----------|-------|-------|
| DIM         | MIN      | NOM   | MAX   |
| A           | 4.07     | 4.45  | 4.83  |
| A1          | 1.15     | 1.28  | 1.41  |
| A2          | 2.04     | 2.42  | 2.79  |
| b           | 1.15     | 1.34  | 1.52  |
| b1          | 0.64     | 0.80  | 0.96  |
| c           | 0.36     | 0.49  | 0.61  |
| D           | 9.66     | 10.10 | 10.53 |
| D1          | 8.43     | 8.63  | 8.83  |
| E           | 14.48    | 15.12 | 15.75 |
| E1          | 12.58    | 12.78 | 12.98 |
| E2          | 1.27 REF |       |       |

| MILLIMETERS |       |       |       |
|-------------|-------|-------|-------|
| DIM         | MIN   | NOM   | MAX   |
| e           | 2.42  | 2.54  | 2.66  |
| e1          | 4.83  | 5.08  | 5.33  |
| H1          | 5.97  | 6.22  | 6.47  |
| L           | 12.70 | 13.49 | 14.27 |
| L1          | 2.80  | 3.45  | 4.10  |
| Q           | 2.54  | 2.79  | 3.04  |
| øP          | 3.60  | 3.85  | 4.09  |
| Z           | ---   | ---   | 3.48  |

NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2018.
2. CONTROLLING DIMENSION: MILLIMETERS.
3. DIMENSION Z DEFINES A ZONE WHERE ALL BODY AND LEAD IRREGULARITIES ARE ALLOWED.

STYLE 1:  
PIN 1. BASE  
2. COLLECTOR  
3. EMITTER  
4. COLLECTOR

STYLE 2:  
PIN 1. BASE  
2. EMITTER  
3. COLLECTOR  
4. EMITTER

STYLE 3:  
PIN 1. CATHODE  
2. ANODE  
3. GATE  
4. ANODE

STYLE 4:  
PIN 1. MAIN TERMINAL 1  
2. MAIN TERMINAL 2  
3. GATE  
4. MAIN TERMINAL 2

STYLE 5:  
PIN 1. GATE  
2. DRAIN  
3. SOURCE  
4. DRAIN

STYLE 6:  
PIN 1. ANODE  
2. CATHODE  
3. ANODE  
4. CATHODE

STYLE 7:  
PIN 1. CATHODE  
2. ANODE  
3. CATHODE  
4. ANODE

STYLE 8:  
PIN 1. CATHODE  
2. ANODE  
3. EXTERNAL TRIP/DELAY  
4. ANODE

STYLE 9:  
PIN 1. GATE  
2. COLLECTOR  
3. EMITTER  
4. COLLECTOR

STYLE 10:  
PIN 1. GATE  
2. SOURCE  
3. DRAIN  
4. SOURCE

STYLE 11:  
PIN 1. DRAIN  
2. SOURCE  
3. GATE  
4. SOURCE

STYLE 12:  
PIN 1. MAIN TERMINAL 1  
2. MAIN TERMINAL 2  
3. GATE  
4. NOT CONNECTED

|                  |                                  |                                                                                                                                                                                  |
|------------------|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| DOCUMENT NUMBER: | 98ASB42148B                      | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |
| DESCRIPTION:     | TO-220-3 10.10x15.12x4.45, 2.54P | PAGE 1 OF 1                                                                                                                                                                      |

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

**onsemi**, **Onsemi**, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

### TECHNICAL PUBLICATIONS:

Technical Library: [www.onsemi.com/design/resources/technical-documentation](http://www.onsemi.com/design/resources/technical-documentation)  
onsemi Website: [www.onsemi.com](http://www.onsemi.com)

### ONLINE SUPPORT: [www.onsemi.com/support](http://www.onsemi.com/support)

For additional information, please contact your local Sales Representative at  
[www.onsemi.com/support/sales](http://www.onsemi.com/support/sales)