

1 Amp—Rectifiers

Outline Drawing No. 19 applies.

REFERENCE TABLE

Code	V_{RRM} (V)	I_{RRM} (μA)	I_{FSM} (A)	$I_{F(AV)}$ (A)	Stock No.
BY126	650	10	40	1	34706C
BY127	1250	10	40	1	34759X

1.5 Amp—Miniature Size Rectifiers

Outline Drawing No. 20 applies.

REFERENCE TABLE

Code	V_{RRM} (V)	I_{RRM} (μA)	I_{FSM} (A)	$I_{F(AV)}$ (A) @ 40°C	Stock No.
IN5391	50	10	50	1.5	32950X
IN5392	100	10	50	1.5	32951R
IN5393	200	10	50	1.5	32952G
IN5394	300	10	50	1.5	32953E
IN5395	400	10	50	1.5	32954C
IN5396	500	10	50	1.5	32955A
IN5397	600	10	50	1.5	32956X
IN5398	800	10	50	1.5	32958F
IN5399	1000	10	50	1.5	32960G

3 Amp Rectifiers

Outline Drawing No. 19 applies.

REFERENCE TABLE

Code	V_{RRM} (V)	I_{RRM} (μA)	I_{FSM} (A)	$I_{F(AV)}$ (A) @ 40°C	Stock No.
IN5400	50	10	200	3	32961E
IN5401	100	10	200	3	32962C
IN5402	200	10	200	3	32963A
IN5403	300	10	200	3	32964X
IN5404	400	10	200	3	32965H
IN5405	500	10	200	3	32966F
IN5406	600	10	200	3	32967D
IN5407	800	10	200	3	32969X
IN5408	1000	10	200	3	32971A

PLEASE QUOTE STOCK NO. AND MANUFACTURER'S CODE WHEN ORDERING