

Fusedrawer für Fuse Links 5x20 mm, with or without Voltage Selector Insert

Standard or Medical Fuse drawer



Fuse drawer without voltage selector insert with shorting bar  
(Fuse links not enclosed)



Fuse drawer with voltage selector insert  
(Fuse links not enclosed)



## Description

- Component
- Snap-in version from front side
- 2 Functions:  
Fuseholder for Fuse links 5x20 mm, Voltage Selector
- Approved together with power entry module

## Characteristics

- Fuse drawer meets requirements of medical standard IEC/EN 60601-1  
The fuse drawer "Fingergrasp" can be removed by hand  
The fuseholder is accessible from the equipment front
- Designed for standard and medical applications
- Suitable for use in equipment according to IEC/UL 60950

## Other versions on request

- Fuse drawer with other voltage values

## References

Fits to type: DD11; DD12; DD21; DD22; KEA-Print; KFA; KMF

## Weblinks

[pdf-datasheet](#), [html-datasheet](#), [General Product Information](#), [Approvals](#), [CE declaration of conformity](#), [RoHS](#), [CHINA-RoHS](#), [Mating Connectors](#), [e-Shop](#), [SCHURTER-Stock-Check](#), [Distributor-Stock-Check](#), [CAD-Drawings](#), [Accessories](#), [Mounting instruction](#), [Detailed request for product](#)

## Voltage Selector Inserts

| Index | Marking on Voltage Selector Insert / Terminal No. |     |       |     |
|-------|---------------------------------------------------|-----|-------|-----|
|       | 1                                                 | 2   | 3     | 4   |
| 01    | 110                                               | 150 | 220   | -   |
| 02    | 120                                               | -   | 240   | -   |
| 03    | 110                                               | -   | 220   | -   |
| 04    | 115                                               | -   | 220   | -   |
| 05    | 110                                               | -   | 230   | -   |
| 06    | 115                                               | -   | 230   | -   |
| 07    | 100                                               | 110 | 220   | 240 |
| 08    | 100                                               | 120 | 220   | 240 |
| 10    | 220                                               | -   | 240   | -   |
| 11    | 120                                               | 220 | 240   | -   |
| 12    | 110                                               | 220 | 240   | -   |
| 13    | 115                                               | 220 | 240   | -   |
| 14    | -                                                 | -   | -     | -   |
| 15    | 100                                               | 120 | 220   | -   |
| 16    | 50 Hz                                             | -   | 60 Hz | -   |
| 19    | 117                                               | 220 | 240   | -   |
| 22    | 110                                               | 220 | 230   | -   |
| 23    | 100                                               | 115 | 220   | 240 |
| 24    | 115                                               | 230 | 240   | -   |
| 25    | 100                                               | 120 | 230   | -   |
| 26    | 220                                               | 230 | 240   | -   |
| 28    | 120                                               | 230 | -     | -   |
| 29    | 100                                               | 120 | 230   | 240 |
| 31    | -                                                 | 120 | 230   | -   |
| 32    | 100                                               | 120 | 200   | 240 |

| Index<br>xx | Marking on Voltage Selector Insert / Terminal No. |     |     |     |
|-------------|---------------------------------------------------|-----|-----|-----|
|             | 1                                                 | 2   | 3   | 4   |
| 33          | 110                                               | 120 | 220 | 240 |
| 34          | 100                                               | 115 | 230 | 240 |
| 36          | 100                                               | 110 | 120 | -   |
| 37          | 100                                               | 110 | 230 | 240 |
| 38          | 110                                               | 127 | 230 | -   |
| 40          | 110                                               | 220 | 240 | 120 |
| 41          | 100                                               | 115 | 230 | -   |
| 42          | 200                                               | 230 | 240 | -   |
| 44          | 1                                                 | 2   | 3   | 4   |
| 45          | 100                                               | 220 | 230 | 240 |
| 47          | 100                                               | -   | 120 | -   |
| 48          | 100                                               | 110 | 230 | -   |
| 49          | 110                                               | 220 | 230 | 240 |
| 51          | 100                                               | -   | -   | -   |
| 52          | 120                                               | 220 | 230 | 240 |
| 53          | 001                                               | -   | -   | -   |
| 54          | 021                                               | 022 | 032 | 042 |
| 55          | 230                                               | -   | 115 | -   |

Index "xx" matches the last two characters of the Order Number within the Variants

## Variants

| Mounting   | Voltage Selector | Fuseholder | Comment                          | Suitable for | Order Number |
|------------|------------------|------------|----------------------------------|--------------|--------------|
| Extra-Safe |                  | 1-pole     | -                                | 1), 2), 3)   | 4301.1407    |
| Extra-Safe |                  | 1-pole     | spare fuse case                  | 1), 2), 3)   | 4301.1411    |
| Fingergrip |                  | 1-pole     | -                                | 1), 2), 3)   | 4301.1405    |
| Fingergrip |                  | 1-pole     | spare fuse case                  | 1), 2), 3)   | 4301.1409    |
| Extra-Safe |                  | 2-pole     | -                                | 1), 2), 3)   | 4301.1403    |
| Extra-Safe |                  | 2-pole     | shorting bar in the neutral side | 1), 2), 3)   | 4301.1415    |
| Fingergrip |                  | 2-pole     | -                                | 1), 2), 3)   | 4301.1401    |
| Fingergrip |                  | 2-pole     | shorting bar in the neutral side | 1), 2), 3)   | 4301.1413    |
| Extra-Safe | ●                | 1-pole     | -                                | 1)           | 4301.1224.xx |
| Extra-Safe | ●                | 1-pole     | spare fuse case                  | 1)           | 4301.2824.xx |
| Fingergrip | ●                | 1-pole     | -                                | 1)           | 4301.1214.xx |
| Fingergrip | ●                | 1-pole     | spare fuse case                  | 1)           | 4301.2814.xx |
| Extra-Safe | ●                | 2-pole     | -                                | 1)           | 4301.1024.xx |
| Extra-Safe | ●                | 2-pole     | shorting bar in the neutral side | 1)           | 4301.3537.xx |
| Fingergrip | ●                | 2-pole     | -                                | 1)           | 4301.1014.xx |
| Fingergrip | ●                | 2-pole     | shorting bar in the neutral side | 1)           | 4301.3536.xx |

1) KEA, KFA;

2) KEA-Print (without voltage selector)

3) KM, DD11, DD12, DD21, DD22 (only 1-/2-pole, without voltage selector)

"xx" see Voltage Selector Insert Table

**Packaging unit** 50 Pcs