

Auxiliary Contacts For Isolator Switches

multicomp

Neutral Contact:



Electrical Symbol



Features:

Neutral Contact (Early Make Late Break):

- Early make late break contact can be fitted either side of the switch
- All switch ratings at AC22
- Rear mount for door interlock and boxed isolator
- Front mount for panel mount isolators

Auxiliary Changeover Contacts:

- 1 NO contact early break/late make + 1 NC contact can be fitted either side of the switch
- Rear mount for door interlocked and boxed isolators


Main Pole Contacts:

- Equivalent switch electrical rating used as 4th/5th pole on either side of the switch
- All switch ratings at AC22
- Front mount for panel mounting Isolators
- Rear mount for door interlock and boxed isolators.

Auxiliary Changeover Contact:



Electrical Symbol



Applications:

Neutral Contact (Early Make Late Break):

To be used as neutral conductor to the switch.

Auxiliary Changeover Contacts:

The auxiliary contact module has two contacts, NO and NC. The NO contact is an early break, late make contact.

Main Pole Contacts:

For switching action of additional pole, when mounted with the switch.

The additional pole on either side of the switch can be used to switch on any single phase requirements simultaneously.

Main Pole Contact:



Electrical Symbol



Auxiliary Changeover Contacts

Rating		
IEC/IEN	16A, 500V	
AC-15	220 to 240V 380 to 440V	6A 4A

Terminal Cross Section		
Single/Multiple Strand Wire	Minimum mm ²	1
	Maximum mm ²	1.5
American Wire Gauge	AWG	16

Auxiliary Contacts For Isolator Switches



Part Number Table

Description	Part Number
Isolator Cont. 25A-63A R/M	LB263AUXEM
Isolator Cont 25A-63A F/M	LB263AUXEMFM
Isolator Cont N 80A R/M	LB280AUXEM
Isolator Cont N 125A R/M	LB125AUXEM
Isolator Cont N 20A-63A Aux	LBAC16RM
Isolator Cont N 125A Aux	LBAC125RM
Isolator Cnt M 25-63A FM	LB263MAINFM
Isolator Cnt M 25-63A RM	LB263MAINPOLE
Isolator Cnt M 80A RM	LB280MAINPOLE
Isolator Cnt M 125A RM	LB2125MAINPOLE

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.