

Digital Multimeter

Clamp, 1,000A



Specifications:

DMM Type	: Clamp
Voltage Measuring Range DC	: 400mV to 600V
Voltage Measuring Range AC	: 4V to 600V
Current Measuring Range AC	: 400A, 1,000A
Resistance Measuring Range	: 400Ω to 40MΩ
Frequency Measuring Range	: 100Hz to 800kHz
No. of Digits / Alpha	: 3-3/4
DMM Functions	: AC Current, AC/DC Voltage, Continuity, Diode, Frequency, Resistance
Ranging	: Auto, Manual
Display Count	: 3,999
AC Current Range Accuracy	: ± (2% + 10 digits)
AC Voltage Range Accuracy	: ± (1.2% + 5 digits)
Battery Size Code	: PP3
Cable Diameter Max	: 46mm
Current AC Max	: 1kA
Current Measuring Range Resolution AC	: 0.1A
Current Range AC	: 400A, 1,000A
DC Voltage Range Accuracy ¹	: ± 0.75% + 2 Digits
External Depth	: 38mm
External Length / Height	: 229mm
External Width	: 67mm
Jaw Opening Max	: 46mm
Frequency Measuring Range Accuracy	: ± (0.1% + 2 digits)
Frequency Measuring Range Resolution	: 0.01Hz
Resistance Measuring Range Resolution	: 0.1R
Resistance Range Accuracy	: ± (1% + 3 digits)
Safety Category	: 600V CATIII

Part Number Table

Description	Part Number
Multimeter, Digital, Clamp, 1,000A	72-6130.

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

