

## Hold-Down Springs and Clips Selection Guide

### DIN Rail Snap-Mount Sockets

| Socket Part No.     | Applicable Relays, Timer  | Hold-Down Spring | Hold-Down Clip     |
|---------------------|---------------------------|------------------|--------------------|
| SR2P-05<br>SR2P-05C | RR2P, RAPP, RBPP          | SR2B-02F1        | SFA-203            |
|                     | RTE-P1, GT3, GT5P         | —                | SFA-203            |
| SR2P-06             | RR2P, RAPP, RBPP          | SR2B-02F1        | SFA-202            |
|                     | GT3 (8-pin), RTE-P1, GT5P | —                | SFA-202            |
| SR3P-05<br>SR3P-05C | RR3PA                     | SR3B-02F1        | SFA-203            |
|                     | RR2KP                     | SR3P-06F3        | SFA-203            |
|                     | RTE-P2, GT3 (11-pin)      | —                | SFA-203            |
| SR3P-06             | RR3PA                     | SR3B-02F1        | SFA-202            |
|                     | RR2KP                     | SR3P-06F3        | SFA-202            |
|                     | RTE-P2, GT3 (11-pin)      | —                | SFA-202            |
| SR3B-05             | RR1BA, RR2BA, RR3B, RTE-B | SR3B-02F1        | SFA-202            |
| SH1B-05<br>SH1B-05C | RH1B, RAHB, RBHB          | SY2S-02F1        | SFA-101<br>SFA-202 |
| SH2B-05<br>SH2B-05C | RH2B, RAMB, RBMB          | SY4S-02F1        | SFA-101<br>SFA-202 |
| SH3B-05<br>SH3B-05C | RH3B, RH2LB               | SH3B-05F1        | SFA-101<br>SFA-202 |
| SH4B-05<br>SH4B-05C | RH4B                      | SH4B-02F1        | SFA-101<br>SFA-202 |
| SY2S-05<br>SY2S-05C | RY2S, RY22S               | SY2S-02F1        | SFA-101<br>SFA-202 |
| SY4S-05<br>SY4S-05C | RY4S, RY42S, RY2LS, RM2S  | SY4S-51F1        | SFA-101<br>SFA-202 |
|                     | RY2KS, GT5Y               | (SY4S-51F3)      | SFA-202            |

### Panel and PC Board Mount Sockets

| Socket Part No.    | Applicable Relays, Timer  | Hold-Down Spring         | Hold-Down Clip     |
|--------------------|---------------------------|--------------------------|--------------------|
| SR2P-51            | RR2P, RAPP, RBPP          | SR3P-01F1                | —                  |
|                    | GT3 (8-pin), RTE-P1       | —                        | SFA-402            |
| SR3P-51            | RR3PA                     | SR3P-01F1                | —                  |
|                    | RR2KP                     | SR3P-51F3                | —                  |
|                    | GT3 (11-pin), RTE-P2      | —                        | SFA-402            |
| SR3B-51            | RR1BA, RR2BA, RR3B, RTE-B | SR3B-02F1                | —                  |
| SH1B-51<br>SH1B-62 | RH1B, RAHB, RBHB          | SY4S-51F1                | SFA-301<br>SFA-302 |
| SH2B-51            | RH2B, RAMB, RBMB          | SY4S-51F1<br>(SY4S-02F1) | SFA-301<br>SFA-302 |
| SH2B-62            | RH2B, RAMB, RBMB          | SY4S-51F1<br>(SY4S-02F1) | —                  |
| SH3B-51<br>SH3B-62 | RH3B, RH2LB               | SY4S-51F1<br>(SY4S-02F1) | SFA-301<br>SFA-302 |
| SH4B-51<br>SH4B-62 | RH4B                      | SY4S-51F1<br>(SY4S-02F1) | SFA-301<br>SFA-302 |
| SY2S-51<br>SY2S-61 | RY2S, RY22S               | SY4S-51F1                | SFA-301<br>SFA-302 |
| SY4S-51<br>SY4S-61 | RY4S, RY42S, RY2LS        | SY4S-51F1<br>(SY4S-02F1) | SFA-301<br>SFA-302 |
|                    | RY2KS                     | SY4S-51F1<br>(SY4S-02F3) | SFA-302            |
|                    | GT5Y                      | —                        | SFA-302            |
| SY4S-62 *          | RY4S, RY42S, RY2LS, RM2S  | SY4S-51F1<br>(SY4S-02F1) | —                  |
|                    | RY2KS                     | SY4S-51F1<br>(SY4S-02F3) | —                  |

\* Does not accept hold down clips

**F**


- When mounting relays with a check button onto panel mount or PC board mount sockets, use the hold-down spring shown in parenthesis. Hold-down springs for relays with check buttons are not available for SR2P-51.
- For close mounting of panel mount or PC mount sockets, use hold-down clips rather than hold-down springs.



SFA-101



SFA-202



SFA-302



SFA-402



SR3P-01F1



SY4S-51F1