



# PRODUCT DATASHEET

## Tina3 series

last update 2/11/2012


## DETAILS

Product Number	CA13100_TINA3-W
Family	Tina3
Type	Assembly
Color	white
Diameter	16.1 mm
Height	6.8 mm
Style	round
Optic Material	PMMA
Holder Material	PC
Fastening	tape
Status	ready
ROHS Compliant	Yes
Date Updated	2/11/2012




## OPTICAL PROPERTIES

LED	Viewing Angle	Light Beam	Efficiency	cd/lm	connector
LUXEON Rebel ES	40 degrees		91 %	1.600	-




Materials


Lens: PMMA  
Holder: PC  
Tape: PU Foam

This drawing is our property. It can't be reproduced or communicated without our written agreement.			Ledil Oy Salorankatu 10 FIN 24240 SALO Finland				
			DRAWING TITLE		Mechanical Drawing		
DRAWN BY as	DATE 21.9.2012	TINA3-RE-ES					
CHECKED BY VS	DATE -	SIZE A4	PART NUMBER			REV 001	
DESIGNED BY -	DATE -	SCALE 3:1	WEIGHT -			SHEET 1/1	

Luminaire: Ledil Oy CA13100\_TINA3-W (Luxeon RE-ES 92lm @ 250mA) Efficiency=91%  
Lamps: 1 x Luxeon RE-ES 92lm @ 250mA



Luminaire: Ledil Oy CA13100\_TINA3-W (Luxeon RE-ES 92lm @ 250mA) Efficiency=91%  
Lamps: 1 x Luxeon RE-ES 92lm @ 250mA



cd/klm

C0 - C180      C90 - C270

**NOTE:** The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.

## **GENERAL INFORMATION**

- Product series especially designed & optimized for series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: [http://www.ledil.com/datasheets/DataSheet\\_TAPE.pdf](http://www.ledil.com/datasheets/DataSheet_TAPE.pdf)

**NOTE 1:** We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit board weaken the strength of the tape.

**NOTE 2:** Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.

If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.