

POWER SPLITTERS/COMBINERS

50 & 75Ω

2 WAY-0° 2 kHz to 10 GHz



ZESC-2



ZFSC-2



ZMSC-2



ZSC-2

MODEL NO.	FREQ. RANGE MHz f _L -f _U	ISOLATION dB					INSERTION LOSS, dB Above 3dB					PHASE UNBAL. Degrees			AMPLITUDE UNBAL. dB			VSWR (:1)		CASE STYLE	CONNECTION	PRICE \$																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
		L Typ.	M° Min.	U Typ.	Min.	Typ.	L Typ.	M° Min.	U Typ.	Max.	L Max.	M° Max.	U Max.	L Max.	M° Max.	U Max.	S Typ.	OUT Typ.	Max.																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																														

NOTES:

- * Isolation specified to 0.004 MHz
- ** Insertion loss, Isolation specified to -20°C from 0.002 to 0.004 MHz
- ⊕ When only specification for M range given, specification applies to entire frequency range.
- ❖ At low range frequency band (f_L to $10 f_L$), linearly derate maximum input power by 13 dB.
- Denotes 75 Ohm model, for coax connector models 75 Ohm BNC connectors are standard.
- ▲ Available only with SMA connectors
- A. General Quality Control Procedures, Environmental Specifications, Hi-Rel and MIL description are given in "Mini-Circuits Guarantees Quality" article.
- B. For details on Connector types, case mounted options, case finishes see "Case styles & Outline Drawings".
- C. Prices and specifications subject to change without notice.
- 1. Absolute maximum power, voltage and current ratings:
 - 1a. Matched power rating:
 - Models ZAPD, ZN2PD, ZC2PD 10 Watt
 - ZAPD-900-5W, ZN2PD-20 5W(as a splitter)
 - ZAPD-30 and other models 1 Watt
 - 1b. Internal load dissipation:
 - ZAPD-900-5W 1W max.
 - ZN2PD-20 0.725W max.
 - ZN2PD-9G, ZAPD-2-22-75 0.25W max.
 - All other models 0.125 Watt

coaxial connections

see case style outline drawing for pin locations

PORT	ar	as	at
SUM PORT	3	5	2
PORT 1	1	1	1
PORT 2	2	2	3
GND EXT.	—	—	—
CASE GND	—	—	—
NOT USED	—	—	—

Mini-Circuits®

Distribution Centers NORTH AMERICA 800-654-7949 • 417 335-5935 • Fax 417-335-5945 • EUROPE 44-1252-832600 • Fax 44-1252-837010

ISO 9001 CERTIFIED

Coaxial



MODEL NO.	FREQ. RANGE MHz f_L - f_U	ISOLATION dB			INSERTION LOSS, dB Above 3dB			PHASE UNBAL. Degrees			AMPLITUDE UNBAL. dB			VSWR (:1)		CASE STYLE Note B	CONNECTION	PRICE \$ Qty. (1-9)
		L	M°	U	L	M°	U	L	M°	U	L	M°	U	S	OUT			
		Typ.	Min.	Typ. Min.	Typ. Min.	Typ. Max.	Typ. Max.	Typ. Max.	Max.	Max.	Max.	Max.	Max.	Max.	Typ. Max.			
ZC2PD-900	800-900			30 20		0.1 0.4		2		0.20	1.10 1.30	1.10 1.30	F183	as	64.95			
ZN2PD-20	750-2000	18 15	25 20	18 15		0.2 0.5		4		0.30	1.16 1.5	1.10 1.35	VVV180	as	67.95			
ZN2PD-920	800-920		30 20			0.15 0.4		2		0.20	1.10 1.20	1.04 1.20	VVV180	as	59.95			
ZN2PD-920W	700-1050		22 15			0.15 0.5		3		0.30	1.20 1.50	1.04 1.20	VVV180	as	54.95			
ZN2PD-1900	1600-1900		30 20			0.18 0.4		2		0.20	1.20 1.35	1.04 1.20	VVV180	as	69.95			
ZN2PD-1900W	1500-2000		24 15			0.2 0.5		3		0.30	1.20 1.50	1.04 1.20	VVV180	as	64.95			
ZN2PD-9G	1700-9000		22 15			0.5 1.4		4		0.60			VVV180	as	69.95			
ZN2PD2-50	500-5000		25 15			0.8 1.4		4		0.5	1.20 —	1.10 —	VVV845	as	74.95			
	600-1600		24 17			0.7 1.1		2		0.3	1.20 —	1.10 —						
	1600-2700		26 18			0.8 1.2		3		0.3	1.20 —	1.10 —						
	2700-3600		28 19			0.9 1.3		3		0.4	1.20 —	1.10 —						
	3700-4800		22 18			0.9 1.4		4		0.5	1.20 —	1.10 —						
	GHz																	
IZY2PD-64	5.8-6.4		35 24			0.2 0.5		5		0.30	1.05 1.30	1.20 1.35	JJJ245	as	89.95			
IZY2PD-86	7.0-8.6		30 18			0.1 0.5		6		0.25	1.10 1.45	1.10 1.40	JJJ245	as	94.95			
ZAPD-1	0.5-1.0		25 19			0.25 0.6		2		0.20			F14	as	54.95			
ZAPD-2	1.0-2.0		25 19			0.25 0.6		2		0.20			F14	as	54.95			
ZAPD-2-22-75	0.91-2.15		30 20			0.2 0.7		2		0.40	1.15 1.60	1.10 1.30	F14	as	58.95			
ZAPD-20	0.7-2.0		30 20			0.30 0.7		3		0.40	1.15 1.35	1.10 1.30	F53	as	59.95			
ZAPD-21	0.5-2.0		25 18			0.25 1.0		3		0.20			F53	as	59.95			
ZAPD-30	0.02-3.0	14 12	16 12	20 14	1.1 1.5	1.1 1.8	1.4 2.3	3 5 9	0.30 0.40 0.80		1.50 1.95	1.55 2.10	F14	as	79.95			
ZAPD-4	2.0-4.2		25 19			0.4 0.8		6		0.40	see Yoni for Performance Data and curves			F14	as	59.95		
ZAPD-50	4.4-5.0		26 20			0.3 0.8		5		0.50				F14	as	54.95		
ZAPD-50W	4.2-6.0		26 16			0.3 0.8		5		0.70				F14	as	64.95		
ZAPD-900-5W	0.1-0.9		23 18			0.3 1.0		3		0.30				1.15 1.50	1.22 1.50	F14	as	59.95
ZAPD-1750	0.95-1.75		30 22			0.2 0.4		4		0.50				1.15 1.50	1.22 1.50	F14	as	54.95

L = low range [f_L to $10 f_L$]
 $L^1 = f_L$ to 6 GHz
 $L^0 = 750$ to 875 MHz

M = mid range [$10 f_L$ to $f_U/2$]
 $U^1 = 6$ GHz to f_U
 $U^0 = 1850$ to 2000 MHz

U = upper range [$f_U/2$ to f_U]

NSN GUIDE

MCL NO.	NSN	MCL NO.	NSN	MCL NO.	NSN
ZAPD-1(TNC)	5985-01-250-4883	ZFSC-2-2(SMA)	6625-01-333-1127	ZSC-2-1(TNC)	6625-01-310-2129
ZAPD-2 (BNC)	5895-01-476-0831	ZFSC-2-2B	5895-01-330-4416	ZSC-2-1	5895-01-214-6032
ZAPD-2(SMA)	5895-01-229-7431	ZFSC-2-4	6625-01-291-3346	ZSC-2-1B	6625-01-018-1066
ZAPD-4	6625-01-173-1887	ZFSC-2-4(TNC)	5985-01-250-4882	ZSC-2-1B(TNC)	6625-01-109-3706
ZAPD-4(SMA)	5985-01-383-0636	ZFSC-2-5	6625-01-253-2444	ZSC-2-1(BNC)	5895-01-036-6254
ZESC-2-11	5985-01-381-9081	ZFSC-2-6	6625-01-419-4241	ZSC-2-1B(BNC)	6625-00-270-3055
ZFSC-2-1	6625-01-139-3499	ZFSC-2-6(BNC)	5895-01-408-6857	ZSC-2-1W	5895-01-283-0850
ZFSC-2-1(SMA)	6625-01-213-6490	ZFSC-2-6B	5985-01-315-2869	ZSC-2-1WB	6625-01-264-8985
ZFSC-2-1(BNC)	5985-01-176-4551	ZFSC-2-10G	5895-01-467-5372	ZSC-2-1-75B	5895-01-136-8182
ZFSC-2-1-75	5895-01-325-4795	ZFSC-2-11(SMA)	6625-01-415-2183	ZSC-2-2B	5820-01-136-7245
ZFSC-2-1W(SMA)	6625-01-200-5094	ZMSC-2-1	5985-01-333-1128	ZSC-2-2-75B	5915-01-012-8162
ZFSC-2-1W	5895-01-348-3534	ZMSC-2-1B	5895-01-253-2445	ZSC-2375	5895-01-229-0157
ZFSC-2-2B(SMA)	6625-01-362-1801	ZMSC-2-1BR	5985-01-338-9329		
		ZMSC-2-1W	5895-01-127-0232		



The Design Engineers Search Engine
Provides Actual Data Instantly
At: <http://www.minicircuits.com>

In Stock... Immediate Delivery
For Custom Versions Of Standard Models
Consult Our Applications Dept.

