

SJPB-L6

Schottky Barrier Rectifier

Apr. 2009

General Description

SJPB-H6 is a Schottky Barrier Diode, and has achieved low leakage current and low VF by selecting the best barrier metal.


Applications

- DC-DC converters
- AC adapter
- High frequency rectification circuit

Features

- Super-high speed & low noise switching.
- Low forward voltage drop.



Package



Key Specifications

Item	Unit	Rating	Conditions
V_{RM}	V	60	
V_F	V	0.70	$I_F=3.0A$
$I_{F(AV)}$	A	3.0	

Typical Characteristics



The information included herein is believed to be accurate and reliable. However, SANKEN ELECTRIC CO., LTD assumes no responsibility for its use ; nor for any infringements of patents or other rights of third parties that may result from its use.

SJPB-L6

Apr. 2009

Schottky Barrier Rectifier

★ Absolute maximum ratings

No.	Item	Symbol	Unit	Rating	Conditions
1	Transient Peak Reverse Voltage	V_{RSM}	V	60	
2	Peak Reverse Voltage	V_{RM}	V	60	
3	Average Forward Current	$I_{F(AV)}$	A	3.0	
4	Peak Surge Forward Current	I_{FSM}	A	50	Half sinewave, one shot
5	I^2t Limiting Value	I^2t	A^2s	8.0	1msec t 10msec
6	Junction Temperature	T_j		-40 ~ +150	
7	Storage Temperature	T_{stg}		-40 ~ +150	

★ Electrical characteristics($T_a=25$, unless otherwise specified)

No.	Item	Symbol	Unit	Value	Conditions
1	Forward Voltage Drop	V_F	V	0.70 max.	$I_F=3.0A$
2	Reverse Leakage Current	I_R	μA	300 max.	$V_R=V_{RM}$
3	Reverse Leakage Current Under High Temperature	$H \cdot I_R$	mA	70 max.	$V_R=V_{RM}$, $T_j=150$
4	Thermal Resistance	$R_{th(j-l)}$	/W	20 max.	Between Junction and Lead




The information included herein is believed to be accurate and reliable. However, SANKEN ELECTRIC CO., LTD assumes no responsibility for its use ; nor for any infringements of patents or other rights of third parties that may result from its use.

SJPB-L6

Schottky Barrier Rectifier

Apr. 2009

★ Characteristics




SJPB-L6

Schottky Barrier Rectifier

Apr. 2009

★ Outline drawings, mm



★ Connection Diagram

