

www.lemo.com

FFY.00.250.NTAC47

SUMMARY

Wires

Fiber

 Low
 0

 High
 0

 Coax
 1

Triax 0

Quad 0

Fluidic 0

Series 00

Termination type Male solder

IP rating 50

 Cable Ø
 3.90 - 4.50 mm

 Matching parts
 ERA.00.250.NTL

Status active

Alternative part



Image is for illustrative purpose only

Download

Request a quote

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model FFY*: Straight plug with cable collet

Keying Circular (can rotate)

Housing Material Brass (nickel plated) shell, collet nut, latch sleeve and mid pieces

Cable Fixing C47: 3.9 - 4.5 mm

Variant

Performance

Configuration 0.25 : 1 Coax (50 Ohm)

Insulator T: PTFE Rated Current 4 Amps

Specifications

Contact Type: Coaxial 50 Ohm (Solder)

Max. Matings: 5000

Contact Dia.: 0.7 mm (0.028in)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Bucket Dia.: 0.6 mm (0.024in) Test voltage: 2.1 kV (rms)

R (max): 6.1 mOhm

Vtest: 2100 V (AC), 3000 V (DC)

Impedance: 50 Ohm VSWR: 1.09 + 0.11 * f/GHz


Others

Endurance (Shell): 5000 mating cycles

F ret (min): 100 N IP Rating: 50

DRAWINGS

Draws







Dimensions

	А	L	М
mm.	8.9	33	25
in.	0,35	1,30	0,98

RECOMMENDED BY LEMO

Tools

Spanner wrench: DCD.0B.005.PA070

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Cables
LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.