

4

3

2

1

THIS DRAWING IS UNPUBLISHED.

RELEASED FOR PUBLICATION

© COPYRIGHT

ALL RIGHTS RESERVED.

LOC

DIST



REVISIONS

P	LTR	DESCRIPTION	DATE	DWN	APVD
	G1	ECR-14-003067	28FEB2014	GK	HMR





REPLACED BY OCEAN STYLE APPLICATOR PART
NUMBER 2151144-1

FOR REPLACEMENT PARTS FOR APPLICATOR 1426050
REFER TO ADDITIONAL PAGE(S). SPARE PARTS KIT (IF LISTED)
WILL REMAIN AVAILABLE.

THE REPLACEMENT OCEAN STYLE APPLICATOR HAS THE
SAME TERMINATOR/PRESS INTERFACE AS APPLICATOR
1426050

THIS DRAWING IS A CONTROLLED DOCUMENT.		DWN	GOPALAKRISHNA HV		 TE Connectivity		
		CHK	RAGHAVENDRA				
DIMENSIONS:		TOLERANCES UNLESS OTHERWISE SPECIFIED:		APVD	RAGHAVENDRA		
		0 PLC ± 1 PLC ± 2 PLC ± 3 PLC ± 4 PLC ± ANGLES ±		NAME			
				PRODUCT SPEC			
				APPLICATION SPEC			
				WEIGHT			
MATERIAL		FINISH		SIZE	CAGE CODE	DRAWING NO	RESTRICTED TO
				A3		©- 1426050	
CUSTOMER DRAWING				SCALE	SHEET 1 OF 2	REV	G1

PART NUMBER	REV	FIRST USED	TERMINATOR	FEED TYPE	DESCRIPTION
1426050-1	G	-	LEADMAKER	MECH POST FEED	CUTS CARRIER
1426050-2	G	-	BENCH	MECH PRE FEED	CUTS CARRIER
1426050-6	G	-	LEADMAKER	MECH POST FEED	CONTINUOUS CARRIER
7-1426050-1	G	-	LEADMAKER	MECH POST FEED	-1 AND SPARE PARTS
7-1426050-2	G	-	BENCH	MECH PRE FEED	-2 AND SPARE PARTS
7-1426050-6	G	-	LEADMAKER	MECH POST FEED	-6 AND SPARE PARTS
7-1426050-7	D	-	-	-	SPARE PARTS KIT

CRIMP DATA (AMP TERMINAL)				
TERMINAL NAME: .040 III UNSEALED CONTACT, TAB (S)				
CRIMP	SIZE	TYPE	RANGE	
WIRE	1.70 [.067 IN]	F	0.3mm ² - 0.5mm ²	
INSUL	1.57 [.062 IN]	F	1.4mm-1.7mm [.055-.067 IN]	
WIRE STRIP LENGTH			APPL INSTRUCTION	
4.00-4.50 [.157-.177 IN]			408-8322	
TERMINAL	-	-		FEED
APPL SPEC	114-5228	-		9.50 [.374 IN]
TERMINALS APPLIED				
353537	-	-	-	-
-	-	-	-	-
-	-	-	-	-
-	-	-	-	-
-	-	-	-	-
-	-	-	-	-
-	-	-	-	-
-	-	-	-	-
-	-	-	-	-

WIRE SIZE mm ² AWG	CRIMP HEIGHT	PIN PN & LENGTH [IN]
0.50mm ²	1.26 ±0.05 [.050 ±.002 IN]	2-354779-9 [.3135]
0.30mm ² or 0.35mm ²	1.17 ±0.05 [.046 ±.002 IN]	3-354779-8 [.3180]
-	-	-
-	-	-
-	-	-
-	-	-

- RECOMMENDED SPARE PARTS.
- GREASE RAM, CAM, CAM FOLLOWER AND FEED ROD LIGHTLY.
 - LUBRICATE DAILY PER THE APPLICATOR INSTRUCTION SHEET SUPPLIED WITH THE APPLICATOR.

VIEW B ROTATED 180°			
POST FEED 40 mm STROKE	POST FEED 30 mm STROKE	PRE FEED 30 mm STROKE	PRE FEED 40 mm STROKE
LOC A DIST 66			