

PLETRONICS 45 MHz MONOLITHIC FUNDAMENTAL CRYSTAL FILTER SERIES®

[Package Outlines](#)

Part# (Click to Order)	Channel Spacing	# of poles	Passband		Stopband				Ripple	Loss	Terminating Impedance	Package Code
			dB	kHz	dB	kHz	dB	kHz	dB	dB	Ω //pF//pF	
P45U8AF	12.5 kHz	2	3	±3.75	10	±12.5	65	-910	1.0	2.0	200//4	A-5
P45U8BF		4	3	±3.75	30	±12.5	90	±910	1.0	4.0	350//6//21	A-5X2
P45U8CF		6	3	±3.75	50	±12.5	90	±910	2.0	6.0	350//5	D-5
P45U12AF	20 kHz	2	3	±6.0	15	±20.0	65	-910	1.0	2.0	500//5	A-5
P45U12BF		4	3	±6.0	35	±20.0	90	±910	1.0	3.0	500//4//12	A-5X2
P45U15AF	25 kHz	2	3	±7.5	15	±25.0	65	-910	1.0	2.0	650//3	A-5
P45U15BF		4	3	±7.5	35	±25.0	90	±910	1.0	3.0	300//4//21	A-5X2
P45U15AG		2	3	±7.5	15	±25.0	65	-910	1.0	2.0	350//1	A-5
P45U15BG		4	3	±7.5	35	±25.0	90	±910	1.0	3.0	650//3//9	A-5X2
P45U20AF		2	3	±10.0	15	±40.0	65	-910	1.0	2.0	800//3	A-5
P45U20BF		4	3	±10.0	35	±40.0	90	±910	1.0	3.0	800//2//7	A-5X2
P45U30AF	50 kHz	2	3	±15.0	10	±50.0	65	-910	1.0	2.0	1200//1.5	A-5
P45U30BF		4	3	±15.0	35	±50.0	90	±910	1.0	3.0	1200//1.5//4	A-5X2
P45U30AG		2	3	±15.0	10	±50.0	65	-910	1.0	2.0	800//2	A-5
P45U30BG		4	3	±15.0	35	±50.0	90	±910	1.0	3.0	800//1//6	A-5X2

HOW TO REACH US:

Pletronics, Inc.
19013-36th Avenue West, Suite H
Lynnwood, WA 98036 USA

(425) 776-1880
FAX: (425) 776-2760
email: ple-sales@pletronics.com

-
- ◆ [Home](#)
 - ◆ [Products](#)
 - ◆ [Contact Info](#)
 - ◆ [Company Info](#)
 - ◆ [Distributors](#)
 - ◆ [Representatives](#)
 - ◆ [Browser Settings](#)
-

Last modified 11/11/99
All specifications subject to change without notice.
Specification sheets and images, copyright 2001 Pletronics, Inc.