

Modern Digital Multimeter



Specifications:

Basic Functions	Range	Best Accuracy
DC Voltage	400mV/4V/40V/400V/1,000V	± (0.8% +1)
AC Voltage	4V/40V/400V/750V	± (1% +5)
DC Current	400μA/4,000μA/40mA/400mA/4A/10A	± (1% +2)
AC Current	400μA/4,000μA/40mA/400mA/4A/10A	± (1.5% +5)
Resistance	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	± (1% +2)
Capacitance	40nF/400nF/4μF/40μF/100μF	± (3% +5)
Temperature (°C)	-40°C to 1,000°C	± (1% +3)
Frequency	10Hz to 10MHz	± (0.1% +3)
Duty Cycle	0.1% to 99.9%	✓

Special Functions

Fused 10A Range		✓
Auto Ranging		✓
Diode		✓
Continuity Buzzer		✓
True RMS	AC	
Relative Mode		✓
Data Hold		✓
RS232C		✓
Display Backlight		✓
Full Icon Display		✓
Low Battery Display		✓
Input Impedance for DC Voltage Measurement	Around 10MΩ	✓
Max Display	3,999	✓

General Characteristics:

Power	9V Battery (6F22)
LCD Size	63mm × 31mm
Product Net Weight	320g
Product Size	177mm × 85mm × 40mm
Standard Accessories	Test Lead, Battery, English Manual, Test Clip, Software, RS232C Interface Cable, Point Contact Temperature Probe
Certifications	UL, cUL

Part Number Table

Description	Part Number
Modern Digital Multimeter	72-7745

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

