

## SmartPro 3kVA 2880W Line Interactive Sine Wave UPS, Extended-Run & SNMPWEBCARD options, 2U Rack/Tower, LCD, USB, RS232, EPO, 120V

#### MODEL NUMBER: SMART3000RMXL2U











#### Description

Tripp Lite SmartPro Line Interactive UPS with enhanced LCD interface offers network-grade power protection for critical server, network and telecommunications equipment. Line Interactive Uninterruptible Power Supply (UPS) with built-in Auto-Voltage Regulation (AVR) actively corrects brownouts and overvoltages back to usable levels while maintaining a full battery charge in case of power failure. Tripp Lite's unique configuration excels in exceptionally poor-power environments with two separate levels of voltage boost to correct both slight undervoltages and severe brownout conditions. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Super-fast switchover from line to battery power occurs within milliseconds to maintain operation of connected equipment without interruption or reboot. 96% line-mode efficiency offers reduced heat emissions and operating costs. Network management interfaces support communications via USB, RS-232 and optional SNMPWEBCARD network interface. HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Network communications ports enable detailed monitoring of equipment load levels, self-test data and utility power conditions. Includes PowerAlert monitoring software and complete cabling. Switched output load banks enable scheduled and real-time remote reboot and load shedding of select outlets. Emergency Power Off (EPO) interface. LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm with push-button momentary alarm-cancel and silent-mode configuration options. Programmable self-test. Field-replaceable, hot-swappable battery modules.

#### **Highlights**

- 3kVA / 3000VA / 2880W line interactive 2U rack/tower UPS, Sine Wave
- 120V output, Corrects brownouts and overvoltages from 83V to 145V
- 0.96 Power Factor, Interactive LCD interface
- Extended runtime options up to 2880W
- 4 post compatible mounting accessories
- 96% line-mode efficiency, 2 switched load banks
- USB, RS232, EPO and slot for SNMPWEBCARD option
- 120V NEMA L5-30P input, 8 NEMA 5-15/20R & 1 L5-30R outlets
- This product is ENERGY STAR qualified for its ability to save customers money while helping to protect the environment

#### **Applications**

Ideal for server, networking and telecommunications equipment

#### Package Includes

- SMART3000RMXL2U UPS system
- PowerAlert Software with USB, Serial & EPO cabling
- 4 post rackmount installation kit
- Instruction manual

#### **Features**

- Tripp Lite SMART3000RMXL2U line interactive 2U rack/tower UPS with 3000VA / 3kVA capacity and extended runtime options
- Line interactive UPS with Automatic Voltage Regulation (AVR) corrects brownouts and overvoltages from 83 to 145V
- NEMA L5-30P input plug; 8 NEMA 5-15/20R and 1 L5-30R output receptacles, Two independently switchable output load banks
- · Maintains uninterrupted operation of connected networking equipment during blackouts, surges, brownouts and overvoltages
- High 96% efficiency rating in line-power mode offers reduced power consumption and BTU emisssions

# Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com



- Internal batteries offer 10 minutes at 50% load (1440W) and 3 minutes at 100% load (2880W)
- Extended runtime is available with optional BP48V24-2U (limit 1), BP48V60RT-3U (multi-pack compatible) and BP48V27-2US (multi-pack compatible) external battery packs
- External battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- Hot-swappable, user-replaceable internal batteries and external battery packs can be replaced with no disruption to connected equipment
- Front panel LCD monitoring screen with MODE and ENTER buttons reports operating mode with 5-bar battery charge graphic, plus 7 selectable screens of detailed UPS and site power information
- LCD interface also supports a number of advanced user setup and operating preferences
- Ships with 4 post rackmount installation hardware; Optional 2POSTRMKITWM enables 2 post rackmount/wallmount installation; Optional 2-9USTAND enables tower placement
- Built-in USB, RS-232 and optional SNMPWEBCARD accessory monitoring options
- HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Included PowerAlert UPS monitoring software; Built-in Emergency Power Off (EPO) interface with cable

### **Specifications**

General Info			
Product Group	UPS SYSTEMS		
OUTPUT			
Output Volt Amp Capacity (VA)	3000		
Output kVA Capacity (kVA)	3		
Output Watt Capacity (Watts)	2880		
Output kW Capacity (kW)	2.88		
Power Factor	.96		
Nominal Output Voltage(s) Supported	120V		
Frequency Compatibility	60 Hz		
Output Voltage Regulation (Line Mode)	+6%, -14%		
Output Voltage Regulation (Battery Mode)	+/-5%		
UPS Output Receptacles	8 5-15/20R outlet(s); 1 L5-30R outlet(s)		
Output Receptacles	Two switchable single outlet 5-15/20R load banks		
Output Circuit Breakers	Two 20A output breakers protect 4 5-15/20R outlets each		
Output AC Waveform (AC Mode)	Pure Sine wave		
Output AC Waveform (Battery Mode)	Pure Sine wave		
INPUT			
Rated input current (Maximum Load)	24A		





Nominal Input Voltage(s) Supported	120V AC
UPS Input Connection Type	L5-30P
UPS Input Cord Length (ft.)	10
UPS Input Cord Length (m)	3
Recommended Electrical Service	30A 120V
Input Phase	Single-Phase
BATTERY	
Full Load Runtime (min.)	3 min. (2880w)
Half Load Runtime (min.)	10 min. (1440w)
Expandable Battery Runtime	Extended runtime supported via optional external battery packs
External Battery Pack Compatibility	BP48V24-2U (limit 1); BP48V60RT-3U (multi-pack compatible); BP48V27-2US (multi-pack compatible)
DC System Voltage (VDC)	48
Battery Recharge Rate (Included Batteries)	Less than 5 hours from 10 to 90% (typical, full load discharge)
Internal UPS Replacement Battery Cartridge	RBC58-2U
Battery Access	Front panel battery access door
Battery Access  Battery Replacement Description	Front panel battery access door  Hot-swappable, replaceable batteries
Battery Replacement Description	
Battery Replacement Description  VOLTAGE REGULATION	Hot-swappable, replaceable batteries
VOLTAGE REGULATION  Voltage Regulation Description	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%  Input voltages between 108 and 96 are boosted by 12%
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%  Input voltages between 108 and 96 are boosted by 12%
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  LEDS ALARMS & SWITCHES	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%  Input voltages between 108 and 96 are boosted by 12%  Input voltages between 83 and 95 are boosted by 24%  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  LEDS ALARMS & SWITCHES  Front Panel LCD Display	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%  Input voltages between 108 and 96 are boosted by 12%  Input voltages between 83 and 95 are boosted by 24%  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  LEDS ALARMS & SWITCHES  Front Panel LCD Display  Audible Alarm	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%  Input voltages between 108 and 96 are boosted by 12%  Input voltages between 83 and 95 are boosted by 24%  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  LEDS ALARMS & SWITCHES  Front Panel LCD Display  Audible Alarm  Alarm Cancel Operation	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145 Input voltages between 127 and 145 are reduced by 12% Input voltages between 108 and 96 are boosted by 12% Input voltages between 83 and 95 are boosted by 24%  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  LEDS ALARMS & SWITCHES  Front Panel LCD Display  Audible Alarm  Alarm Cancel Operation  Switches	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145 Input voltages between 127 and 145 are reduced by 12% Input voltages between 108 and 96 are boosted by 12% Input voltages between 83 and 95 are boosted by 24%  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option
Battery Replacement Description  VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  LEDS ALARMS & SWITCHES  Front Panel LCD Display  Audible Alarm  Alarm Cancel Operation  Switches  SURGE / NOISE SUPPRESSION	Hot-swappable, replaceable batteries  Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145  Input voltages between 127 and 145 are reduced by 12%  Input voltages between 108 and 96 are boosted by 12%  Input voltages between 83 and 95 are boosted by 24%  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions



PHYSICAL		
Installation Form Factors Supported with Included Accessories	4 post 19 inch rackmount	
Installation Form Factors Supported with Optional Accessories	2 post rackmount (2POSTRMKITWM); Wallmount (2POSTRMKITWM); Tower (2-9USTAND)	
Primary Form Factor	Rackmount	
UPS Power Module Dimensions (hwd, in.)	3.5 x 17.5 x 19	
UPS Power Module Dimensions (hwd, cm)	8.9 x 44.4 x 48.3	
Rack Height	2U	
Secondary Form Factor	Tower (requires 2-9USTAND)	
UPS Power Module Weight (lbs.)	72.8	
UPS Power Module Weight (kg)	33.1	
UPS Shipping Dimensions (hwd / in.)	9 x 23.5 x 20	
UPS Shipping Dimensions (hwd / cm)	22.9 x 59.7 x 50.8	
Shipping Weight (lbs.)	84.6	
Shipping Weight (kg)	38.4	
Cooling Method	Fan	
UPS Housing Material	Steel	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	409	
AC Mode Efficiency Rating (100% Load)	96%	
COMMUNICATIONS		
Communications Interface	USB (HID enabled); DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface	
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions	
PowerAlert Software	Included	
Communications Cable	USB, DB9 and EPO cabling included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Network UPS Tools Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at http://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite	





LINE / BATTERY TRANSFER			
Transfer Time	5 milliseconds (AC to battery mode), 1 millisecond (Battery to AC mode)		
Low Voltage Transfer to Battery Power (Setpoint)	83		
High Voltage Transfer to Battery Power (Setpoint)	145		
SPECIAL FEATURES			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Hot swappable batteries		
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS; Individually controllable load banks; Schedulable daily hours of economy mode operation		
CERTIFICATIONS			
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category A (EMI); ENERGY STAR Qualified		
WARRANTY			
Product Warranty Period (Worldwide)	2-year warranty, 3 year with registration. Note: Registration is required for 3-year warranty.		
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance		

© 2014 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.