



Variable Transformers

Single Phase - 1 A to 28 A




Features:

- Low cost
- Precision wound
- Rugged construction
- Standard connections
- Simple to use
- Easy to install
- Open Wound
- Input voltage : 240 V ac
- Output voltage : 0 to 240 / 270 V ac



Single Phase Variac



Installation and Safety Instructions:

1. Installation, commissioning and maintenance should only be carried out by suitably qualified personnel
2. Read all of the instructions before you use the transformer
3. The input must always be applied across the appropriate terminals. Never connect the transformer in series with the load
4. The transformer should be properly earthed using the earth stud or earth terminal
5. This transformer operates at mains Voltage. Do not exceed the maximum voltage and current rating
6. This transformer is not designed to provide mains isolation
7. Please note that when connected to the electrical supply the terminal brushes and tracks surface are at mains voltage which is potentially lethal
8. The carbon brushes should be inspected for damage or wear, faulty or over worn brushes will result in damage to the windings

Variable Transformers

Single Phase - 1 A to 28 A



Specification Table

Maximum Current Rating (A)	Maximum VA	Height (Excluding Knob) (H)	Overall Width (A)	Overall Diameter (B)	Fixing Centres (C × D)	Diameter Fixing Hole	E	F	Height of the Knob (G)	Approximate Weight (Kg)	Part Number
1	240	99	83	99	-	-	-	-	20	1.55	MC1F-1
2	480	95	110		92 × 92	7.5	10	6	25	2.9	MC2F-1
3	720	115								3.3	MC3F-1
6	1,440	110	175		146 × 146	10	25		35	6.8	MC6F-1
10	1,920	130								8.1	MC8F-1
	2,400	135						9		MC10F-1	
15	3,600		225		176 × 176	11		10		12	MC15F-1
20	4,800	145								15	MC20F-1
28	6,720	160	300		238 × 238	13	60			22	MC28F-1

Dimensions : Millimetres

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.