

TOSHIBA Transistor Silicon PNP Epitaxial Type (PCT Process)


RN2412,RN2413

Switching, Inverter Circuit, Interface Circuit
And Driver Circuit Applications

Unit in mm


- With built-in bias resistors
- Simplify circuit design
- Reduce a quantity of parts and manufacturing process
- Complementary to RN1412, RN1413

Equivalent Circuit



Maximum Ratings (Ta = 25°C)

Characterisitic	Symbol	Rating	Unit
Collector-base voltage	V_{CBO}	-50	V
Collector-emitter voltage	V_{CEO}	-50	V
Emitter-base voltage	V_{EBO}	-5	V
Collector current	I_C	-100	mA
Collector power dissipation	P_C	200	mW
Junction temperature	T_j	150	°C
Storage temperature range	T_{stg}	-55~150	°C







Weight: 0.012g






000707EAA1



- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.

Electrical Characteristics (Ta = 25°C)

Characteristic		Symbol	Test Circuit	Test Condition	Min	Typ.	Max	Unit
Collector cut-off current		ICBO	—	V _{CB} = -50V, I _E = 0	—	—	-100	nA
Emitter cut-off current		IEBO	—	V _{EB} = -5V, I _C = 0	—	—	-100	nA
DC current gain		h _{FE}	—	V _{CE} = -5V, I _C = -1mA	120	—	400	—
Collector-emitter saturation voltage		V _{CE} (sat)	—	I _C = -5mA, I _B = -0.25mA	—	-0.1	-0.3	V
Translation frequency		f _T	—	V _{CE} = -10V, I _C = -5mA	—	250	—	MHz
Collector output capacitance		C _{ob}	—	V _{CB} = -10V, I _E = 0, f = 1MHz	—	3	6	pF
Input resistor	RN2412	R1	—	—	15.4	22	28.6	kΩ
	RN2413				32.9	47	61.1	





Type Name	Marking
RN2412	 <p>The diagram shows a rectangular component with two pins at the top and two at the bottom. Inside the rectangle, the characters 'Y N' are printed. A leader line points from the text 'Type Name' to the 'Y' character.</p>
RN2413	 <p>The diagram shows a rectangular component with two pins at the top and two at the bottom. Inside the rectangle, the characters 'Y P' are printed. A leader line points from the text 'Type Name' to the 'Y' character.</p>