



PRODUCT DATASHEET

Tina3 series

last update 2/11/2012


DETAILS

Product Number	CA13178_TINA3-WW
Family	Tina3
Type	Assembly
Color	white
Diameter	16.1 mm
Height	6.8 mm
Style	round
Optic Material	PMMA
Holder Material	PC
Fastening	tape
Status	ready
ROHS Compliant	Yes
Date Updated	2/11/2012



OPTICAL PROPERTIES

LED	Viewing Angle	Light Beam	Efficiency	cd/lm	connector
LUXEON Rebel ES	61 degrees		91 %	0.900	-



Materials

Lens: PMMA
Holder: PC
Tape: PU Foam

This drawing is our property.
It can't be reproduced
or communicated without
our written agreement.




Ledil Oy
Salorankatu 10
FIN 24240 SALO
Finland


DRAWING TITLE				Mechanical Drawing	
TINA3-RE-ES					
SIZE	PART NUMBER			REV	
A4				001	
SCALE	3 : 1	WEIGHT	-	SHEET	1 / 1

DRAWN BY	DATE
as	21.9.2012
CHECKED BY	DATE
VS	-
DESIGNED BY	DATE
-	-

Luminaire: Ledil oy CA13178_TINA3-WW (Luxeon Rebel-ES 92lm @ 250mA) Efficiency=91%
Lamps: 1 x Luxeon Rebel-ES 92lm @ 250mA



Luminaire: Ledil oy CA13178_TINA3-WW (Luxeon Rebel-ES 92lm @ 250mA) Efficiency=91%
Lamps: 1 x Luxeon Rebel-ES 92lm @ 250mA



NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.

GENERAL INFORMATION

- Product series especially designed & optimized for series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: http://www.ledil.com/datasheets/DataSheet_TAPE.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit board weaken the strength of the tape.

NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.

If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.