

Manual Switches

Buttons/Lens for Switches and Indicators

AML51 Series

AML51 PUSHBUTTON ORDER GUIDE

For Incandescent or non-lighted display switches and pushbutton style indicators.

AML51-C	10	R	—
For AML11, 21, 31 switches and AML41 indicators: Pushbutton Style	Display Legend/Type	Full Color or 1st Color Split	2nd Color Split
AML51-C AML51-F AML51-G AML51-A AML51-H AML51-N* AML51-B* AML51-E* AML51-M* AML51-R*	Transmitted Color 10 No legend 20 With legend on cap. Transmitted Color (Clear cap and color insert) 11 No legend 21 With legend on insert Dead Front (Smoky gray cap and color insert) 30 No legend 40 With legend on insert Projected Color (White cap and color insert) 50 No legend 60 With legend on cap	R Red Y Yellow G Green B Blue W White K*** Black L*** Gray A** Amber	R Red Y Yellow G Green B Blue W White K*** Black L*** Gray A** Amber
For AML41D indicators only: AML51-D		Example: AML51-C10R Square full color button; with transmitted color, no legend: red. ** Available with transmitted color and dead front only. *** Black and gray not recommended for lighted display. * AML51-N buttons not available with Display/Legend Types 10 and 20. Note: Dimensions include the .060 in bezel.	

* Available with transmitted color (10 or 20) only.

AML51 LENS ORDER GUIDE

For incandescent display AML41J, K, and L lens style indicators only.

AML51-J	10	R
Lens style	Display/Legend Type	Full Color or 1st Color Split2nd Color Split3rd Color Split
AML51-J AML51-K AML51-L	Transmitted Color 10 No legend 20 With legend Transmitted Color (Clear cap and color insert) 11 No legend 21 With legend Dead Front (Smoky gray cap and color insert) 30 No legend 40 With legend Projected Color (White cap and color insert) 50 No legend 60 With legend	R Red Y Yellow G Green B Blue W White A** Amber

** Not available with projected color.

AML51 lens buttons provide added display area by snapping onto and covering the bezel of AML41J, K, and L indicators. They do not fit other indicators or switches.

Example: **AML51-J10R**
Rectangular lens type button; full color; transmitted color, no lended; red.

HOW TO ORDER BUTTON LEGENDS
When specifying legended buttons, submit a legend order sheet to cover each listing. To insure proper legend orientation, AML housings (when viewed from the panel front) should have the “MICRO SWITCH” identification facing UP on square devices and UP or to the LEFT on rectangular.

Button legend order sheets are shown on the following pages. Reproduce them on your office copier.	
Legend Sheet	Form No.
AML51 Pushbuttons	FO-63394
AML51 Lens buttons	FO-63395
AML52 Pushbuttons	FO-63504
AML53 Paddle switch covers	FO-63567
AML55 Paddle switch covers	FO-63565
AML54 Rockers	FO-63566
AML56 Rockers	FO-63564

Manuals

Manual Switches

Pushbutton Legend Sheet

AML51 Series

Honeywell

AML Pushbutton Legend Sheet

Account NO 126 - 284

LEGEND ORDER GUIDE

Button: Type Orientation	Figure NO	Max Lines/Area					Max Characters/Line				
		5/64	7/64	9/64	13/64	5/16	5/64	7/64	9/64	13/64	5/16
1 AREA	1	4	3	3	2	1	7	5	5	3	1
2 AREA	2	4	3	3	2	1	7	5	5	3	1
3 AREA	3	4	3	3	2	1	7	5	5	3	1
4 AREA	4	4	3	3	2	1	7	5	5	3	1
5 AREA	5	6	4	4	3	2	11	9	8	5	3
6 AREA	6	4	3	3	2	1	7	5	5	3	1
7 AREA	7	6	4	4	3	2	11	9	8	5	3
8 AREA	8	1	1	1	1	0	10	8	7	5	3
9 AREA	9	5	4	4	3	2	11	9	8	5	3

Definitions of Markings

- Thru holes to snap into indicator housings
- Internal reliefs to snap over switch plunger tabs

Standard Legend Placement -

- Use special legends sec. for other placements
- Transmitted Color - Legend on outer shell (Button)
 - Dead Front - Legend on Insert
 - Projected Color - Legend on outer shell (Button)
 - Transmitted color with clear cap legend on insert

LEGEND ORDER CHART

Customer Part No	Fig No	Type Size					Ink Color		But- ton Qty	1st Line						2nd Line						3rd Line						4th Line						5th Line						6th Line																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																		
		5/64 7/64 9/64 13/64 5/16					Black	White																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																		
									1																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																	</

FO-83384-J

Catalog Listing
AML51 -
Customer P.O. No. _____ Customer Dwg. No. _____

MICRO SWITCH Sales Order _____ Line Number _____ Schedule No. _____

Customer: _____

Address: _____ (city) _____ (state) _____

Instructions

- Fill in appropriate catalog listing - one listing/sheet.
- Check proper figure #. Type size, Type color.
- Fill in quantity required.
- Indicate legends desired — Do not exceed maximums shown in legend order guide.

Note

- For Proper Legend Orientation, AML housings (when viewed from front of panel) should have "MICRO SWITCH" logo oriented "Up" on square devices and "UP" or to the "LEFT" on rectangular devices.
- Please use black ink in filling out this form to help us process your order.
- INSERT ONLY ON STYLE A & H BUTTON

SPECIAL LEGENDS

NOTE: Use this area to show special Legend Locations or Configurations NOT shown to the left. NON-STANDARD legends will involve additional charges and increased delivery time.

A3

Modified Gothic

Modified Gothic lettering (A thru Z), numerals (0 thru 9) and Symbols below available in 5/64, 7/64, 9/64, 13/64 and 5/16.

.	,	:	;	!	?	'	-	"	/	(	)	*	&
\$	¢	#	%	°	+	-	±	÷	x	=	≠	>	<
→	↑	↓	←	↖	↗	↘	↙	↕	↔	↞	↠	↡	↢

Sheet prepared by: _____

(Signature)

(Date)

Manual Switches
Lens Legend Sheet

AML51 Series

Honeywell

AML Lens Legend Sheet

Account No _____

LEGEND ORDER GUIDE

Buttom: Type Orientation	Figure No	Max Lines					Max Characters				
		5/64	7/64	9/64	13/64	5/16	5/64	7/64	9/64	13/64	5/16
AREA 1 J	1	4	3	3	2	1	14	11	10	7	3
AREA 1 2 K	2	4	3	3	2	1	13	10	9	6	3
AREA 1 2 3 L	3	4	3	3	2	1	6	6	5	3	1
AREA 1 J	4	4	3	3	2	2	4	3	3	2	1
AREA 1 2 K	5	3	3	2	2	1	9	7	7	4	2
AREA 1 2 3 L	6	2	2	1	1	0	8	7	6	3	2

Standard Legend Placement

- 1. Transmitted Color — Legend on outer shell (Button)
- 2. Dead Front - Legend on insert
- 3. Projected Color - Legend on outer shell (Button)

LEGEND ORDER CHART

Customer Part No	Fig No	Type Size			Ink Color	But ton Qty	Legend Description			
		5/64	7/64	9/64			Sequence: Left-to-Right or Top-to-Bottom			
							1st Line	2nd Line	3rd Line	4th Line
						1				
						2				
						3				
						1				
						2				
						3				
						1				
						2				
						3				

FO-63856-D

Sheet Prepared By: _____

(Signature)

(Date)

Manuals

Catalog Listing AML51 —	
Customer P.O. No.	Customer Dwg. No.
MICRO SWITCH Sales Order	Line Number
	Schedule No.

Customer: _____

Address: _____

(city)

(state)

Instructions

- 1. Fill in appropriate catalog listing - one listing/sheet.
- 2. Check proper figure #. Type size, type color.
- 3. Fill in quantity required.
- 4. Indicate legends desired — Do not exceed maximums shown in legend order guide.

Note

- 1. For Proper Legend Orientation, AML housings (when viewed from front of panel) should have "MICRO SWITCH" logo oriented "UP" on square devices and "UP" or to the "LEFT" on rectangular devices.
- 2. Please use black ink in filling out this form to help us process your order.

Modified Gothic lettering (A thru Z), numerals (0 thru 9) and Symbols below available in 5/64, 7/64, 9/64, 13/64 and 5/16.	A3
Modified Gothic	
. , : ; ! ? ' _ " / () * &	
\$ ¢ # % 0 + - ± ÷ × = ≠ ∞ ∞	
→ ↑ ↓ ← CR 1/41/23/41/3 2/3 @	

SPECIAL LEGENDS

NOTE: Use this area to show special Legend Locations or Configurations NOT shown above. NON-STANDARD legends will involve additional charges and increased delivery time.

Fig. "A"	Fig. "B"
----------	----------