Manual Switches

Buttons/Lens for Switches and Indicators

AML51 PUSHBUTTON ORDER GUIDE (All possible color combinations may not be available.)

For Incandescent or non-lighted display switches and pushbutton style indicators.

AML51-C | **10** | **R** | —

For AML11, 21, 31 switches and AML41 indicators: Pushbutton Style



AML51-C



AML51-F



AML51-G



AML51-A



AML51-H



AML51-N★



AML51-B*



AML51-E*



AML51-M*



AML51-R*

For AML41D indicators only:



AML51-D

Display Legend/Type

Transmitted Color
10 No legend
20 With legend on cap.

Transmitted Color (Clear cap and color insert)
11 No legend
21 With legend on insert

Dead Front (Smoky gray cap and color insert)
30 No legend
40 With legend on insert

******Projected Color** (White cap and color insert)
50 No legend
60 With legend on cap

Full Color or 1st Color Split

R Red
Y Yellow
G Green
B Blue
W**** White
K*** Black
L*** Gray
A** Amber

2nd Color Split

R Red
Y Yellow
G Green
B Blue
W**** White
K*** Black
L*** Gray
A** Amber

Example: **AML51-C10R**
Square full color button; with transmitted color, no legend; red.

**Available with transmitted color and dead front only.
***Black and gray not recommended for lighted display.
†AML51-N buttons not available with Display/Legend Types 10 and 20.
Note: Dimensions include the .060 in bezel.

*Available with transmitted color (10 or 20) only.
****Insert is clear for projected color when ''W'' is used.

AML51 LENS ORDER GUIDE (All possible color combinations may not be available.)

For incandescent display AML41J, K, and L lens style indicators only.

AML51-J | **10** | **R**

Lens style



AML51-J



AML51-K



AML51-L

Display/Legend Type

Transmitted Color
10 No legend
20 With legend

Transmitted Color (Clear cap and color insert)
11 No legend
21 With legend

Dead Front (Smoky gray cap and color insert)
30 No legend
40 With legend

******Projected Color** (White cap and color insert)
50 No legend
60 With legend

Full Color or 1st Color Split	2nd Color Split	3rd Color Split
R Red	**R** Red	**R** Red
Y Yellow	**Y** Yellow	**Y** Yellow
G Green	**G** Green	**G** Green
B Blue	**B** Blue	**B** Blue
W**** White	**W****** White	**W****** White
A** Amber	**A**** Amber	**A**** Amber

**Not available with projected color.
****Insert is clear for projected color when ''W'' is used.

AML51 lens buttons provide added display area by snapping onto and covering the bezel of AML41J, K, and L indicators. They do not fit other indicators or switches.

Example: **AML51-J10R**
Rectangular lens type button; full color; transmitted color, no legend; red.

HOW TO ORDER BUTTON LEGENDS

When specifying legended buttons, submit a legend order sheet to cover each listing. To insure proper legend orientation, AML housings (when viewed from the panel front) should have the ''MICRO SWITCH'' identification facing UP on square devices and UP or to the LEFT on rectangular.

Button legend order sheets are shown on the following pages. Reproduce them on your office copier.

Legend Sheet	Form No.
AML51 Pushbuttons	FO-63394
AML51 Lens buttons	FO-63395
AML52 Pushbuttons	FO-63504
AML53 Paddle switch covers	FO-63567
AML55 Paddle switch covers	FO-63565
AML54 Rockers	FO-63566
AML56 Rockers	FO-63564

Buttons for Switches and Indicators

AML52 BUTTON ORDER GUIDE (All possible color combinations may not be available.)
For AML12, AML22 (w/o light pipe), AML32, AML42 LED display.

AML52-N | **10** | **R**

Button Type	Display/Legend Type	Button Color
For LED Devices **AML52-C** **AML52-A***  **For AML32 Neon Devices** **AML52-N** 	**Transmitted Color** **10** No Legend **20** With Legend	**R** Red **Y** Yellow **G** Green **B** Blue **W** White **K** Black **A** Amber **L** Gray

Examples:
AML52-N10R
Rectangular full screen; for use on neon power switch with transmitted color, no legend; red button.

AML52-C10K
Square full screen; for use with LED device; transmitted color, no legend; black button.

Honeywell

AML 52/57 Pushbutton Legend Sheet/Product Specification for L.E.D. & Neon Button

Page ____ of _____

Account No _____

Catalog Listing AML52 –		
Customer P.O. No.	Customer Dwg. No.	
MICRO SWITCH Sales Order	Line Number	Schedule No.

Customer: _____

Address: _____

(city) (state)

LEGEND ORDER GUIDE

Button: Type Orientation	Figure NO	Max Lines 5/64	7/64	9/64	13/64	5/16	Max Characters 5/64	7/64	9/64	13/64	5/16
C	1	3	2	1	1	1	7	5	5	3	1
C	2	3	2	1	1	1	7	5	5	3	1
N	3	1	1	0	0	0	12	10	0	0	0
N	4	1	1	0	0	0	12	10	0	0	0
A	5	3	2	1	1	1	7	5	4	3	1
A	6	3	2	1	1	1	7	5	4	3	1

Instructions

1. Fill in appropriate catalog listing - one listing/sheet.
2. Check proper figure #. Type size, type color.
3. Fill in quantity required.
4. Indicate legends desired — Do not exceed maximums shown in legend order guide.

Note

1. For Proper Legend Orientation, AML housings (when viewed from front of panel) should have "MICRO SWITCH" logo oriented "UP" on square devices and "UP" or to the"LEFT" on rectangular devices.
2. Please use black ink in filling out this form to help us process your order.

Standard Legend Placement

1. Transmitted Color — Legend on outer shell (Button)
2. Figures 3 and 4 not applicable for AML57 listings

LEGEND ORDER CHART

Customer Part NO	Fig NO	Type Size 5/64	7/64	9/64	13/64	5/16	Ink Color Black	White	Button Qty	Legend Description Sequence: Left-to-Right or Top-to=Bottom 1st Line	2nd Line	3rd Line

Sheet Prepared By: _____ _____
(Signature) (Date)

FO-63504-D

Modified Gothic lettering (A thru Z). numerals (0 thru 9) and Symbols below available in 5/64, 7/64, 9/64, 13/64 and 5/16.

A3
Modified Gothic

.	,	:	;	!	?	'	_	"	/	(	)	*	&
$	¢	#	%	º	+	-	±	÷	x	=	≠	>	<
→	↑	↓	←	C_R	1/4	1/2	3/4	1/3	2/3	@	∞		

SPECIAL LEGENDS

NOTE: Use this area to show special Legend Locations or Configurations NOT shown above. NON-STANDARD legends will involve additional charges and increased delivery time.

Fig. "A" Fig. "B"

Honeywell

AML Pushbutton Legend Sheet/Product Specification

Account NO 126 - 284

Page____of_____

LEGEND ORDER GUIDE

Button: Type Orientation	Figure NO	Max Lines/Area 5/64	7/64	9/64	13/64	5/16	Button Filler	Max Characters/Line 5/64	7/64	9/64	13/64	5/16
AREA 1 A*B P,R	1	4/*3	3/*2	3/*2	2/*1	1/*1		7/*5	5/*4	5/*3	3/*2	1/*1
AREA 1 C	2	4/3	3/2	3/2	2/1	1/1		7/5	5/4	5/3	3/2	1/1
AREA 1 2 D	3	1/1	1/1	1/1	0/0	0/0		7/5	5/4	5/3	0/0	0/0
AREA 1 E,H*	4	4/*3	3/*2	3/*2	2/*1	1/*1		11/*10	9/*8	8/*7	5/*5	3/*3
AREA 1 E,H*	5	6/*6	4/*4	4/*4	3/*3	2/*2		7/*5	5/*4	5/*3	3/*2	1/*1
AREA 1 F	6	4/3	3/2	3/2	2/1	1/1		11/10	9/8	8/7	5/5	3/3
AREA 1 F	7	6/6	4/4	4/4	3/3	2/2		7/5	5/4	5/3	3/2	1/1
AREA 1 2 G,N	8	1/1	1/1	1/1	0/0	0/0		11/10	9/8	8/7	0/0	0/0
AREA 1 M	9	5/0	4/0	3/0	2/0	1/0		8/0	6/0	6/0	3/0	1/0

Definitions of Markings

Thru holes to snap into indicator housings

Internal reliefs to snap over switch plunger tabs

Standard Legend Placement –

Use special legends sec. for other placements

1. Transmitted Color — Legend on outer shell (Button)
2. Dead Front - Legend on Insert
3. Projected Color - Legend on outer shell (Button)
4. Transmitted color with clear cap legend on insert

Catalog Listing AML51 –		
Customer P.O. No.	Customer Dwg. No.	
MICRO SWITCH Sales Order	Line Number	Schedule No.

Customer: _____

Address: _____
(city) (state)

Instructions

1. Fill in appropriate catalog listing - one listing/sheet.
2. Check proper figure #. Type size, Type color.
3. Fill in quantity required.
4. Indicate legends desired — Do not exceed maximums shown in legend order guide.

Note

1. For Proper Legend Orientation, AML housings (when viewed from front of panel) should have "MICRO SWITCH" logo oriented "UP" on square devices and "UP" or to the"LEFT" on rectangular devices.
2. Please use black ink in filling out this form to help us process your order.
3. * INSERT ONLY ON STYLE A & H BUTTON

Modified Gothic lettering (A thru Z). numerals (0 thru 9) and Symbols below available in 5/64, 7/64, 9/64, 13/64 and 5/16.

A3
Modified Gothic

STANDARD SYMBOLS AVAILABLE

.	,	:	;	!	?	'	_	"	/	(	)	*	&
$	¢	#	%	º	+	-	±	÷	x	=	≠	>	<
→	↑	↓	←	C_R	1/4	1/2	3/4	1/3	2/3	@	∞		

SPECIAL LEGENDS

NOTE: Use this area to show special Legend Locations or Configurations NOT shown to the left. NON-STANDARD legends will involve additional charges and increased delivery time.

Fig. "A" | Fig. "B"

LEGEND ORDER CHART

Customer Part No	Fig No	Type Size 5/64	7/64	9/64	13/64	5/16	Ink Color Black	White	Button Qty	AREA	1st Line	2nd Line	3rd Line	4th Line	5th Line	6th Line
										1						
										2						
										1						
										2						
										1						
										2						
										1						
										2						

Sheet prepared by:

_____
(Signature)

_____
(Date)

FO-63394-K

Manuals

Honeywell

AML Lens Legend Sheet/Product Specification

Page ____ of _____

Account No _____

LEGEND ORDER GUIDE

Button: Type Orientation	Figure No	Max Lines 5/64	7/64	9/64	13/64	5/16	Button Filter	Max Characters 5/64	7/64	9/64	13/64	5/16
AREA 1 J	1	4/4	3/3	3/3	2/2	1/1		14/13	11/10	10/9	7/6	3/3
AREA 1 2 K	2	4/4	3/3	3/3	2/2	1/1		6/5	6/5	6/5	3/3	1/1
AREA 1 2 3 L	3	4/4	3/3	3/3	2/2	1/1		4/3	3/3	3/3	2/1	1/1
AREA 1 J	4	4/4	3/3	3/3	3/3	2/2		9/8	7/6	7/6	4/3	2/2
AREA 1 2 K	5	3/3	2/2	2/2	1/1	1/1		8/7	7/6	7/6	4/3	2/2
AREA 1 2 3 L	6	2/2	1/1	1/1	1/1	0/0		8/7	7/6	7/6	4/3	0/0

Standard Legend Placement

1. Transmitted Color — Legend on outer shell (Button)
2. Dead Front - Legend on Insert
3. Projected Color - Legend on outer shell (Button)

Catalog Listing AML51 –		
Customer P.O. No.	Customer Dwg. No.	
MICRO SWITCH Sales Order	Line Number	Schedule No.

Customer: _____

Address: _____
(city) (state)

Instructions

1. Fill in appropriate catalog listing - one listing/sheet.
2. Check proper figure #. Type size, type color.
3. Fill in quantity required.
4. Indicate legends desired — Do not exceed maximums shown in legend order guide.

Note

1. For Proper Legend Orientation, AML housings (when viewed from front of panel) should have "MICRO SWITCH" logo oriented "UP" on square devices and "UP" or to the"LEFT" on rectangular devices.
2. Please use black ink in filling out this form to help us process your order.

LEGEND ORDER CHART

Customer Part No	Fig No	Type Size 5/64	7/64	9/64	13/64	5/16	Ink Color Black	White	Button Qty	AREA	Legend Description Sequence: Left-to-Right or Top-to=Bottom 1st Line	2nd Line	3rd Line	4th Line
										1				
										2				
										3				
										1				
										2				
										3				
										1				
										2				
										3				
										1				
										2				
										3				

Modified Gothic lettering (A thru Z). numerals (0 thru 9) and Symbols below available in 5/64, 7/64, 9/64, 13/64 and 5/16.

A3
Modified Gothic

.	,	:	;	!	?	'	_	"	/	(	)	*	&	
$	¢	#	%	°	+	-	±	÷	x	=	≠	>	<	
→	↑	↓	←	C_R	1/4	1/2	3/4	1/3	2/3	@	∞			

SPECIAL LEGENDS

NOTE: Use this area to show special Legend Locations or Configurations NOT shown above. NON-STANDARD legends will involve additional charges and increased delivery time.

Fig. "A" | Fig. "B"

FO-63395-E

Sheet Prepared By: _____ _____
(Signature) (Date)