

Basestation product portfolio

1-GHz finals and drivers

Product	Package	Matching	Mode of operation	Frequency band (min - max)	Output power	Power gain	Efficiency	Intermodulation distortion (IM3)	Adjacent channel leakage ratio (ACLR)	Adjacent channel power ratio @400kHz (ACPR400)	Adjacent channel power ratio @ 600 kHz (ACPR600)	Error vector magnitude (EVM)	Thermal resistance (Rth)
		(I/O)		(MHz)	(W)	(dB)	(%)	(dBc)	(dBc)	(dBc)	(dBc)	(%)	(K/W)
Finals													
BLF6G10LS-200R	SOT502B	I/O	2C W-CDMA	869 - 894	40	20	27	-	-40	-	-	-	0.35
BLF6G10LS-160	SOT502B	I	2C W-CDMA	800 - 1000	32	22	27	-	-42	-	-	-	0.42
BLC6G10LS-160	SOT896B	I	2C W-CDMA	800 - 1000	32	22.5	27	-	-42	-	-	-	0.42
BLC6G10-160	SOT895A	I	2C W-CDMA	800 - 1000	32	22.5	27	-	-42	-	-	-	0.61
BLF6G10LS-135R	SOT502B	I/O	2C W-CDMA	869 - 894	26	21	28.5	-	-40	-	-	-	0.56
Drivers													
BLF6G10S-45	SOT608B	I/O	CW 2C W-CDMA	800 - 1000	45 1	23.5 23	60 8	-	-50	-	-	-	1.70
BLF6G10-45	SOT608A	I/O	CW 2C W-CDMA	800 - 1000	45 1	23.5 22.5	60 7.8	-	-50	-	-	-	1.70
BLF6G21-15	SOT538A	-	CW	800 - 4000	10	TBD	10	-45	-48	-	-	-	TBD
BLF3G21-30	SOT467C	-	2-Tone PHS class A	HF - 2200	30 9	13.5 16	35 20	-26	-	-	-75	-	1.60
BLF3G21-6	SOT538A	-	2-Tone PHS class A	HF - 2200	6 2	13.5 16	35 20	-23	-	-	-75	-	10
BLF1046	SOT467C	-	CW	HF - 1000	50	16	60	-	-	-	-	-	1.87
BLF1822-10	SOT467C	-	CW	HF - 2200	12	13	40	-	-	-	-	-	5
BLF1043	SOT538A	-	CW	HF - 1000	10	18.5	55	-	-	-	-	-	9
BGF802-20	SOT365C	-	CW CDMA	869 - 894	25 3	30	50 18	-	-69	-	-	-	-
BGF844	SOT365C	-	CW EDGE	869 - 894	23 2.5	30	50 16	-	-	-65	-	0.4	-
BGF944	SOT365C	-	CW EDGE	920 - 960	17 2.5	30	50 16	-	-	-65	-	0.4	-

Basestation product portfolio

2-GHz finals and drivers











Product	Package	Matching	Mode of operation	Frequency band (min - max)	Output power	Power gain	Efficiency	Intermodulation distortion (IM3)	Adjacent channel leakage ratio (ACLR)	Adjacent channel power ratio @400kHz (ACPR400)	Adjacent channel power ratio @ 600 kHz (ACPR600)	Error vector magnitude (EVM)	Thermal resistance (Rth)
		(I/O)		(MHz)	(W)	(dB)	(%)	(dBc)	(dBc)	(dBc)	(dBc)	(%)	(K/W)
Finals													
BLF6G20-180PN	SOT539A	I/O	2C W-CDMA	1800 - 2000	50	18	29.5	-35	-	-	-	-	0.45
BLF6G20LS-180R	SOT502B	I/O	2C W-CDMA	1800 - 2000	40	17	27	-41	-37	-	-	-	0.35
BLF6G20-180R	SOT502A	I/O	2C W-CDMA	1800 - 2000	40	17	27	-41	-37	-	-	-	TBD
BLF6G20LS-140	SOT896B	I/O	2C W-CDMA	1800 - 2000	35.5	16.5	30	-37	-40	-	-	-	0.49
BLF6G20LS-110	SOT502B	I/O	2C W-CDMA	1800 - 2000	25	18	31	-37	-40	-	-	-	0.45
BLF6G20-110	SOT502A	I/O	2C W-CDMA	1800 - 2000	25	19	31	-37	-40	-	-	-	0.52
BLC6G20LS-110	SOT896B	I/O	2C W-CDMA	1800 - 2000	25	19	32	-37	-40	-	-	-	0.45
BLC6G20-110	SOT895A	I/O	2C W-CDMA	1800 - 2000	25	18	32	-37	-40	-	-	-	TBD
BLF6G20LS-75	SOT502B	I/O	CW EDGE	1800 - 2000	63 29.5	19 19	52 37.5	-	-	-61.5	-73	1.7	0.75
BLF6G20-75	SOT502A	I/O	CW EDGE	1800 - 2000	63 29.5	19 19	52 37.5	-	-	-61.5	-73	1.7	TBD
BLC6G20LS-75	SOT896B	I/O	CW EDGE	1800 - 2000	63 29.5	19 19	57 40	-	-	-61.5	-72	0.9	0.75
BLC6G20-75	SOT895A	I/O	CW EDGE	1800 - 2000	63 29.5	19 19	57 40	-	-	-61.5	-72	1.7	0.90
Drivers													
BLF6G20S-45	SOT608B	I/O	2C W-CDMA	1800 - 2000	2.5	19.2	14	-	-50	-	-	-	1.70
BLF6G20-45	SOT608A	I/O	2C W-CDMA	1800 - 2000	2.5	19.2	14	-	-50	-	-	-	1.70
BLF6G21-10	SOT538A	-	CW	800 - 4000	10	TBD	10	-45	-48	-	-	-	TBD
BLF3G21-30	SOT467C	-	2-Tone PHS class A	HF - 2200	30 9	13.5 16	35 20	-26	-	-	-75	-	1.60
BLF3G21-6	SOT538A	-	2-Tone PHS class A	HF - 2200	6 2	13.5 16	35 20	-23	-	-	-75	-	10
BLF2045	SOT467C	-	CW	1800 - 2200	30	11	30	-	-	-	-	-	2.10
BLF1822-10	SOT467C	-	CW	HF - 2200	12	13	40	-	-	-	-	-	5
BLF2043	SOT538A	-	CW	HF - 2200	12	12	40	-	-	-	-	-	9
BLF2043F	SOT467C	-	CW	HF - 2200	10	12	30	-	-	-	-	-	5
BGF1801-10	SOT365C	-	CW EDGE	1805 - 1880	10 3.5	26	35 20	-	-	-63	-	1.2	-

Basestation product portfolio

2.2-GHz finals and drivers

Product	Package	Matching	Mode of operation	Frequency band (min - max)	Output power	Power gain	Efficiency	Intermodulation distortion (IM3)	Adjacent channel leakage ratio (ACLR)	Adjacent channel power ratio @400kHz (ACPR400)	Adjacent channel power ratio @ 600 kHz (ACPR600)	Error vector magnitude (EVM)	Thermal resistance (Rth)
		(I/O)		(MHz)	(W)	(dB)	(%)	(dBc)	(dBc)	(dBc)	(dBc)	(%)	(K/W)
Finals													
BLF6G22-180PN	SOT539A	I/O	2C W-CDMA	2000 - 2200	50	17.5	27.5	-	-35	-	-	-	0.45
BLF6G22LS-180R	SOT502B	I/O	IS-95	2000 - 2200	40	16	25	-37	-41	-	-	-	TBD
BLF6G22-180R	SOT502A	I/O	IS-95	2000 - 2200	40	16	25	-37	-41	-	-	-	TBD
BLF6G22LS-140	SOT502B	I/O	2C W-CDMA	2000 - 2200	32	17	28	-37	-40	-	-	-	TBD
BLF6G22LS-130	SOT502B	I/O	2C W-CDMA	2000 - 2200	30	17	28.5	-37	-40	-	-	-	0.43
BLF6G22LS-100	SOT502B	I/O	2C W-CDMA	2000 - 2200	25	18.2	29	-37	-41	-	-	-	0.43
BLF6G22-100	SOT502A	I/O	2C W-CDMA	2000 - 2200	25	17.6	29	-36	-39	-	-	-	TBD
BLC6G22-100	SOT895A	I/O	2C W-CDMA	2000 - 2200	-	-	-	-	-	-	-	-	TBD
BLF6G22LS-75	SOT502B	I/O	2C W-CDMA	2000 - 2200	17	18.7	30.5	-37.5	-41.5	-	-	-	0.75
BLC6G22LS-75	SOT896B	I/O	2C W-CDMA	2000 - 2200	17	18.5	31	-37	-41	-	-	-	0.75
BLC6G22-75	SOT895A	I/O	2C W-CDMA	2000 - 2200	17	18.5	31	-37	-41	-	-	-	0.90
Drivers													
BLF6G22S-45	SOT608B	I/O	2C W-CDMA	2000 - 2200	2.5	18.5	13	-	-49	-	-	-	1.70
BLF6G22-45	SOT608A	I/O	2C W-CDMA	2000 - 2200	2.5	18.5	13	-	-49	-	-	-	1.70
BLM6G22-30G	SOT822-1	I/O	2C W-CDMA	2100 - 2200	2	29.5	9	-48	-50	-	-	-	2.1
BLM6G22-30	SOT834-1	I/O	2C W-CDMA	2100 - 2200	2	29.5	9	-48	-50	-	-	-	2.1
BLF6G21-10	SOT538A	-	CW	800 - 4000	10	TBD	10	-45	-48	-	-	-	TBD
BLF3G22-30	SOT608A	I/O	2-Tone PHS class A W-CDMA / UMTS	2000 - 2200	30 10 6.5	14 16 15	34 20 21	-38	-42	-	-	-	1.85
BLF3G21-30	SOT467C	-	2-Tone PHS class A	HF - 2200	30 9	13.5 16	35 20	-26	-	-	-75	-	1.60
BLF3G21-6	SOT538A	-	2-Tone PHS class A	HF - 2200	6 2	13.5 16	35 20	-23	-	-	-75	-	10
BLF1822-10	SOT467C	-	CW	HF - 2200	12	13	40	-	-	-	-	-	5
BLF2043	SOT538A	-	CW	HF - 2200	12	12	40	-	-	-	-	-	9
BLF2043F	SOT467C	-	CW	HF - 2200	10	12	30	-	-	-	-	-	5

Packages

					
SOT502A	SOT502B	SOT896B	SOT895A	SOT608A	SOT608B
					
SOT467C	SOT538A	SOT365C	SOT539A	SOT822-1	SOT834-1

www.nxp.com

© 2008 NXP B.V.

All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Date of release: May 2008

Document order number: 9397 750 16521

Printed in the Netherlands

founded by

PHILIPS