

MN101E13G

Type	MN101E13G	MN101EF13G
Internal ROM type	Mask ROM	FLASH
ROM (byte)	128K	
RAM (byte)	4K	
Package (Lead-free)	QFP084-P-1818E	QFP084-P-1818E (ES (Engineering Sample) available)
Minimum Instruction Execution Time	100 ns (at 3.135 V to 3.465 V, , normal-mode)	100 ns

■ Interrupts

External (7 lines)

Internal (13 lines) : Timer × 4, A/D × 1, RESET × 1, OSD × 1, Serial × 2, I²C × 1, Caption × 1, Remote control × 1, HSYNC× 1, VSYNC× 1

■ Timer Counter

8-bit timer × 4

Watchdog timer : Time-out period is selectable.

■ Serial interface

I²C × 1 : for multimaster mode, bus line (output) has 2 systems

Sync serial / UART × 1

■ Caption / Teletext Decoder

• Built-in sync separator × 1

■ I/O Pins

I/O	35	Common use
-----	----	------------

■ A/D converter

10-bit × 8-ch. (with S/H)

■ PWM

8-bit × 6-ch. , 14-bit × 1-ch.

■ Special Ports

Remote control reception

■ CRTC

1-layer display (graphics, characters, splits)

■ Notes


Remote control input discriminant circuit built-in, build-in NTSC video signal processing circuit, built-in 3-line comb filter

■ Development tools

In-circuit Emulator

PX-PAC101E02-4W9J

■ Pin Assignment



QFP084-P-1818E

Note) *1: 5 V dielectric N-ch. open drain output pin
*2: Mask ROM = VDD, Flash memory built-in type = VPP

Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
 - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd. Industrial Co., Ltd.