



- Features :
- \*Universal AC input / Full range
- \*Protections: Short circuit / Overload / Over voltage
- \*Cooling by free air convection
- \*LED indicator for power on
- \*100% full load burn-in test
- \*All using 105°C long life electrolytic capacitors
- \*Withstand 300VAC surge input for 5 second
- 'High operating temperature up to 70°C
- \*Withstand 5G vibration test







MODEL		RT-85A						g life and high reliability RT-85C			RT-85D		
	OUTPUT NUMBER	CH1	CH2	CH3	CH1 '3	years wa	irganty	CH1	CH2	СНЗ	CH1	CH2	CH3
ОИТРИТ	DC VOLTAGE	5V	12V	-5V	5V	12V	-12V	5V	15V	-15V	5V	24V	12V
	RATED CURRENT	8A	3.5A	0.5A	8A	3.5A	0.5A	7A	3A	0.5A	6A	2A	1A
	CURRENT RANGE Note.6	2 ~ 10A	0.3 ~ 4A	0 ~ 1A	2 ~ 10A	0.3 ~ 4A	0 ~ 1A	2 ~ 10A	0.3 ~ 4A	0 ~ 1A	2 ~ 10A	0.3 ~ 2.5A	0.1 ~ 1A
	RATED POWER Note.6	84.5W		88W			87.5W			90W			
	RIPPLE & NOISE (max.) Note.2	80mVp-p   120mVp-p   100		100mVp-p	80mVp-p 120mVp-p 120mVp-p		80mVp-p 120mVp-p 120mVp-p		80mVp-p 150mVp-p 120mV		120mVp-		
	VOLTAGE ADJ. RANGE	CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V		
	VOLTAGE TOLERANCE Note.3	±2.0%	±5.0%	±6.0%	±2.0%	±5.0%	±6.0%	±2.0%	+3,-7%	±6.0%	±2.0%	±5.0%	±6.0%
	LINE REGULATION Note.4	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%
	LOAD REGULATION Note.5	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%
	SETUP, RISE TIME	500ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load											
	HOLD UP TIME (Typ.)	100ms/230VAC 18ms/115VAC at full load											
INPUT	VOLTAGE RANGE	88 ~ 264VAC 125 ~ 373VDC (Withstand 300VAC surge for 5sec. Without damage)											
	FREQUENCY RANGE	47 ~ 63Hz											
	EFFICIENCY (Typ.)	76%			76%	77%					79%		
	AC CURRENT (Typ.)	2.5A/115\	/AC 1	.5A/230VA	,								
	INRUSH CURRENT (Typ.)	COLD START 40A/230VAC											
	LEAKAGE CURRENT	<2mA/240VAC											
PROTECTION	OVER OAR	110 ~ 150% rated output power											
	OVERLOAD	Protection type : Hiccup mode, recovers automatically after fault condition is removed											
	01/50 1/01 74 05	CH1: 5.75 ~ 6.75V											
	OVER VOLTAGE	Protection type: Hiccup mode, recovers automatically after fault condition is removed											
ENVIRONMENT	WORKING TEMP.	-25 ~ +70°C (Refer to "Derating Curve")											
	WORKING HUMIDITY	20 ~ 90% RH non-condensing											
	STORAGE TEMP., HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH											
	TEMP. COEFFICIENT	±0.03%/°C (0 ~ 50°C)on +5V output											
	VIBRATION	10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes											
SAFETY & EMC (Note 7)	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 approved											
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2.0KVAC O/P-FG:0.5KVAC											
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C/ 70% RH											
	EMC EMISSION	Compliance to EN55032 (CISPR32) Class B, EN61000-3-2,-3											
	EMC IMMUNITY	Complian	ce to EN61	000-4-2,3,4	I,5,6,8,11, I	EN61000-6	-2 (EN5008	2-2), heav	y industry le	evel, criteria	a A		
OTHERS	MTBF	215Khrs r	nin. MIL	-HDBK-217	'F (25°C)								
	DIMENSION	159*97*3	3mm (L*W*	H)	. ,								
	PACKING	0.6Kg; 24pcs/15.4Kg/0.7CUFT											
NOTE	2. Ripple & noise are measure	lly mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.  ed at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.  tolerance, line regulation and load regulation.											

- Tolerance: includes set up tolerance, line regulation and load regulation.
   Line regulation is measured from low line to high line at rated load.
   Load regulation is measured from 20% to 100% rated load, and other output at 60% rated load.
   Each output can work within current range. But total output power can't exceed rated output power.
   The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on http://www.meanwell.com)
- 8. Length of set up time is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.



