



SAW Components

Data Sheet B7603

Data Sheet

An abstract graphic featuring the word "EPCOS" in large, glowing, 3D letters. The letters are white with a blue glow and are positioned diagonally across the frame. In the background, there is a faint, stylized globe with circuitry patterns, suggesting a global network or technological theme. The overall color scheme is dark with blue and white highlights.



SAW Components

B7603

Low-Loss Filter for Mobile Communication

897,5 MHz


Data Sheet



Chip sized SAW package

Features

- Low-loss RF filter for mobile telephone EGSM system, transmit path
- Low amplitude ripple
- Usable passband 35 MHz
- No matching network required for operation at 50 Ω
- Ceramic Package for Surface Mounted Technology (SMT)




Terminals

- Ni, gold-plated

Dimensions in mm, approx. weight 0,027g

Pin configuration

2	Input
3	Input - ground
5	Output
4	Output - ground
1,6	Case ground



Type	Ordering code	Marking and Package according to	Packing according to
B7603	B39901-B7603-A210	C61157-A7-A61	F61074-V8083-Z000

Electrostatic Sensitive Device (ESD)

Maximum ratings

Operable temperature range	T	- 20 / + 80	$^{\circ}\text{C}$	source and load impedance 50 Ω peak power of GSM signal, duty cycle 1 : 8 continuous wave
Storage temperature range	T_{stg}	- 40 / + 85	$^{\circ}\text{C}$	
DC voltage	V_{DC}	0	V	
Input power max. 880...915 MHz	P_{IN}	10	dBm	
elsewhere		5	dBm	



SAW Components

B7603

Low-Loss Filter for Mobile Communication

897,5 MHz

Data Sheet



Characteristics

Operating temperature range: $T = 25 \pm 2 \text{ }^{\circ}\text{C}$

Terminating source impedance: $Z_S = 50 \text{ } \Omega$

Terminating load impedance: $Z_L = 50 \text{ } \Omega$

			min.	typ.	max.	
Center frequency	f_c		—	897,50	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$					
	880,0 ... 915,0 MHz		—	2,6	2,7	dB
Amplitude ripple (p-p)	$\Delta\alpha$					
	880,0 ... 915,0 MHz		—	1,3	1,4	dB
Input VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Output VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Attenuation	α					
	0,0 ... 840,0 MHz		17	18	—	dB
	840,0 ... 860,0 MHz		17	20	—	dB
	860,0 ... 870,0 MHz		10	25	—	dB
	925,0 ... 935,0 MHz		4,5	8	—	dB
	935,0 ... 1850,0 MHz		20	21	—	dB
	1850,0 ... 3660,0 MHz		7	16	—	dB



SAW Components

B7603

Low-Loss Filter for Mobile Communication

897,5 MHz

Data Sheet



Characteristics

Operating temperature range: $T = +10$ to $+60^{\circ}\text{C}$

Terminating source impedance: $Z_S = 50\ \Omega$

Terminating load impedance: $Z_L = 50\ \Omega$

			min.	typ.	max.	
Center frequency	f_c		—	897,50	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$					
	880,0 ... 915,0 MHz		—	2,7	2,8	dB
Amplitude ripple (p-p)	$\Delta\alpha$					
	880,0 ... 915,0 MHz		—	1,4	1,5	dB
Input VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Output VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Attenuation	α					
	0,0 ... 840,0 MHz		17	18	—	dB
	840,0 ... 860,0 MHz		17	20	—	dB
	860,0 ... 870,0 MHz		10	19	—	dB
	925,0 ... 935,0 MHz		4	7	—	dB
	935,0 ... 1850,0 MHz		20	21	—	dB
	1850,0 ... 3660,0 MHz		7	16	—	dB



SAW Components

B7603

Low-Loss Filter for Mobile Communication

897,5 MHz

Data Sheet



Characteristics

Operating temperature range: $T = -20$ to $+70^{\circ}\text{C}$

Terminating source impedance: $Z_S = 50\ \Omega$

Terminating load impedance: $Z_L = 50\ \Omega$

			min.	typ.	max.	
Center frequency	f_c		—	897,50	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$					
	880,0 ... 915,0 MHz		—	2,7	3,1	dB
Amplitude ripple (p-p)	$\Delta\alpha$					
	880,0 ... 915,0 MHz		—	1,4	1,8	dB
Input VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Output VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Attenuation	α					
	0,0 ... 840,0 MHz		17	18	—	dB
	840,0 ... 860,0 MHz		17	19	—	dB
	860,0 ... 870,0 MHz		10	20	—	dB
	925,0 ... 935,0 MHz		3	5	—	dB
	935,0 ... 1850,0 MHz		20	21	—	dB
	1850,0 ... 3660,0 MHz		7	16	—	dB



SAW Components

B7603

Low-Loss Filter for Mobile Communication

897,5 MHz

Data Sheet



Characteristics

Operating temperature range: $T = -10$ to $+80^{\circ}\text{C}$

Terminating source impedance: $Z_S = 50\ \Omega$

Terminating load impedance: $Z_L = 50\ \Omega$

			min.	typ.	max.	
Center frequency	f_c		—	897,50	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$					
	880,0 ... 915,0 MHz		—	2,7	3,0	dB
Amplitude ripple (p-p)	$\Delta\alpha$					
	880,0 ... 915,0 MHz		—	1,4	1,7	dB
Input VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Output VSWR						
	880,0 ... 915,0 MHz		—	2,0	2,2	
Attenuation	α					
	0,0 ... 840,0 MHz		17	18	—	dB
	840,0 ... 860,0 MHz		17	20	—	dB
	860,0 ... 870,0 MHz		9	18	—	dB
	925,0 ... 935,0 MHz		4	6	—	dB
	935,0 ... 1850,0 MHz		20	21	—	dB
	1850,0 ... 3660,0 MHz		7	16	—	dB



SAW Components

B7603


Low-Loss Filter for Mobile Communication

897,5 MHz


Data Sheet



Transfer function (measurement)



Transfer function (wideband; measurement)





SAW Components	B7603
Low-Loss Filter for Mobile Communication	897,5 MHz
Data Sheet	SMD

Published by EPCOS AG
Surface Acoustic Wave Components Division, OFW E MF
P.O. Box 80 17 09, D-81617 München

© EPCOS AG 1999. All Rights Reserved.

As far as patents or other rights of third parties are concerned, liability is only assumed for components per se, not for applications, processes and circuits implemented within components or assemblies.

The information describes the type of component and shall not be considered as assured characteristics.

Terms of delivery and rights to change design reserved.

For questions on technology, prices and delivery please contact the sales offices of EPCOS AG or the international representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our sales offices.