


Thermally-Enhanced High Power RF LDMOS FETs 130 W, 869 – 960 MHz


Description

The PTF081301E and PTF081301F are 130-watt, internally-matched **GOLDMOS** FETs intended for EDGE and CDMA applications in the 869 to 960 MHz bands. Thermally-enhanced packaging provides the coolest operation available. Full gold metallization ensures excellent device lifetime and reliability.

PTF081301E
Package 30248



PTF081301F
Package 31248



Features

- Thermally-enhanced packages
- Broadband internal matching
- Typical EDGE performance
 - Average output power = 65 W
 - Gain = 18 dB
 - Efficiency = 40%
- Typical CW performance
 - Output power at P-1dB = 150 W
 - Gain = 17 dB
 - Efficiency = 55%
- Integrated ESD protection: Human Body Model, Class 1 (minimum)
- Excellent thermal stability
- Low HCI drift
- Capable of handling 10:1 VSWR @ 28 V, 130 W (CW) output power

RF Characteristics

EDGE Measurements (not subject to production test—verified by design/characterization in Infineon test fixture)

$V_{DD} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$, $P_{OUT} = 65\text{ W}$, $f = 959.8\text{ MHz}$

Characteristic	Symbol	Min	Typ	Max	Unit
Error Vector Magnitude	EVM (RMS)	—	2.5	—	%
Modulation Spectrum @ 400 kHz	ACPR	—	-62	—	dBc
Modulation Spectrum @ 600 kHz	ACPR	—	-74	—	dBc
Gain	G_{ps}	—	18	—	dB
Drain Efficiency	η_D	—	40	—	%

All published data at $T_{CASE} = 25^\circ\text{C}$ unless otherwise indicated

ESD: Electrostatic discharge sensitive device—observe handling precautions!

RF Characteristics (cont.)

Two-Tone Measurements (tested in Infineon test fixture)

$V_{DD} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$, $P_{OUT} = 130\text{ W PEP}$, $f = 960\text{ MHz}$, tone spacing = 1 MHz

Characteristic	Symbol	Min	Typ	Max	Unit
Gain	G_{ps}	17	18	—	dB
Drain Efficiency	η_D	40	42	—	%
Intermodulation Distortion	IMD	—	-32	-29	dBc

DC Characteristics

Characteristic	Conditions	Symbol	Min	Typ	Max	Unit
Drain-Source Breakdown Voltage	$V_{GS} = 0\text{ V}$, $I_{DS} = 10\text{ }\mu\text{A}$	$V_{(BR)DSS}$	65	—	—	V
Drain Leakage Current	$V_{DS} = 28\text{ V}$, $V_{GS} = 0\text{ V}$	I_{DSS}	—	—	1.0	μA
On-State Resistance	$V_{GS} = 10\text{ V}$, $I_{DS} = 1\text{ A}$	$R_{DS(on)}$	—	0.1	—	Ω
Operating Gate Voltage	$V_{DS} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$	V_{GS}	2.5	2.9	4.0	V
Gate Leakage Current	$V_{GS} = 10\text{ V}$, $V_{DS} = 0\text{ V}$	I_{GSS}	—	—	1.0	μA

Maximum Ratings

Parameter	Symbol	Value	Unit
Drain-Source Voltage	V_{DSS}	65	V
Gate-Source Voltage	V_{GS}	-0.5 to +12	V
Junction Temperature	T_J	200	$^{\circ}\text{C}$
Total Device Dissipation	P_D	473	W
Above 25 $^{\circ}\text{C}$ derate by		2.70	W/ $^{\circ}\text{C}$
Storage Temperature Range	T_{STG}	-40 to +150	$^{\circ}\text{C}$
Thermal Resistance ($T_{CASE} = 70^{\circ}\text{C}$)	$R_{\theta JC}$	0.37	$^{\circ}\text{C/W}$


Ordering Information

Type	Package Outline	Package Description	Marking
PTF081301E	30248	Thermally-enhanced slotted flange, single-ended	PTF081301E
PTF081301F	31248	Thermally-enhanced earless flange, single-ended	PTF081301F

Typical Performance (measurements taken in production test fixture)


IM3 vs. Output Power at Selected Biases

$V_{DD} = 28\text{ V}$, $f_1 = 959$, $f_2 = 960\text{ MHz}$, series show I_{DQ}




Broadband Performance

$V_{DD} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$, $P_{OUT} = 51.14\text{ dBm}$




Power Sweep

$V_{DD} = 28\text{ V}$, $f = 960\text{ MHz}$



Gain & Efficiency vs. Output Power


$V_{DD} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$, $f = 960\text{ MHz}$



Typical Performance (cont.)


Output Power (at 1 dB Compression) vs. Supply Voltage

$I_{DQ} = 950 \text{ mA}$, $f = 960 \text{ MHz}$




IS-95 CDMA Performance

$V_{DD} = 28 \text{ V}$, $I_{DQ} = 950 \text{ mA}$, $f = 860 \text{ MHz}$




IS-95 CDMA Performance

$V_{DD} = 28 \text{ V}$, $I_{DQ} = 950 \text{ mA}$, $f = 860 \text{ MHz}$



EDGE EVM Performance


$V_{DD} = 28 \text{ V}$, $I_{DQ} = 950 \text{ mA}$, $f = 959.8 \text{ MHz}$



Typical Performance (cont.)

Three-Carrier CDMA 2000 Performance


$V_{DD} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$, $f = 960\text{ MHz}$



Intermodulation Distortion vs. Output Power


(as measured in a broadband circuit)

$V_{DD} = 28\text{ V}$, $I_{DQ} = 950\text{ mA}$, $f_1 = 959\text{ MHz}$, $f_2 = 960\text{ MHz}$




Gate-Source Voltage vs. Temperature


Voltage normalized to typical gate voltage,
series show current.



Broadband Circuit Impedance




Frequency	Z Source Ω		Z Load Ω	
MHz	R	jX	R	jX
860	5.35	-3.80	1.59	0.99
920	5.41	-2.54	1.56	1.74
940	5.43	-2.16	1.56	1.91
960	5.42	-1.70	1.56	2.15
980	5.48	-1.24	1.50	2.34



See next page for Reference Circuit

Reference Circuit



Reference Circuit Schematic for 960 MHz


Circuit Assembly Information

DUT	PTF081301E or PTF081301F	LDMOS Transistor
PCB	0.76 mm [.030"] thick, $\epsilon_r = 4.5$	2 oz. copper Rogers TMM4

Microstrip	Electrical Characteristics at 960 MHz ¹	Dimensions: L x W (mm)	Dimensions: L x W (in.)
$\ell 1$	0.075λ , 50.0 Ω	12.70 x 1.35	0.500 x 0.053
$\ell 2$	0.101λ , 50.0 Ω	17.27 x 1.35	0.680 x 0.053
$\ell 3$	0.055λ , 50.0 Ω	9.40 x 1.35	0.370 x 0.053
$\ell 4$	0.289λ , 74.0 Ω	50.80 x 0.64	2.000 x 0.025
$\ell 5$	0.061λ , 7.5 Ω	9.27 x 16.26	0.365 x 0.640
$\ell 6$	0.036λ , 7.9 Ω	5.46 x 15.24	0.215 x 0.600
$\ell 7, \ell 8$	0.132λ , 50.0 Ω	22.61 x 1.27	0.890 x 0.050
$\ell 9$	0.114λ , 7.9 Ω	17.40 x 15.24	0.685 x 0.600
$\ell 10$	0.047λ , 7.9 Ω	7.24 x 15.24	0.285 x 0.600
$\ell 11$	0.134λ , 38.0 Ω	22.35 x 2.16	0.880 x 0.085
$\ell 12$	0.029λ , 50.0 Ω	4.95 x 1.37	0.195 x 0.054

¹Electrical characteristics rounded

Reference Circuit (cont.)




Reference Circuit* (not to scale)

Component	Description	Suggested Manufacturer	P/N or Comment
C1	Tantalum capacitor, TE Series, 10 μ F, 35 V	Digi-Key	PC56106-ND, SMD
C2, C11, C22	Capacitor, 0.1 μ F, 50 V, 1206	Digi-Key	PCC104BCT-ND
C3, C4, C7, C17, C18	Capacitor, 33 pF	ATC	100B 330
C5	Capacitor, 5.0 pF	ATC	100B 5R0
C6, C15	Capacitor, 0.5 pF	ATC	100B 0R5
C8, C9, C19, C20	Capacitor, 1 μ F, 50 V	Digi-Key	19528-ND
C10, C12, C21, C23	Tantalum cap, 10 μ F, 50 V, TPS Series, SMD	Garrett Electronics	TPSE106K050R0400
C13, C14	Capacitor, 6.8 pF	ATC	100B 6R8
C16	Capacitor, 0.3 pF	ATC	100B 0R3
C24, C25, C26	Capacitor, 0.001 μ F, 50 V, 0603	Digi-Key	PCC1772CT-ND
L1, L2	Ferrite, 6 mm	Ferroxcube	53/3/4.6-452
Q1	Transistor	Infineon	BCP56
QQ1	Voltage regulator	National Semiconductor	LM7805
R1	Resistor, 10 ohms, 1/4 W, 1206	Digi-Key	P10ECT-ND
R2	Resistor, 5.1 k-ohms, 1/4 W, 1206	Digi-Key	5.1KECT-ND
R3	Resistor, 1.2 k-ohms, 1/10 W, 0603	Digi-Key	P1.2KGCT-ND
R4	Resistor, 1.3 k-ohms, 1/10 W, 0603	Digi-Key	P1.3KGCT-ND
R5	Potentiometer, 10 k-ohms, 0.25 W	Digi-Key	3224W-103ETR-ND
R6	Resistor, 22 k-ohms, 1/10 W, 0603	Digi-Key	P22KGCT-ND
R7	Resistor, 3.3 k-ohms, 1/4 W, 1206	Digi-Key	P3.3KECT-ND


*Gerber files for this circuit are available on request.

Package Outline Specifications



Find the latest and most complete information about products and packaging at the Infineon Internet page
<http://www.infineon.com/products>

Package Outline Specifications (cont.)



Find the latest and most complete information about products and packaging at the Infineon Internet page
<http://www.infineon.com/products>

Revision History: 2005-05-02

Data Sheet

Previous Version: 2004-08-27, Data Sheet


Page	Subjects (major changes since last revision)
1, 2	PTF081301F released
7, 8	Circuit descriptions
9, 10	Add and revise case outlines

We Listen to Your Comments

Any information within this document that you feel is wrong, unclear or missing at all?
 Your feedback will help us to continuously improve the quality of this document.
 Please send your proposal (including a reference to this document) to:

highpowerRF@infineon.com

To request other information, contact us at:
 +1 877 465 3667 (1-877-GOLDMOS) USA
 or +1 408 776 0600 International



GOLDMOS® is a registered trademark of Infineon Technologies AG.

Edition 2005-05-02

**Published by Infineon Technologies AG,
 St.-Martin-Strasse 53,
 81669 München, Germany**

**© Infineon Technologies AG 2004.
 All Rights Reserved.**

Attention please!

The information herein is given to describe certain components and shall not be considered as a guarantee of characteristics.

Terms of delivery and rights to technical change reserved.

We hereby disclaim any and all warranties, including but not limited to warranties of non-infringement, regarding circuits, descriptions and charts stated herein.

Information

For further information on technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies Office (www.infineon.com/rfpower).

Warnings

Due to technical requirements components may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies Office.

Infineon Technologies Components may only be used in life-support devices or systems with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system, or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body, or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.