



MODEL: SDC-2010

DC / DC CONVERTERS

CAR POWER ADAPTER
*Regulated switch mode
DC DC adapter*

DESCRIPTION

A high tech efficient car power adapter built to provide stable clean DC power for the voltage sensitive electronic digital equipment with minimal strain on the car's electrical power source.

Applications: CD-players, cassette-recorders, radios, games such as Game-boy, portable DVD-players, LCD-TV, digital cameras, camcorders, speed check-scanners, map reading lights, and etc.



FEATURES

- IC regulated switch mode DC converter.
- 82% efficiency resulting cool running and less strain on car's electrical power source.
- 11 -30 V DC input voltages suitable for most truck and car.
- 7 selectible regulated output voltages.
- 7 sets of detachable plugs (polarity reversible) suitable for most portables.
- LED power indicator.

SPECIFICATIONS

MODEL

Input Voltage
Regulated output voltages

Contininuous Output Current
Maximum Output current
Efficiency
Indicator
Protection devices

Approvals
Accessory

SDC-2010

11 - 30V DC (negative earth)
Regulated at 1,5V - 3V - 4,5V - 6V -
7,5V - 9V and 12V (12V is regulated only
when input voltage is higher than 16V)

1500mA

1800mA

82%

LED Power-ON

Short circuit protection
Automatic thermal cut off
Automatic overload cut off
2,0 Amp safety fuse

CE approval (EMC 55014)

7 pieces of most commonly used plugs

FOR MORE DETAILED INFORMATION, PLEASE CONTACT OUR SALES / SUPPORT DEPT.