


## 5 Channel Driver for CD/CD-ROM **BA5811FM**

### ● Description

The BA5811FM is 5-channel driver including 4-channel BTL drivers and 1-channel reversible motor driver for CD/CD-ROM applications. Separating Vcc into Pre and Pow can make the power more efficient. A power-saving mode is enabled by a power-save terminal.

### ● Dimension(Units : mm)



### ● Features

- 1) Small surface mounting power package HSOP-M28
- 2) Thermal shut down circuit built-in
- 3) Wide dynamic range  
(4.0V typical at PREVCC=12V, POWVCC=5V)
- 4) 4-channel BTL driver  
(2-channel is able to be used for a stepping motor)
- 5) The output voltage is adjustable by the voltage control terminal.

HSOP-M28

### ● Applications

CD, CD-ROM

### ● Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Power supply voltage	PREVCC, POWVCC	18	V
Power dissipation	Pd	2.2*	W
Operating temperature range	Topr	-40 ~ +85	°C
Storage temperature range	Tstg	-55 ~ +150	°C

Derating:17.6mV/°C for operation above Ta=25°C.

On less than 3% (percentage occupied by copper foil), 70mm×70mm, t=1.6mm, glass epoxy mounting.

●Guaranteed operating ranges(Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit
Operating supply voltage	PREVCC	4.3	—	13.2	V
	POWVCC	4.3	—	PREVCC	V


●Electrical characteristics

(Unless otherwise noted, Ta=25°C, PREVCC=12V, POWVCC12/34=5V, BIAS=1.65V, PS=2V, RL=8 )

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Quiescent current	ICC	—	24	35	mA	No load
Power save on current	IPS	—	1.6	2.8	mA	PS="L"
< BTL driver >						
Output offset voltage	VOO	-50	0	50	mV	
Max. output voltage	VOM	3.6	4.0	—	V	
Closed loop voltage gain	GVC	13.6	15.6	17.6	dB	
< OP-AMP (CH3, 4) >						
Input offset voltage	VOFOP	-6	0	6	mV	
High level output voltage	VOHOP	11.5	—	—	V	BIAS=6V
Low level output voltage	VOLOP	—	—	0.5	V	BIAS=6V
< Loading driver >						
Output saturation voltage1	VSAT1	0.7	1.2	1.7	V	IL=200mA (Upper + Lower)
Output adjustable gain on "H" side voltage	GVH	7.2	9.0	10.8	dB	"H"side output for input (LDCNT)

This product is not designed for protection against radioactive rays.

●Application circuit



## Appendix

---

### Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document use silicon as a basic material.

Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

#### About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.