



IF FILTER FOR INTERCARRIER APPLICATION

Type	Picture Carrier		Chroma Carrier(dB)	Sound Carrier	Ajacent Picture Carrier (dB)	Ajacent Sound Carrier (dB)	Lower Spurious Response	Upper Spurious Response (dB)	Standard	Package	Overseas Type	SAMPLE DIMENSIONS TEST CIRCUIT
	Frequency(MHz)	Attenuation(dB)										
IF45A1D	45.75	6 $\pm$ 2	1 $\pm$ 1.5	19.1 $\pm$ 2	42	40	35	35	M/N	SIP5D	M1967D	
IF389A1M	38.9	6.5 $\pm$ 2	2.7 $\pm$ 1.5	19.0 $\pm$ 2	42	40	34	33	B/G	SIP5K	G1865M	
IF389A2M	38.9	5.5 $\pm$ 2	3.9 $\pm$ 1.5	15.7 $\pm$ 2	40	37	35	33	B/G	SIP5K	G1872M	
IF45A4M	45.75	4.8 $\pm$ 1.5	4.3 $\pm$ 1.5	17.1 $\pm$ 2	37	37	32	32	M/N	SIP5K	M1681M	
IF389B1M	38.9	5.7 $\pm$ 1.5	3.8 $\pm$ 1.5	20.3 $\pm$ 1.5	44	42	35	35	B/G	SIP5K	K2955M	
				20.9 $\pm$ 1.5					D/K			
IF45A1M	45.75	6 $\pm$ 1.5	0.9 $\pm$ 1.5	19.1 $\pm$ 2	42	40	32	32	M/N	SIP5K	M1967M	
IF45A3M	45.75	6.4 $\pm$ 1.5	1.3 $\pm$ 1.5	19.4 $\pm$ 2	42	40	35	35	M/N	SIP5K	M1976M	
IF389A1D	45.75	6 $\pm$ 1.5	1.0 $\pm$ 1.5	19.1 $\pm$ 2	42	40	35	35	M/N	SIP5D	G1865M	
IF58A1M	58.75	0	1.2 $\pm$ 1.5	-13.4 $\pm$ 3	-37	-35	30	30	M	F12	TSF1145P	
HDF5241P	45.75	-5.8 $\pm$ 2	-1.9 $\pm$ 1.5	-16.6 $\pm$ 2	-41	-39	-35	-31	M	F12	TSF5241P	

ii



[\[Home \]](#) | [About SDE](#) | [Request Info](#) | [Saw Filter](#) | [Saw Resonator](#) | [Ceramic Resonator](#) | [Ceramic Discriminator](#)
[\[Ceramic Filter1 \]](#) | [Ceramic Filter2](#) | [Ceramic Trap](#) | [Crystal Unit](#) | [Clock Oscillator](#) | [Dielectric Filter](#) | [Dielectric Resonator](#)

Copyright 2001 by Shoulder Electronics Limited
 Contact Us: Tel: 86-755-2979884 Fax:86-755-2979885
 Questions or comments: info@china-shoulder.com