Reference voltage power supply BA3932

The BA3932 is a monolithic reference voltage power supply IC for use in CD radio cassette players.

Applications

CD radio cassette players, mini-component stereo audio systems

Features

- With 9.0V output for audio power supply, 5.0V output for microcontrollers, 5.0 and 8.0V outputs for CD players, 14.7V output for motor drivers, the IC is best suited for CD radio cassette players.
- Precise power supply (5V ± 0.1V) can be obtained by using external reference voltage input (only AUDIO output has an internal reference voltage system).
- 3) Zero standby current. (Typ.)
- Output current limit circuit protects the IC against short-circuiting damage.
- 5) Compact SIP-M12 package allows a large power dissipation (3W: no heat sink).
- Thermal protection circuit prevents heat damage to the IC.

●Absolute maximum ratings (Ta = 25°C)

Parameter	Symbol	Limits	Unit
Applied voltage	Vcc	23	٧
Power dissipation	Pd	3000*	mW
Operating temperature	Topr	−25~+75	Ĉ
Storage temperature	Tstg	−55∼ +150	င


^{*} Reduced by 24mW for each increase in Ta of 1°C over 25°C.

Recommended operating conditions

Parameter	Symbol	Limits	Unit
Power supply voltage Vcc		6.5~22.0*1	V

^{*1} For basic operation at Ta = 25 °C.

●Block diagram





●Pin descriptions


Pin No.	Pin name	Function
1	AUDIO 9V	AUDIO 9V output
2	С	Capacitor for regulating AUDIO 9V
3	PRE GND	AUDIO system GND
4	RADIO 5V	RADIO 5V output pin; output when MODE SW is 1.4V (typical)
5	COM 5V	Microcontroller 5V output
6	CD 5V	CD 5V output pin; output when MODE SW is 3.2V (typical)
7	CD 8V	CD 8V output pin; output when MODE SW is 3.2V (typical)
8	MODE SW	Pin to select CD 5V, CD 8V, or RADIO 5V output
9	Vcc	Power supply
10	REF STB	Reference voltage 5V output pin; also a standby SW
11	MOTOR 14.7V	MOTOR 14.7V output
12	GND	Large current GND, connected to the IC substrate


Regulator ICs

●Input / output circuits

















Units: R (Ω)

BA3932

●Electrical characteristics (unless otherwise noted, Ta = 25°C and Vcc = 16.0V)


Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Standby supply current	Isт	_	0	10	μΑ	REF STB=0V
Output voltage (AUDIO 9V)	V ₀₁	8.5	9.0	9.5	V	lo1=250mA
Voltage regulation	Δ V ₀₁₁	_	40	200	mV	Vcc=11 ~ 22V lo1=250mA
Load regulation	Δ V _{O12}	_	30	200	mV	lo1=0 ~ 250mA
Minimum I/O voltage differential *	Δ V013	_	1.1	2.1	V	lo1=250mA
Output current capacity *	l 01	300	710	_	mA	V ₀₁ ≧8.5V
Ripple rejection ratio	R.R1	50	62	_	dB	f=100Hz V _{RR} =-10dBV
Output voltage (MOTOR 14.7V)	V _{O2}	14.1	14.7	15.3	V	lo2=600mA
Voltage regulation	△ V _{O21}	_	50	200	mV	Vcc=16 ~ 22V lo2=600mA
Load regulation	△ V022	_	150	600	mV	lo2=0 ~ 600mA
Minimum I/O voltage differential *	△ V023	_	0.5	0.9	V	lo2=600mA
Output current capacity	l ₀₂	1.2	1.4	_	Α	Vo2≧14.1V
Output voltage (CD 8.0V)	Vоз	7.5	8.0	8.5	V	lo3=400mA
Voltage regulation	∆ V031	_	20	200	mV	Vcc=9 ~ 22V lo3=400mA
Load regulation	∆ V032	_	70	250	mV	lo₃=0 ~ 400mA
Minimum I/O voltage differential *	Д ∨озз	_	0.3	1.0	V	lo3=400mA
Output current capacity	Юз	0.8	1.2	_	Α	Vo₃≧7.5V
Ripple rejection ratio	R.R3	40	60	_	dB	f=100Hz V _{RR} =-10dBV
Output voltage (CD 5V)	V ₀₄	4.90	5.0	5.10	V	I ₀₄ =180mA
Voltage regulation	∆ V _{O41}	_	20	200	mV	Vcc=6.5 ~ 22V lo4=180mA
Load regulation	△ V042	_	20	200	mV	lo₄=0 ~ 180mA
Minimum I/O voltage differential *	△ V043	_	1.0	1.5	V	lo4=180mA
Output current capacity	l 04	220	400	_	mA	V ₀₄ ≧4.90V
Ripple rejection ratio	R.R4	50	60	_	dB	f=100Hz V _{RR} =-10dBV
Output voltage (RADIO 5V)	Vo ₅	4.90	5.0	5.10	V	los=80mA
Voltage regulation	∆ V051	_	20	200	mV	Vcc=6.5 ~ 22V los=80mA
Load regulation	∆ V ₀₅₂	_	20	200	mV	los=0 ~ 80mA
Minimum I/O voltage differential *	Δ V ₀₅₃	_	0.8	1.5	V	los=80mA
Output current capacity	l ₀₅	100	220	_	mA	Vo5≧4.90V
Ripple rejection ratio	R.R5	50	68	_	dB	f=100Hz V _{RR} =-10dBV

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Output voltage (COM 5V)	V ₀₆	4.90	5.0	5.10	٧	lo6=180mA
Voltage regulation	Δ V061	_	20	200	mV	Vcc=6.5~22V loe=180mA
Load regulation	Δ V062	_	20	200	mV	lo6=0 ~180mA
Minimum I/O voltage differential *	Δ V063	_	1.0	1.5	٧	loe=180mA
Output current capacity	106	220	400	_	mA	Vo6≧4.90V
Ripple rejection ratio	R.R6	50	60	_	dB	f=100Hz V _{RR} =-10dBV
$\langle Input \ (MODE \ SW) \rangle$						
Voltage when RADIO MODE ON	Vмтнн	1.1	1.4	1.7	٧	RADIO output voltage when switched to HIGH
Voltage when RADIO MODE OFF	VMTHL	2.9	3.2	3.5	٧	RADIO output voltage when switched to LOW
Voltage when CD MODE ON	VRTHH	2.9	3.2	3.5	٧	CD5V, CD8.0V output voltage when switched to HIGH
Input high level current	I _{IH1}	80	110	140	μΑ	MODE SW pin=5 V
⟨Input (REF STB)⟩						
Input high level current	Iref	_	210	500	μΑ	REF=5V, STAND BY pin=5V
Output voltage differential for each 5V system	ΔVDEF	_	0	0.25	V	

ONot designed for radiation resistance.

Circuit operation

(1) Timing chart



AUDIO 9V, MOTOR 14.7V, and COM 5V are output regardless of MODE SW.


RADIO 5V rises when MODE SW is 1.4V (typical), and CD 8V and CD 5V rise when MODE SW is 3.2V (typical).


(2) Estimate of allowable power dissipation Except under transitional conditions, the power dissipation of this IC is 3W per unit at 25°C. See Fig. 3 for heat reduction characteristics, including some cases where heat sinks are used.

^{*} Output current of AUDIO (9V) is theoretically 300 to 970 mA.

^{*} Minimum I/O voltage differential refers to the difference between input and output voltage when VCC is set to the minimum output voltage (see the relationship between VCC is and each output on a separate page).

Regulator ICs BA3932





Calculation of PMAX

• Power consumed by AUDIO 9V

 $P_1 = (V_{CC} - 9.0V) \times I1$

• Power consumed by MOTOR 14.7V

 $P_2 = (V_{CC} - 14.7V) \times I2$

• Power consumed by CD 8.0V

 $P_3 = (V_{CC} - 8.0V) \times I3$

• Power consumed by CD 5.0V

 $P_4 = (Vcc - 5.0V) \times I4$

Power consumed by RADIO 5.0V

 $P_5 = (V_{CC} - 5.0V) \times 15$

• Power consumed by COM 5.0V

 $P_6 = (V_{CC} - 5.0V) \times 16$

• Power consumed internally by each circuit

 $P_7 = V_{CC} \times circuit current$

* I1 = maximum output for AUDIO 9V

 I_2 = maximum output for MOTOR 14.7V

 I_3 = maximum output for CD 8.0V

 I_4 = maximum output for CD 5.0V

I₅ = maximum output for RADIO 5.0V

 I_6 = maximum output for COM 5.0V

Operation notes

(1) Operating power supply voltage

When operating within proper ranges of power supply voltage and ambient temperature, most circuit functions are guaranteed. Although the rated values of electrical characteristics cannot be absolutely guaranteed, characteristic values do not change drastically within the proper ranges.

(2) Power dissipation (Pd)

Refer to the heat reduction characteristics (Fig. 3) and the rough estimation of IC power dissipation given on a separate page. Make sure to use the IC within the allowable power dissipation with a sufficient margin.

(3) Preventing oscillation at each output and installing a ripple filter capacitor.

To stop oscillation of output, make sure to connect a capacitor between GND and each of the AUDIO 9V (pin 1), RADIO (pin 4), COM (pin 5), CD 5V (pin 6), CD 8V (pin 7), and MOTOR 14.7V (pin 11) output pins. We recommend using a tantalum electrolytic capacitor having a capacitance of $10\mu\text{F}$ or greater ($100\mu\text{F}$ or greater for AUDIO 9V) with minimal temperature susceptibility. Also,

sudden deterioration of the AUDIO 9V ripple rejection during a power drop can be prevented by connecting a capacitor ($220\mu F$ or greater recommended) to the C pin (pin 2).

(4) Overcurrent protection circuit

An overcurrent protection circuit is installed on the AU-DIO 9V (pin 1), RADIO (pin 4), COM (pin 5), CD 5V (pin 6), CD 8V (pin 7), and MOTOR 14.7V (pin 11) outputs, based on the respective output current. This prevents IC destruction by overcurrent, by limiting the current with a curve shape of "7" in the voltage-current graph. The IC is designed with margins so that current flow will be restricted and latching will be prevented even if a large current suddenly flows through a large capacitor. Note that these protection circuits are only good for preventing damage from sudden accidents. Make sure your design does not cause the protection circuit to operate continuously under transitional conditions (for instance, if output is clamped at 1VF or higher, short mode circuit operates at 1VF or lower).

Regulator ICs BA3932

(5) Reference voltage

Because output voltage is dependent on the input reference voltage, unstable input results in output wavering and degradation of ripple rejection. Take care when setting the reference voltage power supply. Note that the AUDIO output, which has a built-in reference voltage system, is not affected by the external reference voltage.

(6) Thermal protection circuit

A built-in thermal protection circuit prevents thermal damage to the IC. All outputs are switched OFF when the circuit operates, and revert to the original state when temperature drops to a certain level.

(7) Grounding

Each ground line in the application circuit must be adequately short regarding the PREGND (pin 3) and GND (pin 12) pins. Make sure to arrange the ground lines, the AUDIO system, and other outputs in a pattern that prevents electric interference.

Thermal derating curve




Fig.3

External dimensions (Units: mm)

