



Main Features

Protective Safety Features: Prevents damage to both the car battery and the appliance plugged in.

Flexible Design: Adjustable positioning whatever the vehicle.

Compact and Lightweight: Easily stored within your vehicle.

Functional: Suitable for both professional and personal use.

Spring Tension Switch: Accommodates different sized cigarette lighter sockets.

Specification

Maximum power rating 75 watts (5 mins)

Continuous power rating 56 watts (4 hours)

Surge capacity 150 watts

Standby current 0.1 amps

Nominal voltage 12 volts DC

Efficiency 90%

Output Modified sine wave

Part number RINV75

Barcode 5011274007508

Boxed outer qty. 20 x 1

The MP:75 Mininverter is and marked

Typical applications Watts

Mobile phone charger 5W – 10W

Camcorder charger 3W – 20W

Video game console 39W – 100W

Portable work light 8W – 60W

Portable stereo system 10W – 40W

Laptop computer 60W – 90W

Palm Top computer 56W – 70W

Digital camera charger 3W – 19W