

Fluke 9062 Motor & Phase Rotation Indicator

Unique phase rotation indicator with motor rotation ability



The unique Fluke 9062 provides rotary field and motor rotation indication with the benefits of contact-less detection. Purpose made for commercial and industrial environments, the Fluke 9062 provides rapid indication of 3 phase rotation using test leads supplied or can be used to determine motor rotation on synchronous and asynchronous 3 phase motors. The contact-less detection is ideal for use on motors where the shaft is not visible. The included test probes have a variable clamping range for safe contact, also in industrial sockets.



- 3 phase indication
- Indication of phase rotation
- Indication of motor rotation direction
- Contact free determination of the rotation direction of running motors

Technical Specifications	
Voltage range	Up to 440 V
Phase Display	120-440 V AC
Frequency range	2-400 Hz
Operating timer	Continuous
Environmental Specifications	
Operating temperature	0 °C to 40 °C
Operating Altitude	Up to 2000m
Humidity (Without Condensation)	15 % to 80 %
Dust/water resistance	IP 40
Safety Specifications	
Electrical Safety	EN 61010, EN 61557-7

Overvoltage category	CAT III, 300 V
Mechanical & General Specifications	
Size	124 x 61 x 27 mm
Weight	1 x 9 V
Batteries	1 x 9 V
Warranty	2 years