


RF/CABLE LOW PASS FILTERS



- For use in HFC, cable modems and termination systems
- Domestic and international versions
- Less than 1 dB inband insertion loss
- Small group delay variation
- Small surface mount package



Electrical Specifications @ 25°C

Part Number	In/Out Impedance	Cut-Off Passband Frequency	Insertion Loss (dB MAX)	Return Loss (dB MIN)	GDV (MAX)	Stopband (dB MIN)	
CX5013	75 Ω	68.0 MHz TYP	1.5 @ 1-60 MHz	15 @ 1-60 MHz	35 ns @ 60 MHz	15 @ 75 MHz	30 @ 100-500 MHz



Mechanical

Schematic

CX5013



SUGGESTED PAD LAYOUT



Weight 1.35 grams
Tape & Reel 600/reel
Tube25/tube

Dimensions: Inches
mm
Unless otherwise specified,
all tolerances are $\pm .010$
0,25

For More Information:

Pulse Worldwide Headquarters

12220 World Trade Dr.
San Diego, CA 92128
U.S.A.

www.pulseeng.com

Tel: 858 674 8100
Fax: 858 674 8262

Pulse Europe

Einsteinstrasse 1
D-71083 Herrenberg
Germany

Tel: 49 7032 7806 0
Fax: 49 7032 7806 135

Pulse China Headquarters

B402, Shenzhen Academy of
Aerospace Technology Bldg.
10th Kejinan Rd.
High-Tech Zone
Nanshan District
Shenzhen, PR China 518057
Tel: 86 755 33966678
Fax: 86 755 33966700

Pulse North China

Room 2704/2705
Super Ocean Finance Ctr.
2067 Yan An Rd. West
Shanghai 200336
China

Tel: 86 21 62787060
Fax: 86 2162786973

Pulse South Asia

135 Joo Seng Rd.
#03-02
PM Industrial Bldg.
Singapore 368363

Tel: 65 6287 8998
Fax: 65 6287 8998

Pulse North Asia

3F, No. 198
Zhongyuan Rd.
Zhongli City
Taoyuan County 320
Taiwan R. O. C.
Tel: 886 3 4356768
Fax: FRE 886 3 43568 20
Pulse: 886 3 4356823

Performance warranty of products offered on this data sheet is limited to the parameters specified. Data is subject to change without notice. Other brand and product names mentioned herein may be trademarks or registered trademarks of their respective owners.

© Copyright, 2009. Pulse Engineering, Inc. All rights reserved.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Pulse:

[CX5013T](#) [C5005T](#) [C5001T](#) [C5001](#) [C5005](#) [C5003](#) [C5003T](#) [CX5013](#)