



INPUT INTERFACE TERMINAL-TYPE OPTOCOUPLER  
RELAY 1NO (TRANSISTOR) AC/DC INPUT 24V DC  
OUTPUT MAX. 30V

General technical details:		
Type of voltage		AC/DC
Supply voltage frequency / for auxiliary and control current circuit / rated value		
• minimum	Hz	50
• maximum	Hz	60
Control supply voltage		
• at 50 Hz / at AC / rated value		
• minimum	V	24
• maximum	V	24
• at 60 Hz / at AC / rated value		
• minimum	V	24
• maximum	V	24
• for DC / rated value		
• minimum	V	24
• maximum	V	24
Number of NC contacts / for auxiliary contacts		0
Number of NO contacts / for auxiliary contacts		1
Number of changeover contacts / for auxiliary contacts		0
Switching behaviour		monostable

Reference code / according to DIN 40719 extended according to IEC 204-2 / according to IEC 750		K
Reference code / according to DIN EN 61346-2		K




#### Mechanical design:

Design of the electrical connection		screw-type terminals
Design of the electrical connection / jumper socket		No
Design of the relay operating mechanism		poled
Design of the switching function		NO contact
• guided		No
Product component / jumper socket		No
Width	mm	12.5
Height	mm	60
Depth	mm	62

#### Ambient conditions:

Protection class IP		IP20
Ambient temperature		
• during operating	°C	-25 ... +60

#### Certificates/approvals:

General Product Approval	other
  	<a href="#">Declaration of Conformity</a> <a href="#">other</a>

#### Further information:

##### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/industrial-controls/catalogs>

##### Industry Mall (Online ordering system)

<http://www.siemens.com/industrial-controls/mall>

##### CAX-Online-Generator

<http://www.siemens.com/cax>

##### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/VW/view/en/3TX7002-4AB00/all>

##### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3TX7002-4AB00](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3TX7002-4AB00)

last change:

Jun 16, 2014