


## RF amplifier for Car CD

### BH3515FV

#### ●Description

BH3515FV is a RF amplifier for Car CD player that incorporates 3 speed equalization with gain switching and operating voltage of 3 ~ 5.5V. Equalizer circuit is applied to x1 time speed, x1.5 times speed, and x2 times speed. Gain switching pin is incorporated for CD-RW

#### ●Dimension (Units : mm)



#### ●Features

- 1) Multi-read type (CD, CD-R, CD-RW)
- 2) For x1speed, x1.5speed, x2speed
- 3) Operating power supply voltage range: 3V~5.5V

SSOP-B28

#### ●Applications

CD, CD-R, CD-RW read type Car CD,  
Car CD with shock-proof function

#### ●Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Power supply voltage	Vcc	7.0	V
Power dissipation	Pd	800	mW
Operating temperature range	Topr	-40 ~ +85	°C
Storage temperature range	Tstg	-55 ~ +125	°C

Derating : 8.0mW/°C for operation above Ta=25°C


● Recommended Operating Conditions (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit
Power supply voltage	V <sub>CC</sub>	3.0	3.3	5.5	V

● Electrical characteristics (Unless otherwise noted; Ta=25°C, V<sub>CC</sub>=3.3V)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
No load consumption current	I <sub>Q</sub>	15	20	25	mA	Normal gain
Adder amp. gain 1 (at normal)	GRF1	4	6	8	dB	Normal gain
Adder amp. gain 2 (at RW)	GRF2	16	18	20	dB	Gain up
AGC operation level 1	VOPAGC1	580	700	820	mVp-p	VCC=3.3V, f=500kHz, VIN=500mVpp
AGC operation level 2	VOPAGC2	0.95	1.15	1.35	Vp-p	VCC=5V, f=500kHz, VIN=500mVpp
Frequency characteristic 1	Gf1	2	3.5	5	dB	f=144k/720k, SPDCTL=Low (x1 speed)
Frequency characteristic 2	Gf2	2	3.5	5	dB	f=216k/1.08M, SPDCTL=Hi-Z (x1.5 speed)
Frequency characteristic 3	Gf3	2	3.5	5	dB	f=288k/1.44M, SPDCTL=High (x2 speed)
RFDET detection level	VRFDET	70	100	130	mVp-p	f=500kHz, RFDET=H L

● Application Circuit



### Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document use silicon as a basic material.  
Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

#### About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.