

EasyBee Evaluation Board[™]


For research and development of IEEE 802.15.4 and ZigBee radios

Summary

One of the easiest ways to evaluate and develop products using the EasyBee IEEE 802.15.4 radio module is with the EasyBee Evaluation Board. It is a regular EasyBee radio mounted on an adapter which allows it to be plugged directly into the PICDEM-Z ZigBee Development Kit (not included, available from buy.microchip.com).


The EasyBee Evaluation Board is electrically identical to Microchip Technology's 2.4GHz daughter card and is a direct plug-in equivalent.

The EasyBee module itself is production-ready and provides a fast route to market for IEEE 802.15.4 and ZigBee products. CE / FCC qualification is in process. A range of all-weather enclosures and directional reflectors is also in development.



Features

- Integral quarter wave RF stage with matched
- Signature 'S' antenna, free-space range 120m, compact, low 'hand-effect' design
- Texas Instruments CC2420 RF Transceiver
- 12-pin 0.1" pitch connection to PICDEM-Z motherboard



Pin Descriptions		
1	Vdd	+3.3V power
2	Vss	Power ground reference
3	Resetn	Reset (active low)
4	VRegEn	Voltage regulator enable (active high)
5	FIFO	Data in FIFO
6	CSn	Chip select (active low)
7	SI	SPI serial data input
8	SO	SPI serial data output
9	SCK	SPI serial data clock
10	CCA	Clear channel assessment
11	SFD	Start of frame delimiter
12	FIFOP	FIFO near full

Ordering Information

Manufactured to ISO9001:2000



Part No	Description
EVAL-EASYBEE	IEEE 802.15.4 radio evaluation board



Developed by:

FlexiPanel Ltd 2 Marshall St, 3rd Floor, London W1F 9BB, United Kingdom email: support@flexipanel.com www.flexipanel.com



Manufactured by:

R F Solutions Ltd Unit 21, Cliffe Industrial Estate, Lewes, BN8 6JL, United Kingdom email: sales@rfsolutions.co.uk http://www.rfsolutions.co.uk Tel: +44 (0)1273 898 000

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

FlexiPanel: EVAL-EASYBEE