

Family Charger

North American Region

Download Instructions and Warranty Information

[English](#) | [Français](#) | [Español](#)

Product Detail:

Designation: Family Charger

Color: Black and Silver

Charging Current: 2 or 4 "AA" 1100mA (1 battery per bay)
1 or 2 "AA-C-D" 1100mA (1 battery per bay)
6 or 8 "AA" 550mA (2 batteries per bay)
3 or 4 "AA-C-D" 550mA (2 batteries per bay)
1 to 4 "AAA" 450mA
2 or 4 "AAA" 450 mA
6 or 8 "AAA" 450 mA
1 to 2 "9V" 30mA
Trickle Charge: "AA-C-D" 50mA
"AAA" 25mA
"9V" 2mA

Shutoff Mechanism: Delta V Detection and Timer Control
Delta V Detection 5mV per cell for "AA-AAA-C-D"
Max Timer Control 2 or 4 "AA" / 1 or 2 "AA-C-D" 3 hours
6 or 8 "AA" / 3 or 4 "AA-C-D" 6 hours
2 or 4 or 6 or 8 "AAA" 3 hours
1 to 2 "9V" 7 hours

Charger Input : DC 12V, 1A

AC Adapter Input: 100-240V AC 50/60Hz 0.35A

AC Adapter Output: DC 12V, 1A

Weight (charger): 460 grams (16.2 oz.)

Dimensions (mm): 72 x 203 x 111 (H x L x W)

Volume (cm³): 16223 (charger), 1248 (AC adapter)

Safety Features: Delta V Charging Cut Off
Short Circuit and Reverse Polarity Protection
Safety Timer to Prevent Over Charge
Bad Battery Detection



Only one battery size can be charged per charging cycle. Do not charge different battery sizes at the same time

EASY

- Drop batteries in the charger, close the lid, charging begins automatically
- Contacts auto-adjust
- LCD enables users to see charge status



VERSATILE & FAST

Charges:

- 4 AA in 3hr* (2500 mAh)
- 8 AA in 6hr (2500 mAh)
- 4 AAA in 3hr* (900 mAh)
- 8 AAA in 6hr (900 mAh)
- 4 C/D in 6hr (2500 mAh)
- 9V 175 in 7hr (175 mAh)

*Maximum of one battery per bay for shortest charging times



SAFE

- Power is only on when lid is closed
- Auto shut off feature when batteries are done



Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

©Energizer Holdings, Inc.

Contents herein do not constitute a warranty.

Energizer