

FA Series

Power supply for mast amplifiers.

APPLICATION

Individual systems and small installations. Compatible with the requirements for Digital Terrestrial TV and High Definition TV.

CHARACTERISTICS

- High performance switched power supply, which provides a high output current with less consumption.
- Modern design and small size, making it easier to install.
- "F"-type connectors.
- The 4-output FA 154 model avoids having to include an external splitter in installations with up to 4 connections.
- Protected against short-circuits.
- With an ON indicator led.



Supply voltage	195 ÷ 265 Vac
Operating temperature	0 ÷ 50 °C

12 V

MODEL	FA 152	FA 154	FA 202 S	
Reference	66106	66107	66108	
Number of outputs	2	4	2	
Frequency range	MHz	5 ÷ 862		
Through losses	dB	4	7	4
Output voltage	Vdc	24 ± 10%		12 ± 10%
Max. output current	mA	150		200
Input / output impedance	Ω	75		
Packing dimensions	mm	140 x 97 x 51		
Weight	Kg	0,26	0,36	0,26

AMB 700 + FA 152

