

REDINGTON COUNTERS, INC.
P.O. Box 608, 130 Addison Road, Windsor, CT 06095
Toll Free: (860) 688-6205 • Fax: 860/688-1591
E-Mail: Info@RedingtonCounters.com • Website: www.RedingtonCounters.com

Item # 9300-HTK, Hand Tachometer Kit



Hand Tachometer Kit

Hand Tachometer Kit includes hand tachometer, 9V battery, instruction manual, certificate of calibration, cone adapter, funnel adapter, contact adapter, master wheel, reflective tape, and carrying case.

SPECIFICATIONS

Model No.	9300-HTK
Rotation speed (non-contact)	6.0 to 99999 RPM (rev/min)
Rotation speed (contact)	6.0 to 25000 (rev/min)
Surface speed (contact)	0.6 to 2500.0 M/M (m/min) 0.7 to 2734.0 Y/M (yard/min) 23.6 to 98425 I/M (inch/min) 2.0 to 8202.1 F/M (feet/min)
Length (contact)	0.1 to 9999.9 m (meter) 0.1 to 10936 YD (yard) 0.3 32808 FT (feet)
Detection	Laser diode
Response time	1 second
Total number of revolutions	1 to 99999 REV (rev)
Accuracy	6.0 to 5999.9 RPM: $\pm 0.01\%$ and ± 1 digit 5999.9 to 99999 RPM: $\pm 0.05\%$ & ± 1 digit Surface speed, length 0.5% and ± 1 digit
Resolution	6.0 to 9999.9 RPM : 0.1 RPM 10000 to 99999 RPM : 1 RPM
Battery	9V (006P, IEC6F22, NEDA1604)
Automatic Power Cutoff	Automatically after approx. 30 second
Dimension	5.79 x 1.93 x 1.14 Inch
Dimension	147 x 49 x 29 mm
Operating Temperature	32 to 122 °F
Operating Temperature	0 to 50 °C
Weight	3.4 oz
Weight	95 gm

Weight (contact adapter)	1.8 oz
Weight (contact adapter)	50 g