



FEATURES

- 12~36V/Wide-input, plug into the ATX connector with board output
- Compact and user-friendly design for installation and maintenance
- Fan-less design for mission-critical application
- Small size for 1U or higher system to save space
- Watchdog Timer function

SPECIFICATION

Input Voltage	12V~36V
Line Regulation	11.5V~36V/input
Max Output	120Watts
Efficiency	>85% @ 12V
Input Connector	Mini-Fit 6 pin (P/N: B6902400)
Output Connector	- Mini-Fit 20 pin (P/N: B6902410) - 12V output cable (P/N: B6902420)
Dimension (WxDxH)	150 x 51 x 22.5 mm

CHARACTERISTICS

Output Voltage	Current Range	Current Range
+12V	0~8A	0~6A
+5V	0~8A	0~6A
+3.3V	0~7A	0~5.25A
+5Vsb	0~2A	0~1.5A
-12V	0~0.15A	0~0.12A

ORDERING GUIDE

- **GADIWA-3160**
120W DC/DC 12V~36V/wide-input, ATX/output, Board Type Converter

Installation Image

