

## Pilot Lights (Assembled)

Style	Operating Voltage	Standard Bezel		Flush Bezel		② Color Code
		Solder/Tab Terminal (silver contacts)	PC Board Terminal (gold contacts)	Solder/Tab Terminal (silver contacts)	PC Board Terminal (gold contacts)	
Standard Bezel (black)						
	5V DC	LB①P-②T01②	LB①P-③T01V②	LB③④P-⑤T01②	LB③④P-⑥T01V②	
						
						
						
Flush Bezel (metallic or black)	12V AC/DC	LB①P-②T03②	LB①P-③T03V②	LB③④P-⑤T03②	LB③④P-⑥T03V②	Specify the color code in place of ② in the Part Number.: A: amber G: green PW: white R: red S: blue Y: yellow
						
						
						
	24V AC/DC	LB①P-②T04②	LB①P-③T04V②	LB③④P-⑤T04②	LB③④P-⑥T04V②	

- For Standard Bezel part numbers specify:
  - bezel shape in place of ①. 1 (round), 2 (square), 3 (rectangular)
  - lens/LED color in place of ②. A (amber), G (green), PW (white), R (red), S (blue), Y (yellow)
  - lens type code in place of ③. 1 (flat), 2 (dome with round lens)
- For Flush Bezel part numbers specify:
  - lens/LED in place of ②. A (amber), G (green), PW (white), R (red), S (blue), Y (yellow)
  - bezel shape in place of ③. 6 (round), 7 (square), 8 (rectangular)
  - bezel material in place of ④. M (metallic), Blank (black)
  - lens type code in place of ⑤. 1 (flat), 2 (dome with round lens)
- Pilot lights contain an LED unit.
- See page page 511 for dimensions.
- See page page 525 for replacement LED unit.