

Battery Charge Meter



Specifications:

Terminal Resistance Range	: 0.01Ω
Meter Function	: DC Amps
Meter Range	: 0A to 5A
Coil Resistance	: 0.01Ω
External Depth	: 10mm
External Length / Height	: 47mm
External Width	: 47mm
Meter Movement FSD	: 5A
Pitch Spacing	: 18mm

Range	Ω	Item
		SD-506
DC 100uA		-
DC 1mA		
DC 20mA		
DC 500mA		
DC 1A		
DC 3A		
DC 5A		0.01Ω
DC 10A		
DC 15A		
DC 20A		
DC 30A		-
DC 50A		
DC 12V		1.3KΩ
DC 15V		2.3KΩ
DC 24V		3KΩ
DC 30V		
DC 300V		-

Part Number Table

Description	Part Number
Battery Charge Meter, 0 to 5A	SD506/0-5A

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.