

General Purpose Fuses

 French Ferrule

499-493

gl, gG

Ratings - gl-gG (Optional Blown-Fuse Indicator)

SIZE (mm x mm)	RATED IN CURRENT (A)	RATED VOLTAGE	CATALOG NUMBER		REFERENCE NUMBER		INTERRUPTING RATING (A)	STANDARD PACK/CTN.
			w/o Indicator	w/Indicator	w/o Indicator	w/Indicator		
8 x 31	0.5	400V	15009	-	P218181	-	20kA - 400V	10
	1		15011	-	C218709	-		
	2		15013	15213	Q219227	B222204		
	4		15019	15219	W222958	X222959		
	6		15023	15223	A211025	V201291		
	8		15027	15227	B213096	B211026		
	10		15031	15231	A214813	A212060		
	12		15033	15233	R216146	C213087		
	16		15035	15235	P216650	Y214105		
	20		15037	15237	F217877	J215127		
	25		15039	15239	D218710	S216147		
10 x 38	0.5	500V	16009	-	C211027	-	120kA - 500V	10
	1		16011	-	B212061	-		
	2		16013	16213	D213098	S216853		
	4		16019	16219	X213598	E217170		
	6		16023	16223	K215128	T218185		
	8		16027	16227	D217169	V219231		
	10		16031	16231	S218194	E222207		
	12		16033	16233	W219761	H200751		
	16		16035	16235	G200750	H201609		
	20		16037	16237	D211028	X211551		
	25		16039	16239	E213099	W212585		
	32		16043	16243	A214107	Z213600		
		400V					120kA - 400V	
14 x 51	1	690V	17011	-	K218716	-	80kA - 690V	10
	2		17013	17213	Y218234	C201288		
	4		17019	17219	A219765	H211032		
	6		17023	17223	H222210	G212066		
	8		17027	17227	D222965	K213104		
	10		17031	17231	L200754	H214820		
	12		17033	17233	L201812	R215640		
	16		17035	17235	A211554	X216657		
	20		17037	17237	Z212588	N217684		
	25		17039	17239	C213603	M218718		
	32		17043	17243	W216656	C219767	120kA - 500V	
	40	500V	17047	17247	X218198	F222967	120kA - 500V	
	50	400V	17051	17251	Z219235	D201289	120kA - 400V	
22 x 58	4	690V	18013	-	F219241	-	80kA - 690V	10
	6		18019	18219	H219772	Q211039		
	8		18023	18223	P222216	P212073		
	10		18027	18227	L222972	R213110		
	12		18031	18231	T200761	N214119		
	16		18033	18233	J201304	Y215140		
	20		18035	18235	S201818	D216157		
	25		18037	18237	P211038	R217181		
	32		18039	18239	N212072	F218206		
	40		18043	18243	F212584	H219243		
	50		18047	18247	J213809	R222218		
	63		18051	18251	P214626	W200763		
	80		18055	18255	Y215646	V201820		
	100		18059	18259	Q217180	K211563		
	125	500V	18063	18263	E218205	H212596	120kA - 500V	
		400V	18065	18265	J219773	L213611	120kA - 400V	


Blown-Fuse Indicator



BEFORE



AFTER



Dimensions

FUSE SIZE	A	B	C
8 x 31	8.5	31.5	6.3
10 x 38	10.3	38	10.5
14 x 51	14.3	51	13.8
22 x 58	22.2	58	16.2

Ferraz Shawmut