


## Foot Candle/Lux Meter



**Accurate light level measurements**

*Plus analog output for capturing readings to a recorder*

### Features:

- Accurately displays light level in terms of Fc or Lux over three ranges:  
Fc (0-200, 0-2000 and 0-5000Fc) and  
Lux (0-2000, 0-20000, 0-50000Lux)
- Resolution of 0.1Fc or 1Lux  
with 5% accuracy
- Select fast (1 second) or slow  
(2 seconds) response
- Monitor light levels using outputs;  
1mV per count analog output for  
capturing readings to a recorder
- Utilizes precision photo diode and color  
correction filter; Cosine/color corrected
- Dimensions: 6.4 x 2.8 x 1.2" (163 x 70 x 30mm);  
Weight: 7.8oz (220g)
- Complete with 9V battery



### Ordering Information:

401025.....Foot Candle/Lux Meter  
401025-NIST .....401025 with NIST Certificate  
409996.....Vinyl Pouch Carrying Case

