

AE-TS56-16Am



DIP40/TSOP56 specialized adapter for FLASH memory.

Device package dimensions: 14 x 20 mm, 0.5 mm pitch.

Click the programmer model below to get an appropriate list of the devices supported by the adapter:

- [ChipProg+](#)
- [ChipProg-40](#)
- [ChipProg-48, ChipProg-G4](#)

Adapter Wiring Diagram:

DIP-40	TSOP-56	U1, 74AHC573	U2, 74AHC573	C1, 150pF	C2, 0.1uF
1	29				
2	28				
3		11	11	1	
4	14				
5	56				
6	55				
7	13				
8	17				
9	16				
10	20				
11	21				
12	22				
13	23				
14	24				

15	25				
16	26				
17	31				
18	27				
19	30				
20	33.52	1, 10	1, 10	2	2
21	32				
22	34				
23	35	2			
24	36		2		
25	37	3			
26	38		3		
27	39	4			
28	40		4		
29	41	5			
30	42		5		
31	44	6			
32	45		6		
33	46	7			
34	47		7		
35	48	8			
36	49		8		
37	50	9			
38	51		9		
39	53				
40	43	20	20		1
	1		12		
	2		13		
	3	12			
	4	13			
	5	14			
	6	15			
	7	16			
	8	17			
	9	18			
	10	19			
	11		16		
	12		15		
	15		14		
	18		17		
	19		18		

	54		19		
--	----	--	----	--	--