



Time-Delay, Current-Limiting

250 Volts, 3 $\frac{3}{10}$ -200 Amps

HAC-R




Dimensional Data

3 $\frac{3}{10}$ A to 30A

35A to 60A



70A to 100A



125A to 200A

General Information:

- A general purpose 250 Volt AC time-delay cartridge fuse for residential and light-duty motor protection.
- The HAC-R fuse has the same physical dimensions as the Class R fuses.

Catalog Symbol: HAC-R

Time-Delay, Current-Limiting

Ampere Rating: 3 $\frac{3}{10}$ to 200 Amperes

Voltage Rating: 250 Volts (or less)

Agency Approvals:

UL Listed, UL248-12, 250 VAC/125 VDC,

Guide JDDZ, File E4273

CSA Certified, C22.2 No. 248.12,

250 VAC, Class 1422-02, File 53787

Carton Quantity and Weight

Electrical Ratings (Catalog Symbol and Amperes)

250 Volts

HAC-R-3 $\frac{3}{10}$	HAC-R-25	HAC-R-60
HAC-R-5	HAC-R-30	HAC-R-70
HAC-R-6 $\frac{1}{4}$	HAC-R-35	HAC-R-80
HAC-R-10	HAC-R-40	HAC-R-100
HAC-R-15	HAC-R-45	HAC-R-125
HAC-R-20	HAC-R-50	HAC-R-200

Catalog Number	Carton Specifications							
	Shelf Pack				Master Pack			
	Qty.	Size	Cu. In.	Wt. (Lbs.)	Qty.	Size	Cu. In.	Wt. (Lbs.)
HAC-R-3 $\frac{3}{10}$ HAC-R-5 HAC-R-6 $\frac{1}{4}$ HAC-R-10 HAC-R-15 HAC-R-20 HAC-R-25 HAC-R-30	10	3" × 2 $\frac{1}{4}$ " × 1 $\frac{1}{4}$ "	8.4	0.4	100	6 $\frac{1}{2}$ " × 4 $\frac{5}{8}$ " × 3"	90.2	5.5
HAC-R-35 HAC-R-40 HAC-R-45 HAC-R-50 HAC-R-60	10	4 $\frac{1}{2}$ " × 3 $\frac{1}{4}$ " × 3 $\frac{3}{4}$ "	51.8	1.0	100	9 $\frac{1}{4}$ " × 6 $\frac{3}{4}$ " × 4 $\frac{1}{4}$ "	265.4	12.5
HAC-R-70 HAC-R-80 HAC-R-100	5	5 $\frac{3}{4}$ " × 1 $\frac{1}{4}$ " × 6 $\frac{3}{8}$ "	45.8	1.5	—	—	—	—
HAC-R-125 HAC-R-200	1	7 $\frac{1}{2}$ " × 2" × 2"	30.0	0.874	—	—	—	—

The only controlled copy of this BIF document is the electronic read-only version located on the Bussmann Network Drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Bussmann reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Bussmann also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Eaton:

[HAC-R-10](#) [HAC-R-100](#) [HAC-R-20](#) [HAC-R-40](#) [HAC-R-5](#) [HAC-R-80](#)