

FU8230

Secvest 2WAY Wireless Indoor Sounder

The Secvest wireless indoor sounder is an optional accessory for the Secvest 2WAY. As a purely acoustic signalling unit, it supports the wireless outdoor siren and the alarm panel of the Secvest 2WAY with a 90 dB tone. The sounder and the alarm panel communicate on 868.6625 MHz, a radio frequency that has been specially reserved for security purposes. The wireless indoor sounder can be powered via a batteries or power supply. When using batteries, the service life is approx. 2 years. A weakening battery is indicated at the alarm panel of the Secvest 2WAY and a red LED on the sounder.



Product highlights:

- For acoustic support of the Secvest and the wireless outside siren
 - Robust injection molded ABS housing
 - Loud signalling unit
 - DC power supply for use without batteries (optional)
 -
-

FU8230

Secvest 2WAY Wireless Indoor Sounder

Technical Data		
Duplex antenna technology	868.6625 MHz	DC network connection for operating without a battery
Battery service life	More than 2 years	LED indication for weak battery and teaching-in in UVM
Acoustic pressure	90 dB(A) @ 1 m	
Simplex function for multi-siren systems	Optional	
		Dimensions (WxHxD) 122x208x60 mm