

SLx Gold Signal Amplifiers



The SLx range of Gold Signal aerial amplifiers are designed to improve picture and sound quality by amplifying weak UHF, VHF, DAB and FM radio signals. Can also be used to distribute VCR, Digital TV and Sky/Sky+ signals without loss of reception.

- Unlike standard boosters SLx Gold's flat gain response across full frequency spectrum ensures optimum digital reception
- Dedicated inputs for UHF and FM/DAB
- Side mounted terminals provide easy cable management
- Infra-red by-pass for digilinks
- Surge Protection
- Full VHF compatability for TV and FM/DAB including Ireland
- Integrated by-pass to control Digital satellite receivers from a second TV

	SLx2	SLx4	SLx6	SLx8
Inputs	2	2	2	2
Outputs	2	4	6	8
Frequency Range (UHF MHz)	470-862	470-862	470-862	470-862
Frequency Range (VHF MHz)	47-300	47-300	47-300	47-300
Gain	12dB	8dB	8dB	8dB
Noise Figure	<4dB	<4dB	<4dB	<4dB
Isolation Loss	22dB	22dB	22dB	22dB
Weight	440g	517g	740g	750g
Dimensions (WxDxH)mm	172x75x46	207x75x46	285x85x50	285x85x50

447536.428071

Model	Order Code	Price Each
SLx2	127-1331	
SLx4	127-1332	
SLx6	127-1333	
SLx8	127-1334	
SLx4 F Type	127-1336	
SLx6 F Type	127-1338	
SLx8 F Type	127-1339	